

REPLACEABLE ELECTRICAL PARTS

PARTS ORDERING INFORMATION

Replacement parts are available from or through your local Tektronix, Inc. Field Office or representative.

Changes to Tektronix instruments are sometimes made to accommodate improved components as they become available, and to give you the benefit of the latest circuit improvements developed in our engineering department. It is therefore important, when ordering parts, to include the following information in your order: Part number, instrument type or number, serial number, and modification number if applicable.

If a part you have ordered has been replaced with a new or improved part, your local Tektronix, Inc. Field Office or representative will contact you concerning any change in part number.

Change information, if any, is located at the rear of this manual.

SPECIAL NOTES AND SYMBOLS

X000 Part first added at this serial number
00X Part removed after this serial number

ITEM NAME

In the Parts List, an Item Name is separated from the description by a colon (:). Because of space limitations, an Item Name may sometimes appear as incomplete. For further Item Name identification, the U.S. Federal Cataloging Handbook H6-1 can be utilized where possible.

ABBREVIATIONS

ACTR	ACTUATOR	PLSTC	PLASTIC
ASSY	ASSEMBLY	QTZ	QUARTZ
CAP	CAPACITOR	RECP	RECEPTACLE
CER	CERAMIC	RES	RESISTOR
CKT	CIRCUIT	RF	RADIO FREQUENCY
COMP	COMPOSITION	SEL	SELECTED
CONN	CONNECTOR	SEMICOND	SEMICONDUCTOR
ELCTLT	ELECTROLYTIC	SENS	SENSITIVE
ELEC	ELECTRICAL	VAR	VARIABLE
INCAND	INCANDESCENT	WW	WIREWOUND
LED	LIGHT EMITTING DIODE	XFMR	TRANSFORMER
NONWIR	NON WIREWOUND	XTAL	CRYSTAL

CROSS INDEX—MFR. CODE NUMBER TO MANUFACTURER

Mfr. Code	Manufacturer	Address	City, State, Zip
0000A	LEMO USA	2015 SECOND ST.	BERKELEY, CA 94710
00779	AMP, INC.	P O BOX 3608	HARRISBURG, PA 17105
00853	SANGAMO ELECTRIC CO., S. CAROLINA DIV.	P O BOX 128	PICKENS, SC 29671
01121	ALLEN-BRADLEY COMPANY	1201 2ND STREET SOUTH	MILWAUKEE, WI 53204
01295	TEXAS INSTRUMENTS, INC., SEMICONDUCTOR GROUP	P O BOX 5012, 13500 N CENTRAL EXPRESSWAY	DALLAS, TX 75222
02114	FERROXCUBE CORPORATION	PO BOX 359, MARION ROAD	SAUGERTIES, NY 12477
03888	KDI PYROFILM CORPORATION	60 S JEFFERSON ROAD	WHIPPANY, NJ 07981
04222	AVX CERAMICS, DIVISION OF AVX CORP.	P O BOX 867, 19TH AVE. SOUTH	MYRTLE BEACH, SC 29577
04713	MOTOROLA, INC., SEMICONDUCTOR PROD. DIV.	5005 E MCDOWELL RD, PO BOX 20923	PHOENIX, AZ 85036
05397	UNION CARBIDE CORPORATION, MATERIALS SYSTEMS DIVISION	11901 MADISON AVENUE	CLEVELAND, OH 44101
05587	COUCH, S.H., DIVISION, ESB, INC.	36 RIVER STREET	BOSTON, MA 02126
07263	FAIRCHILD SEMICONDUCTOR, A DIV. OF FAIRCHILD CAMERA AND INSTRUMENT CORP.	464 ELLIS STREET	MOUNTAIN VIEW, CA 94042
08806	GENERAL ELECTRIC CO., MINIATURE LAMP PRODUCTS DEPARTMENT	NELA PARK	CLEVELAND, OH 44112
12697	CLAROSTAT MFG. CO., INC.	LOWER WASHINGTON STREET	DOVER, NH 03820
12969	UNITRODE CORPORATION	580 PLEASANT STREET	WATERTOWN, MA 02172
13511	AMPHENOL CADRE DIV., BUNKER RAMO CORP.		LOS GATOS, CA 95030
14193	CAL-R, INC.	1601 OLYMPIC BLVD.	SANTA MONICA, CA 90404
14298	AMERICAN COMPONENTS, INC., AN INSILCO COMPANY	8TH AVE. AT HARRY STREET	CONSHOHOCKEN, PA 19428
14752	ELECTRO CUBE INC.	1710 S. DEL MAR AVE.	SAN GABRIEL, CA 91776
15454	RODAN INDUSTRIES, INC.	2905 BLUE STAR ST.	ANAHEIM, CA 92806
16546	U.S. CAPACITOR CORP/CENTRALAB ELECTRONICS DIV.	4561 COLORADO	LOS ANGELES, CA 90039
18583	CURTIS INSTRUMENTS, INC.	200 KISCO AVE.	MOUNT KISCO, NY 10549
24546	CORNING GLASS WORKS, ELECTRONIC COMPONENTS DIVISION	550 HIGH STREET	BRADFORD, PA 16701
24931	SPECIALTY CONNECTOR CO., INC.	3560 MADISON AVE.	INDIANAPOLIS, IN 46227
25088	SIEMENS CORP.	186 WOOD AVE. S	ISELIN, NJ 08830
27014	NATIONAL SEMICONDUCTOR CORP.	2900 SEMICONDUCTOR DR.	SANTA CLARA, CA 95051
32293	INTERSIL, INC.	10900 N. TANTAU AVE.	CUPERTINO, CA 95014
32997	BOURNS, INC., TRIMPOT PRODUCTS DIV.	1200 COLUMBIA AVE.	RIVERSIDE, CA 92507
50157	MIDWEST COMPONENTS INC.	P. O. BOX 787	
53184	XCITON CORPORATION	1981 PORT CITY BLVD.	MUSKEGON, MI 49443
53944	ELT INC., GLOW LITE DIVISION	5 HEMLOCK STREET	LATHAM, NY 12110
56289	SPRAGUE ELECTRIC CO.	BOX 698	PAULS VALLEY, OK 73075
71400	BUSSMAN MFG., DIVISION OF MCGRAW-EDISON CO.	2536 W. UNIVERSITY ST.	NORTH ADAMS, MA 01247
71590	CENTRALAB ELECTRONICS, DIV. OF GLOBE-UNION, INC.		ST. LOUIS, MO 63107
71744	CHICAGO MINIATURE LAMP WORKS	P O BOX 858	FORT DODGE, IA 50501
72982	ERIE TECHNOLOGICAL PRODUCTS, INC.	4433 RAVENSWOOD AVE.	CHICAGO, IL 60640
73138	BECKMAN INSTRUMENTS, INC., HELIPOT DIV.	644 W. 12TH ST.	ERIE, PA 16512
73899	JFD ELECTRONICS COMPONENTS CORP.	2500 HARBOR BLVD.	FULLERTON, CA 92634
74970	JOHNSON, E. F., CO.	PINETREE ROAD	OXFORD, NC 27565
75042	TRW ELECTRONIC COMPONENTS, IRC FIXED RESISTORS, PHILADELPHIA DIVISION	299 10TH AVE. S. W.	WASECA, MN 56093
76493	BELL INDUSTRIES, INC., MILLER, J. W., DIV.	401 N. BROAD ST.	PHILADELPHIA, PA 19108
77342	AMF INC., POTTER AND BRUMFIELD DIV.	19070 REYES AVE., P O BOX 5825	COMPTON, CA 90224
78488	STACKPOLE CARBON CO.	200 RICHLAND CREEK DRIVE	PRINCETON, IN 47671
80009	TEKTRONIX, INC.		ST. MARYS, PA 15857
80031	ELECTRA-MIDLAND CORP., MEPCO DIV.	P O BOX 500	BEAVERTON, OR 97077
80740	BECKMAN INSTRUMENTS, INC.	22 COLUMBIA ROAD	MORRISTOWN, NJ 07960
81073	GRAYHILL, INC.	2500 HARBOR BLVD.	FULLERTON, CA 92634
82104	STANDARD GRIGSBY CO., DIV. OF SUN CHEMICAL CORPORATION	561 HILLGROVE AVE., PO BOX 373	LA GRANGE, IL 60525
82389	SWITCHCRAFT, INC.	920 RATHBONE AVENUE	AURORA, IL 60507
84411	TRW ELECTRONIC COMPONENTS, TRW CAPACITORS	5555 N. ELSTON AVE.	CHICAGO, IL 60630
90201	MALLORY CAPACITOR CO., DIV. OF P. R. MALLORY AND CO., INC.	112 W. FIRST ST.	OGALLALA, NE 69153
91418	RADIO MATERIALS COMPANY, DIV. OF P.R. MALLORY AND COMPANY, INC.	3029 E. WASHINGTON STREET P. O. BOX 372	INDIANAPOLIS, IN 46206
		4242 W BRYN MAWR	CHICAGO, IL 60646

CROSS INDEX—MFR. CODE NUMBER TO MANUFACTURER

Mfr. Code	Manufacturer	Address	City, State, Zip
91637	DALE ELECTRONICS, INC.	P. O. BOX 609	COLUMBUS, NE 68601
91836	KINGS ELECTRONICS CO., INC.	40 MARBLEDALE ROAD	TUCKAHOE, NY 10707
93410	ESSEX INTERNATIONAL, INC., CONTROLS DIV. LEXINGTON PLANT	P. O. BOX 1007	MANSFIELD, OH 44903
93958	REPUBLIC ELECTRONICS CORPORATION	176 E 7TH STREET	PATERSON, NJ 07524
95275	VITRAMON, INC.	P O BOX 544	BRIDGEPORT, CT 06601
99699	DEUTSCH RELAYS, INC.	65 DALY ROAD	EAST NORTHPORT, LI, NY 11731

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
A1(2)	670-1514-00	B010100	B166669	CKT BOARD ASSY:LIGHT BLOCK(485,485-1)	80009	670-1514-00
A1(2)	670-1514-01	B166700		CKT BOARD ASSY:LIGHT BLOCK(485,485-1)	80009	670-1514-01
A2(2)	670-2599-00	B010100	B166669	CKT BOARD ASSY:LIGHT BLOCK(485-2)	80009	670-1599-00
A2(2)	670-2599-01	B166700		CKT BOARD ASSY:LIGHT BLOCK(485-2)	80009	670-2599-01
A3(2)	670-1512-00	B010100	B079999	CKT BOARD ASSY:HI Z(485,485-1)	80009	670-1512-00
A3(2)	670-1512-01	B080000	B155789	CKT BOARD ASSY:HI Z(485,485-1)	80009	670-1512-01
A3(2)	670-1512-02	B155790	B159999	CKT BOARD ASSY:HI Z(485,485-1)	80009	670-1512-02
A3(2)	670-1512-04	B160000	B166699	CKT BOARD ASSY:HI Z(485,485-1)	80009	670-1512-04
A3(2)	670-1512-05	B166700	B166999	CKT BOARD ASSY:HI Z(485,485-1)	80009	670-1512-05
A3(2)	670-1512-06	B167000		CKT BOARD ASSY:HI Z(485,485-1)	80009	670-1512-06
A4(2)	670-2564-00	B010100	B159999	CKT BOARD ASSY:LOW Z CONTROL(485-2)	80009	670-2564-00
A4(2)	670-2564-02	B160000	B166699	CKT BOARD ASSY:LOW Z CONTROL(485-2)	80009	670-2564-02
A4(2)	670-2564-03	B167000		CKT BOARD ASSY:LOW Z CONTROL(485-2)	80009	670-2564-03
A5(2)	670-1513-00			CKT BOARD ASSY:50 OHM ATTEN(485,485-1)	80009	670-1513-00
A6(2)	670-2598-00			CKT BOARD ASSY:50 OHM ATTEN(485-2)	80009	670-2598-00
A7	670-1662-00	B010100	B159999	CKT BOARD ASSY:VERTICAL	80009	670-1662-00
A7	670-1662-01	B160000		CKT BOARD ASSY:VERTICAL	80009	670-1662-01
A8	670-1660-00			CKT BOARD ASSY:A TRIGGER(485)	80009	670-1660-00
A9	670-2699-00			CKT BOARD ASSY:A TRIGGER(485-1,485-2)	80009	670-2699-00
A10	670-1663-00	B010100	B129999	CKT BOARD ASSY:SWEEP GEN	80009	670-1663-00
A10	670-1663-01	B130000		CKT BOARD ASSY:SWEEP GEN	80009	670-1663-01
A11	670-1666-00			CKT BOARD ASSY:HORIZ AMPL	80009	670-1666-00
A12	670-1664-00	B010100	B049999	CKT BOARD ASSY:TIMING SWEEP	80009	670-1664-00
A12	670-1664-01	B050000	B154999	CKT BOARD ASSY:TIMING SWEEP	80009	670-1664-01
A12	670-1664-02	B155000		CKT BOARD ASSY:TIMING SWEEP	80009	670-1664-02
A13	670-1665-00			CKT BOARD ASSY:POWER	80009	670-1665-00
A14	670-1659-00			CKT BOARD ASSY:INVERTER	80009	670-1659-00
A15	670-1661-00			CKT BOARD ASSY:TRANSFORMER	80009	670-1661-00
A16	670-2352-00			CKT BOARD ASSY:LINE FILTER	80009	670-2352-00
B1480	147-0035-00			MOTOR,DC:BRUSHLESS,10-15VDC,145MA	25088	1AD3001-0A
C1	283-0204-00			CAP.,FXD,CER DI:0.01UF,20%,50V	72982	8121N061Z5U0103M
C2	283-0204-00			CAP.,FXD,CER DI:0.01UF,20%,50V	72982	8121N061Z5U0103M
C3	283-0204-00			CAP.,FXD,CER DI:0.01UF,20%,50V	72982	8121N061Z5U0103M
C4	283-0204-00	B010100	B155789X	CAP.,FXD,CER DI:0.01UF,20%,50V (C3, 485,485-1 ONLY)	72982	8121N061Z5U0103M
C10	283-0204-00			CAP.,FXD,CER DI:0.01UF,20%,50V (C10, 485,485-1 ONLY)	72982	8121N061Z5U0103M
C11	281-0627-00	XB160000		CAP.,FXD,CER DI:1PF,+/-0.25PF,500V	72982	301-000COK0109C
C12	281-0138-00			CAP.,VAR,PLSTC:0.4-1.2PF,600V (C12, 485,485-1 ONLY)	74970	273-0051-001
C16	285-0816-03			CAP.,FXD,PLSTC:0.019UF,10%,600V (C16, 485,485-1 ONLY)	80009	285-0816-03
C17	281-0580-00	B010100	B019999X	CAP.,FXD,CER DI:470PF,10%,500V (C17, 485,485-1 ONLY)	04222	7001-1374
C18	283-0181-00			CAP.,FXD,CER DI:1.8PF,10%,100V (C18, 485,485-1 ONLY)	72982	8101B121COK0189B
C20 C22	307-1014-01	B010100	B143499	ATTENUATOR,FXD:100X (485,485-1 ONLY)	80009	307-1014-01
C20 C22	307-1014-03	B143500		ATTENUATOR,FXD:100X (485,485-1 ONLY)	80009	307-1014-03
C24	307-1013-01	B010100	B143499	ATTENUATOR,FXD:10X (C24 & C26 FURN AS A UNIT. 485,485-1 ONLY)	80009	307-1013-01
C24	307-1013-03	B143500		ATTENUATOR,FXD:10X (C24 & C26 FURN AS A UNIT. 485,485-1 ONLY)	80009	307-1013-03

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
C25	281-0615-00			CAP., FXD, CER DI: 3.9PF, +/-0.5PF, 200V (C25, 485, 485-1 ONLY)	72982	374001C0J0399D
C26	307-1013-01	B010100	B143499	ATTENUATOR, FXD: 10X (C26 & C24 FURN AS A UNIT. 485, 485-1 ONLY)	80009	307-1013-01
C26	307-1013-03	B143500		ATTENUATOR, FXD: 10X (C26 & C24 FURN AS A UNIT. 485, 485-1 ONLY)	80009	307-1013-03
C28	281-0722-00			CAP., FXD, CER DI: 7.5PF, +/-1PF, 500V (C28, 485, 485-1 ONLY)	72982	374005C0H0759B
C29	283-0222-00			CAP., FXD, CER DI: 120PF, 20%, 50V (C29, 485, 485-1 ONLY)	93958	51720-1
C33	283-0141-00			CAP., FXD, CER DI: 200PF, 10%, 600V (C33, 485, 485-1 ONLY)	14193	PD-0321-201K
C34	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V (C34, 485, 485-1 ONLY)	72982	8121N061Z5U0103M
C37	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V (C37, 485, 485-1 ONLY)	72982	8121N061Z5U0103M
C38	290-0134-00	B010100	B019999	CAP., FXD, ELCTLT: 22UF, 20%, 15V (C38, 485, 485-1 ONLY)	56289	150D226X0015B2
C38	290-0140-00	B020000		CAP., FXD, ELCTLT: 120UF, 20%, 10V (C38, 485, 485-1 ONLY)	05397	T110C127M010AS
C41	283-0203-00			CAP., FXD, CER DI: 0.47UF, 20%, 50V (C41, 485, 485-1 ONLY)	72982	8131N075 E474M
C43	283-0160-00			CAP., FXD, CER DI: 1.5PF, 10%, 50V (C43, 485, 485-1 ONLY)	72982	8101A058C0K159B
C44	283-0204-00	XB020433	B020435	CAP., FXD, CER DI: 0.01UF, 20%, 50V (C44, 485, 485-1 ONLY)	72982	8121N061Z5U0103M
C44	283-0191-00	B020436		CAP., FXD, CER DI: 0.022UF, 20%, 50V (C44, 485, 485-1 ONLY)	72982	8121N075Z5U0223M
C45	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V (C45, 485, 485-1 ONLY)	72982	8121N061Z5U0103M
C46	281-0160-00			CAP., VAR, CER DI: 7-25PF, 350V (C46, 485, 485-1 ONLY)	72982	538-011B7-25
C47	283-0070-00	B010100	B020432X	CAP., FXD, CER DI: 30PF, 10%, 50V (C47, 485, 485-1 ONLY)	72982	8121-060C0G0300K
C48	283-0065-00			CAP., FXD, CER DI: 0.001UF, 5%, 100V (C48, 485, 485-1 ONLY)	72982	805-518-25D0102J
C49	283-0330-00	B010100	B020432	CAP., FXD, CER DI: 100PF, 5%, 50V (C49, 485, 485-1 ONLY)	72982	8111N068C0G0101J
C49	283-0156-00	B020433		CAP., FXD, CER DI: 1000PF, +100-0%, 200V (C49, 485, 485-1 ONLY)	72982	8111A208Z5U0102Z
C50	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V (C50, 485, 485-1 ONLY)	72982	8121N061Z5U0103M
C51	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V (C51, 485, 485-1 ONLY)	72982	8121N061Z5U0103M
C52	283-0203-00			CAP., FXD, CER DI: 0.47UF, 20%, 50V (C52, 485, 485-1 ONLY)	72982	8131N075 E474M
C55	281-0091-00			CAP., VAR, CER DI: 2-8PF (C55, 485, 485-1 ONLY)	72982	538-011 A2-8
C57	283-0158-00			CAP., FXD, CER DI: 1PF, 10%, 50V (C57, 485, 485-1 ONLY)	72982	8101B057C0K0109B
C59	283-0203-00			CAP., FXD, CER DI: 0.47UF, 20%, 50V (C59, 485, 485-1 ONLY)	72982	8131N075 E474M
C60	283-0204-00	XB030000		CAP., FXD, CER DI: 0.01UF, 20%, 50V	72982	8121N061Z5U0103M
C61	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V (C61, 485, 485-1 ONLY)	56289	196D226X0015KA1
C62	283-0010-00			CAP., FXD, CER DI: 0.05UF, +100-20%, 50V (C62, 485, 485-1 ONLY)	56289	273C20

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
C67	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V (C67, 485, 485-1 ONLY)	72982	8121N061Z5U0103M
C68	283-0260-00			CAP., FXD, CER DI: 5.6PF, 5%, 200V (C68, 485, 485-1 ONLY)	72982	8111B200C0G569C
C69	283-0140-00			CAP., FXD, CER DI: 4.7PF, 5%, 50V (C69, 485, 485-1 ONLY)	72982	8101E003A479C
C70	281-0645-00	B010100	B020432	CAP., FXD, CER DI: 8.2PF, +/-0.25PF, 500V (C70, 485, 485-1 ONLY)	72982	374005C0H0829C
C70	281-0161-00	B020433		CAP., VAR, CER DI: 5-15PF, 350V (C70, 485, 485-1 ONLY)	72982	518-000A5-15
C72	283-0203-00			CAP., FXD, CER DI: 0.47UF, 20%, 50V (C72, 485, 485-1 ONLY)	72982	8131N075 E474M
C73	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V (C73, 485, 485-1 ONLY)	56289	196D226X0015KA1
C74	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V (C74, 485, 485-1 ONLY)	72982	8121N061Z5U0103M
C76	281-0651-00			CAP., FXD, CER DI: 47PF, 5%, 200V (C76, 485, 485-1 ONLY)	72982	374001T2H0470J
C77	281-0651-00	B010100	B020432	CAP., FXD, CER DI: 47PF, 5%, 200V (C77, 485, 485-1 ONLY)	72982	374001T2H0470J
C77	281-0634-00	B020433		CAP., FXD, CER DI: 10PF, +/-0.25PF, 500V (C77, 485, 485-1 ONLY)	72982	374011C0G100C
C82	283-0111-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V (C82, 485, 485-1 ONLY)	72982	8121-N088Z5U104M
C84	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V	72982	8121N061Z5U0103M
C86	290-0536-00	B010100	B109999	CAP., FXD, ELCTLT: 10UF, 20%, 25V	90201	TDC106M025FL
C86	290-0527-00	B110000		CAP., FXD, ELCTLT: 15UF, 20%, 20V	90201	TDC156M020FL
C87	283-0203-00			CAP., FXD, CER DI: 0.47UF, 20%, 50V	72982	8131N075 E474M
C92	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V (C92, 485, 485-1 ONLY)	72982	8121N061Z5U0103M
C93	290-0524-00			CAP., FXD, ELCTLT: 4.7UF, 20%, 10V	90201	TDC475M010EL
C94	283-0198-00			CAP., FXD, CER DI: 0.22UF, 20%, 50V (C94, 485, 485-1 ONLY)	72982	8121N083Z5U0224M
C95	283-0111-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8121-N088Z5U104M
C101	283-0278-00			CAP., FXD, CER DI: 2.2UF, 20%, 100V	72982	8150-M100Z5U225M
C102	283-0277-00			CAP., FXD, CER DI: 0.01UF, 10%, 100V	72982	CC1505W5R0103K
C104	283-0156-00			CAP., FXD, CER DI: 1000PF, +100-0%, 200V	72982	8111A208Z5U0102Z
C105	283-0277-00			CAP., FXD, CER DI: 0.01UF, 10%, 100V	72982	CC1505W5R0103K
C201	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C204	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C211	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C214	281-0123-00			CAP., VAR, CER DI: 5-25PF, 100V (PART OF CIRCUIT BOARD)	72982	518-000A5-25
C215	-----			(PART OF CIRCUIT BOARD)		
C216	-----			(PART OF CIRCUIT BOARD)		
C217	283-0191-00			CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C223	283-0191-00			CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C240	281-0151-00			CAP., VAR, CER DI: 1-3PF, 100V	72982	518-600A1-3
C242	290-0526-00			CAP., FXD, ELCTLT: 6.8UF, 20%, 6V (PART OF CIRCUIT BOARD)	90201	TDC685M006EL
C244	-----			(PART OF CIRCUIT BOARD)		
C247	-----			(PART OF CIRCUIT BOARD)		
C253	283-0198-00			CAP., FXD, CER DI: 0.22UF, 20%, 50V	72982	8121N083Z5U0224M
C254	283-0238-00			CAP., FXD, CER DI: 0.01UF, 10%, 50V	72982	8121N075X7R0103K
C262	290-0524-00			CAP., FXD, ELCTLT: 4.7UF, 20%, 10V	90201	TDC475M010EL
C266	290-0524-00			CAP., FXD, ELCTLT: 4.7UF, 20%, 10V	90201	TDC475M010EL
C272	283-0023-00			CAP., FXD, CER DI: 0.1UF, +80-20%, 12V	91418	MX0104Z1205R5

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
C282	283-0191-00			CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C290	283-0191-00			CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C310	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C311	-----			(PART OF CIRCUIT BOARD)		
C312	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C314	283-0191-00			CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C315	281-0123-00			CAP., VAR, CER DI: 5-25PF, 100V	72982	518-000A5-25
C316	-----			(PART OF CIRCUIT BOARD)		
C317	283-0191-00			CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C319	283-0191-00			CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C323	283-0191-00			CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C333	283-0191-00			CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C334	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C340	281-0151-00			CAP., VAR, CER DI: 1-3PF, 100V	72982	518-600A1-3
C342	290-0526-00			CAP., FXD, ELCTLT: 6.8UF, 20%, 6V	90201	TDC685M006EL
C344	-----			(PART OF CIRCUIT BOARD)		
C347	-----			(PART OF CIRCUIT BOARD)		
C356	283-0198-00			CAP., FXD, CER DI: 0.22UF, 20%, 50V	72982	8121N083Z5U0224M
C357	283-0238-00			CAP., FXD, CER DI: 0.01UF, 10%, 50V	72982	8121N075X7R0103K
C362	290-0524-00			CAP., FXD, ELCTLT: 4.7UF, 20%, 10V	90201	TDC475M010EL
C366	290-0524-00			CAP., FXD, ELCTLT: 4.7UF, 20%, 10V	90201	TDC475M010EL
C372	283-0023-00			CAP., FXD, CER DI: 0.1UF, +80-20%, 12V	91418	MX0104Z1205R5
C382	283-0191-00			CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C401	-----			(PART OF CIRCUIT BOARD)		
C403	290-0512-00	B010100	B109999X	CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C405	-----			(PART OF CIRCUIT BOARD)		
C407	283-0154-00			CAP., FXD, CER DI: 22PF, 5%, 50V	72982	8111B061COG220J
C419	290-0527-00			CAP., FXD, ELCTLT: 15UF, 20%, 20V	90201	TDC156M020FL
C421	-----			(PART OF CIRCUIT BOARD)		
C423	290-0512-00	B010100	B109999X	CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C425	-----			(PART OF CIRCUIT BOARD)		
C427	283-0154-00			CAP., FXD, CER DI: 22PF, 5%, 50V	72982	8111B061COG220J
C428	283-0191-00	B010100	B039999X	CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C430	283-0000-00			CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C458	281-0613-00			CAP., FXD, CER DI: 10PF, +/-1PF, 200V	72982	374001COG100F
C466	281-0629-00			CAP., FXD, CER DI: 33PF, 5%, 600V	72982	308-000COG0330J
C502	-----			(PART OF CIRCUIT BOARD)		
C503	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C505	-----			(PART OF CIRCUIT BOARD)		
C512	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C518	283-0191-00			CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C521	-----			(PART OF CIRCUIT BOARD)		
C523	283-0191-00	B010100	B109999X	CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C525	-----			(PART OF CIRCUIT BOARD)		
C532	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C538	283-0191-00			CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C542	283-0191-00			CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C543	283-0156-00			CAP., FXD, CER DI: 1000PF, +100-0%, 200V	72982	8111A208Z5U0102Z
C545	281-0700-00			CAP., FXD, CER DI: 3.3PF, 10%, 200V	72982	374005S380339K
C546	283-0181-00	XB090000		CAP., FXD, CER DI: 1.8PF, 10%, 100V	72982	8101B121COK0189B
C548	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C549	283-0156-00			CAP., FXD, CER DI: 1000PF, +100-0%, 200V	72982	8111A208Z5U0102Z
C556	283-0140-00			CAP., FXD, CER DI: 4.7PF, 5%, 50V	72982	8101E003A479C
C557	283-0638-00			CAP., FXD, MICA D: 130PF, 1%, 100V	00853	D151F131F0
C563	281-0616-00	B010100	B089999	CAP., FXD, CER DI: 6.8PF, +/-0.5PF, 200V	72982	374001COH0689D

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
C563	281-0613-00	B090000	B149999	CAP., FXD, CER DI: 10PF, +/-1PF, 200V	72982	374001COG100F
C563	281-0650-00	B150000		CAP., FXD, CER DI: 18PF, 10%, 200V	72982	374001COH180K
C565	281-0616-00	B010100	B089999	CAP., FXD, CER DI: 6.8PF, +/-0.5PF, 200V	72982	374001COH0689D
C565	281-0613-00	B090000	B149999	CAP., FXD, CER DI: 10PF, +/-1PF, 200V	72982	374001COG100F
C565	281-0650-00	B150000		CAP., FXD, CER DI: 18PF, 10%, 200V	72982	374001COH180K
C568	281-0552-00			CAP., FXD, CER DI: 25PF, 5%, 500V	72982	301-000P2G0250J
C572	283-0604-00			CAP., FXD, MICA D: 304PF, 2%, 300V	00853	D153F3040G0
C579	281-0552-00			CAP., FXD, CER DI: 25PF, 5%, 500V	72982	301-000P2G0250J
C581	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C583	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C585	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C601	283-0156-00			CAP., FXD, CER DI: 1000PF, +100-0%, 200V	72982	8111A208Z5U0102Z
C606	283-0177-00			CAP., FXD, CER DI: 1UF, +80-20%, 25V	72982	8131N039 E 105Z
C607	283-0326-00			CAP., FXD, CER DI: 0.082UF, 10%, 50V	16546	CW20C823K
C608	283-0238-00			CAP., FXD, CER DI: 0.01UF, 10%, 50V	72982	8121N075X7R0103K
C609	283-0176-00			CAP., FXD, CER DI: 0.0022UF, 20%, 50V	72982	8121B058X7R0222M
C613	283-0182-00			CAP., FXD, CER DI: 51PF, 5%, 400V	72982	8121N400COG0510J
C614	283-0182-00			CAP., FXD, CER DI: 51PF, 5%, 400V	72982	8121N400COG0510J
C615	281-0158-00			CAP., VAR, CER DI: 7-45PF, 50V	73899	DVJ-5006
C617	281-0122-00			CAP., VAR, CER DI: 2.5-9PF, 100V	72982	518-000A2.5-9
C621	-----			(PART OF CIRCUIT BOARD)		
C624	283-0191-00			CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C625	-----			(PART OF CIRCUIT BOARD)		
C633	283-0000-00			CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C642	-----			(PART OF CIRCUIT BOARD)		
C644	283-0181-00			CAP., FXD, CER DI: 1.8PF, 10%, 100V	72982	8101B121COK0189B
C647	-----			(PART OF CIRCUIT BOARD)		
C648	283-0191-00			CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C649	283-0191-00			CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C652	283-0725-00			CAP., FXD, MICA D: 214PF, 1%, 500V	00853	D15-5E2140F0
C654	283-0725-00			CAP., FXD, MICA D: 214PF, 1%, 500V	00853	D15-5E2140F0
C655	283-0647-00			CAP., FXD, MICA D: 70PF, 1%, 100V	00853	D151E700F0
C656	283-0647-00			CAP., FXD, MICA D: 70PF, 1%, 100V	00853	D151E700F0
C657	-----			(PART OF CIRCUIT BOARD)		
C658	-----			(PART OF CIRCUIT BOARD)		
C662	-----			(PART OF CIRCUIT BOARD)		
C663	283-0191-00			CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C667	283-0191-00			CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C669	-----			(PART OF CIRCUIT BOARD)		
C684	290-0534-00	B010100	B142339X	CAP., FXD, ELCTLT: 1UF, 20%, 35V	56289	196D105X0035HA1
C695	283-0178-00			CAP., FXD, CER DI: 0.1UF, +80-20%, 100V	72982	8131N145651 104Z
C696	290-0517-00			CAP., FXD, ELCTLT: 6.8UF, 20%, 35V	56289	196D685X0035KA1
C697	290-0527-00			CAP., FXD, ELCTLT: 15UF, 20%, 20V	90201	TDC156M020FL
C698	290-0527-00			CAP., FXD, ELCTLT: 15UF, 20%, 20V	90201	TDC156M020FL
C699	283-0238-00	XB030000		CAP., FXD, CER DI: 0.01UF, 10%, 50V	72982	8121N075X7R0103K
C701	283-0156-00			CAP., FXD, CER DI: 1000PF, +100-0%, 200V	72982	8111A208Z5U0102Z
C702	281-0578-00			CAP., FXD, CER DI: 18PF, 5%, 500V	72982	301-050COG0180J
C703	283-0076-00	XB020000		CAP., FXD, CER DI: 27PF, 10%, 500V	56289	40C287A2
C704	283-0644-00			CAP., FXD, MICA D: 150PF, 1%, 500V	00853	D151E151F0
C705	283-0334-00	B010100	B059999	CAP., FXD, CER DI: 130PF, +1-2%, 500V	72982	8121N501COG0131G
C705	283-0618-00	B060000		CAP., FXD, MICA D: 130PF, 2%, 300V	00853	D155E131G0
C706	283-0068-00			CAP., FXD, CER DI: 0.01UF, +100-0%, 500V	56289	19C241
C707	283-0159-00			CAP., FXD, CER DI: 18PF, 5%, 50V	72982	8111B065COG0180J
C711	283-0140-00			CAP., FXD, CER DI: 4.7PF, 5%, 50V	72982	8101E003A479C
C714	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V	72982	8121N061Z5U0103M
C715	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V	72982	8121N061Z5U0103M

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Discont	Name & Description	Mfr Code	Mfr Part Number
C728	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V	72982	8121N061Z5U0103M
C731	-----			(PART OF CIRCUIT BOARD)		
C733	283-0159-00			CAP., FXD, CER DI: 18PF, 5%, 50V	72982	8111B065C0G0180J
C734	283-0108-00	XB050000		CAP., FXD, CER DI: 220PF, 10%, 200V	56289	272C13
C735	-----			(PART OF CIRCUIT BOARD)		
C744	283-0159-00			CAP., FXD, CER DI: 18PF, 5%, 50V	72982	8111B065C0G0180J
C746	-----			(PART OF CIRCUIT BOARD)		
C748	-----			(PART OF CIRCUIT BOARD)		
C750	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V	72982	8121N061Z5U0103M
C752	283-0025-00			CAP., FXD, CER DI: 500PF, 5%, 500V	91418	JE501K501959
C756	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V	72982	8121N061Z5U0103M
C761	283-0185-00			CAP., FXD, CER DI: 2.5PF, 5%, 50V	72982	8101B057C0K0295B
C762	283-0185-00			CAP., FXD, CER DI: 2.5PF, 5%, 50V	72982	8101B057C0K0295B
C763	283-0185-00			CAP., FXD, CER DI: 2.5PF, 5%, 50V	72982	8101B057C0K0295B
C768	283-0060-00			CAP., FXD, CER DI: 100PF, 5%, 200V	72982	855-535U2J101J
C769	281-0519-00			CAP., FXD, CER DI: 47PF, +/-4.7PF, 500V	72982	308-000C0G0470K
C772	281-0519-00			CAP., FXD, CER DI: 47PF, +/-4.7PF, 500V	72982	308-000C0G0470K
C785	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C787	290-0534-00			CAP., FXD, ELCTLT: 1UF, 20%, 35V	56289	196D105X0035HA1
C811	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C821	283-0076-00	B010100	B010209	CAP., FXD, CER DI: 27PF, 10%, 500V	56289	40C287A2
C821	281-0519-00	B010210		CAP., FXD, CER DI: 47PF, +/-4.7PF, 500V	72982	308-000C0G0470K
C824	283-0076-00			CAP., FXD, CER DI: 27PF, 10%, 500V	56289	40C287A2
C835	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V	72982	8121N061Z5U0103M
	-----			(C835, 485 ONLY)		
C837	283-0185-00	B010100	B069999X	CAP., FXD, CER DI: 2.5PF, 5%, 50V	72982	8101B057C0K0295B
	-----			(C837, 485 ONLY)		
C838	283-0156-00			CAP., FXD, CER DI: 1000PF, +100-0%, 200V	72982	8111A208Z5U0102Z
	-----			(C838, 485 ONLY)		
C839	283-0156-00			CAP., FXD, CER DI: 1000PF, +100-0%, 200V	72982	8111A208Z5U0102Z
	-----			(C839, 485 ONLY)		
C843	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V	72982	8121N061Z5U0103M
C844	290-0527-00			CAP., FXD, ELCTLT: 15UF, 20%, 20V	90201	TDC156M020FL
C845	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C846	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C847	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C848	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V	72982	8121N061Z5U0103M
	-----			(C848, 485 ONLY)		
C849	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
	-----			(C849, 485 ONLY)		
C853	283-0111-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8121-N088Z5U104M
C856	281-0628-00	B010100	B010285	CAP., FXD, CER DI: 15PF, 5%, 500V	72982	301-000C0G0150J
C856	281-0564-00	B010286		CAP., FXD, CER DI: 24PF, 5%, 500V	72982	301-000C0G0240J
C861	290-0512-00	XB010435		CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C862	283-0003-00			CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C863	281-0512-00			CAP., FXD, CER DI: 27PF, +/-2.7PF, 500V	72982	308-000C0G0270K
C867	281-0628-00			CAP., FXD, CER DI: 15PF, 5%, 500V	72982	301-000C0G0150J
C869	281-0589-00			CAP., FXD, CER DI: 170PF, 5%, 500V	72982	301000Z5D0171J
C874	281-0504-00			CAP., FXD, CER DI: 10PF, +/-1PF, 500V	72982	301-055C0G0100F
C876	281-0550-00			CAP., FXD, CER DI: 120PF, 10%, 500V	04222	7001-1373
C877	281-0184-00			CAP., VAR, PLSTC: 2-18PF, 500VDC	80031	2805D00218BN02FO
C878	283-0629-00			CAP., FXD, MICA D: 62PF, 1%, 500V	00853	D105E620F0
C879	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C881	283-0663-00			CAP., FXD, MICA D: 16.8PF, +/-0.5PF, 500V	00853	D155C16.8D0
C882	281-0182-00			CAP., VAR, PLSTC: 1.8-10PF, 500V	80031	2805D1R810BH02FO

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
C883	283-0239-00			CAP., FXD, CER DI: 0.022UF, 10%, 50V	72982	8121N083X7R0223K
C894	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C900	281-0578-00			CAP., FXD, CER DI: 18PF, 5%, 500V	72982	301-050C0G0180J
C902	283-0059-00	B010100	B010434	CAP., FXD, CER DI: 1UF, +80-20%, 25V	72982	8131N031Z5U0105Z
C902	290-0512-00	B010435		CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C911	283-0003-00	B010100	B010434	CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C911	290-0512-00	B010435		CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C912	283-0003-00	B010100	B010434X	CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C917	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C921	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C932	281-0578-00			CAP., FXD, CER DI: 18PF, 5%, 500V	72982	301-050C0G0180J
C938	283-0000-00			CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C943	283-0059-00			CAP., FXD, CER DI: 1UF, +80-20%, 25V	72982	8131N031Z5U0105Z
C945	283-0059-00			CAP., FXD, CER DI: 1UF, +80-20%, 25V	72982	8131N031Z5U0105Z
C962	283-0004-00	B010100	B010434	CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C962	290-0512-00	B010435		CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C965	290-0519-00			CAP., FXD, ELCTLT: 100UF, 20%, 20V	90201	TDC107M020WLD
C1002	281-0578-00			CAP., FXD, CER DI: 18PF, 5%, 500V	72982	301-050C0G0180J
C1003	283-0076-00	XB020000		CAP., FXD, CER DI: 27PF, 10%, 500V	56289	40C287A2
C1004	283-0644-00			CAP., FXD, MICA D: 150PF, 1%, 500V	00853	D151E151F0
C1005	283-0334-00	B010100	B059999	CAP., FXD, CER DI: 130PF, +1-2%, 500V	72982	8121N501COG0131G
C1005	283-0618-00	B060000		CAP., FXD, MICA D: 130PF, 2%, 300V	00853	D155E131G0
C1006	283-0068-00			CAP., FXD, CER DI: 0.01UF, +100-0%, 500V	56289	19C241
C1007	283-0159-00			CAP., FXD, CER DI: 18PF, 5%, 50V	72982	8111B065C0G0180J
C1011	283-0140-00			CAP., FXD, CER DI: 4.7PF, 5%, 50V	72982	8101E003A479C
C1012	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V	72982	8121N061Z5U0103M
C1013	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V	72982	8121N061Z5U0103M
C1014	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V	72982	8121N061Z5U0103M
C1016	283-0260-00			CAP., FXD, CER DI: 5.6PF, 5%, 200V	72982	8111B200C0G569C
C1027	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V	72982	8121N061Z5U0103M
C1029	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V	72982	8121N061Z5U0103M
C1030	283-0157-00			CAP., FXD, CER DI: 7PF, 5%, 500V	72982	8111B064C0H0709J
C1031	-----			(PART OF CIRCUIT BOARD)		
C1034	-----			(PART OF CIRCUIT BOARD)		
C1035	283-0108-00	XB050000		CAP., FXD, CER DI: 220PF, 10%, 200V	56289	272C13
C1040	283-0204-00			CAP., FXD, CER DI: 0.01UF, 20%, 50V	72982	8121N061Z5U0103M
C1041	-----			(PART OF CIRCUIT BOARD)		
C1043	283-0191-00	XB070000		CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C1044	-----			(PART OF CIRCUIT BOARD)		
C1045	283-0159-00			CAP., FXD, CER DI: 18PF, 5%, 50V	72982	8111B065C0G0180J
C1046	283-0191-00	XB070000		CAP., FXD, CER DI: 0.022UF, 20%, 50V	72982	8121N075Z5U0223M
C1052	283-0025-00			CAP., FXD, CER DI: 500PF, 5%, 500V	91418	JE501K501959
C1061	283-0185-00			CAP., FXD, CER DI: 2.5PF, 5%, 50V	72982	8101B057C0K0295B
C1063	283-0185-00			CAP., FXD, CER DI: 2.5PF, 5%, 50V	72982	8101B057C0K0295B
C1064	283-0185-00			CAP., FXD, CER DI: 2.5PF, 5%, 50V	72982	8101B057C0K0295B
C1071	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1072	283-0115-00			CAP., FXD, CER DI: 47PF, 5%, 200V	72982	805-519-C0G0470J
C1079	283-0115-00			CAP., FXD, CER DI: 47PF, 5%, 200V	72982	805-519-C0G0470J
C1099	290-0527-00			CAP., FXD, ELCTLT: 15UF, 20%, 20V	90201	TDC156M020FL
C1101	290-0580-00			CAP., FXD, ELCTLT: 0.27UF, 20%, 50V	56289	196D274X0050HA1
C1121	283-0113-00			CAP., FXD, CER DI: 56PF, 1%, 500V	72982	851-559A560F
C1130	290-0527-00			CAP., FXD, ELCTLT: 15UF, 20%, 20V	90201	TDC156M020FL
C1131	290-0527-00			CAP., FXD, ELCTLT: 15UF, 20%, 20V	90201	TDC156M020FL
C1132	283-0111-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8121-N088Z5U104M
C1133	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
C1134	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C1136	283-0111-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8121-N088Z5U104M
C1137	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C1139	290-0527-00			CAP., FXD, ELCTLT: 15UF, 20%, 20V	90201	TDC156M020FL
C1156	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1164	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1166	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1171	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1172	281-0604-00			CAP., FXD, CER DI: 2.2PF, +/-0.25PF, 500V	72982	301-000C0J0229C
C1174	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1177	281-0529-00			CAP., FXD, CER DI: 1.5PF, +/-0.25PF, 500V	72982	301-000C0K0159C
C1181	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1182	281-0604-00			CAP., FXD, CER DI: 2.2PF, +/-0.25PF, 500V	72982	301-000C0J0229C
C1184	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1187	281-0619-00			CAP., FXD, CER DI: 1.2PF, +/-0.1PF, 200V	72982	374000C0K0129B
C1190	281-0166-00			CAP., VAR, AIR DI: 1.9-15.7PF, 250V	74970	187-0109-005
C1192	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1199	290-0135-00			CAP., FXD, ELCTLT: 15UF, 20%, 20V	56289	150D156X0020BZ
C1204	281-0628-00			CAP., FXD, CER DI: 15PF, 5%, 500V	72982	301-000C0G0150J
C1206	283-0111-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8121-N088Z5U104M
C1214	283-0003-00			CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C1217	281-0601-00			CAP., FXD, CER DI: 7.5PF, 500V	72982	301-000C0H0759D
C1219	281-0589-00			CAP., FXD, CER DI: 170PF, 5%, 500V	72982	301000Z5D0171J
C1229	281-0512-00			CAP., FXD, CER DI: 27PF, +/-2.7PF, 500V	72982	308-000C0G0270K
C1232	283-0104-00			CAP., FXD, CER DI: 2000PF, 5%, 500V	72982	811-565B202J
C1235	281-0763-00	XB144450		CAP., FXD, CER DI: 47PF, 10%, 100V	72982	8035D9AADC1G470K
C1238	281-0528-00	B010100	B109999X	CAP., FXD, CER DI: 82PF, +/-8.2PF, 500V	72982	301-000U2M0820K
C1241	281-0550-00			CAP., FXD, CER DI: 120PF, 10%, 500V	04222	7001-1373
C1242	281-0184-00			CAP., VAR, PLSTC: 2-18PF, 500VDC	80031	2805D00218BN02F0
C1243	283-0633-00			CAP., FXD, MICA D: 77PF, 1%, 100V	00853	D151E770F0
C1247	281-0658-00			CAP., FXD, CER DI: 6.2PF, +/-0.25PF, 500V	72982	301-000C0H0629C
C1248	281-0178-00			CAP., VAR, PLSTC: 1-3.5PF, 500V	80031	2805D013R5BH02F0
C1254	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1263	281-0564-00			CAP., FXD, CER DI: 24PF, 5%, 500V	72982	301-000C0G0240J
C1268	283-0000-00			CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C1301	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1335	281-0622-00			CAP., FXD, CER DI: 47PF, 1%, 500V	72982	308-000C0G0470F
C1336	283-0111-00			CAP., FXD, CER DI: 0.1UF, 20%, 50V	72982	8121-N088Z5U104M
C1347	283-0647-00			CAP., FXD, MICA D: 70PF, 1%, 100V	00853	D151E700F0
C1364	281-0166-00			CAP., VAR, AIR DI: 1.9-15.7PF, 250V	74970	187-0109-005
C1366	283-0156-00	XB020000		CAP., FXD, CER DI: 1000PF, +100-0%, 200V	72982	8111A208Z5U0102Z
C1371	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1372	283-0168-00			CAP., FXD, CER DI: 12PF, 5%, 100V	72982	8101B121C0G0120J
C1374	283-0114-00			CAP., FXD, CER DI: 0.0015UF, 5%, 200V	72982	805-509B152J
C1402	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1404	285-0908-02			CAP., FXD, PLSTC: 0.01UF, 3%, 50V	80009	285-0908-02
C1405	285-0840-02			CAP., FXD, PLSTC: 1UF, 3.5%, 35V	80009	285-0840-02
	-----			(AVAILABLE AS A MATCHED SET, PART NUMBER		
	-----			295-0147-00. THE LETTER SUFFIX AND THE		
	-----			TOLERANCE SHOULD BE THE SAME FOR ALL OF		
	-----			TIMING CAPACITORS IN THE ASSEMBLY)		
C1431	281-0580-00			CAP., FXD, CER DI: 470PF, 10%, 500V	04222	7001-1374
C1432	281-0589-00			CAP., FXD, CER DI: 170PF, 5%, 500V	72982	301000Z5D0171J
C1433	285-0651-01			CAP., FXD, PLSTC: 0.0017UF, 5%, 100V	84411	TEK44-172551
C1434	285-0566-00			CAP., FXD, PLSTC: 0.022UF, 10%, 200V	56289	410P22392
C1435	285-0919-00			CAP., FXD, PLSTC: 0.22UF, 10%, 100V	56289	LP66A1B224K002
C1436	290-0523-00			CAP., FXD, ELCTLT: 2.2UF, 20%, 20V	56289	196D225X0020HA1

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
C1437	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C1442}	285-0752-01			CAP., FXD, PLSTC: 1UF, 3.5%, 50V	80009	285-0752-01
C1443}	285-0753-04			CAP., FXD, PLSTC: 0.01UF, 3.5%, 100V (SEE FOOTNOTE ON C1405)	80009	285-0753-04
C1482	290-0167-00			CAP., FXD, ELCTLT: 10UF, 20%, 15V	56289	150D106X0015B2
C1484	290-0534-00			CAP., FXD, ELCTLT: 1UF, 20%, 35V	56289	196D105X0035HA1
C1522	281-0603-00			CAP., FXD, CER DI: 39PF, 5%, 500V	72982	308-000C0G0390J
C1533	283-0003-00			CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C1537	290-0580-00			CAP., FXD, ELCTLT: 0.27UF, 20%, 50V	56289	196D274X0050HA1
C1538	290-0536-00			CAP., FXD, ELCTLT: 10UF, 20%, 25V	90201	TDC106M025FL
C1551	281-0512-00			CAP., FXD, CER DI: 27PF, +/-2.7PF, 500V	72982	308-000C0G0270K
C1552	281-0549-00			CAP., FXD, CER DI: 68PF, 10%, 500V	72982	301-000U2J0680K
C1558	290-0523-00			CAP., FXD, ELCTLT: 2.2UF, 20%, 20V	56289	196D225X0020HA1
C1562	283-0000-00			CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C1578	290-0512-00			CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C1579	290-0524-00			CAP., FXD, ELCTLT: 4.7UF, 20%, 10V	90201	TDC475M010EL
C1586	283-0668-00			CAP., FXD, MICA D: 184PF, 1%, 500V	00853	D155F1840FO
C1588	283-0000-00			CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C1600	283-0092-00			CAP., FXD, CER DI: 0.03UF, +80-20%, 200V	72982	845-534E303Z
C1601	283-0105-00			CAP., FXD, CER DI: 0.01UF, +80-20%, 2000V	56289	41C316
C1602	283-0013-00			CAP., FXD, CER DI: 0.01UF, +100-0%, 1000V	56289	33C29A7
C1603	283-0071-00			CAP., FXD, CER DI: 0.0068UF, +80-30%, 5000V	56289	45C10A1
C1611	283-0327-00			CAP., FXD, CER DI: 1000PF, +80-20%, 4000V	72982	3904BW100C102Z
C1612	283-0071-00			CAP., FXD, CER DI: 0.0068UF, +80-30%, 5000V	56289	45C10A1
C1619	285-0572-00			CAP., FXD, PLSTC: 0.1UF, 20%, 200V	56289	410P10402
C1621	283-0000-00			CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C1622	283-0003-00			CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C1627	283-0060-00			CAP., FXD, CER DI: 100PF, 5%, 200V	72982	855-535U2J101J
C1633	283-0327-00			CAP., FXD, CER DI: 1000PF, +80-20%, 4000V	72982	3904BW100C102Z
C1646	283-0327-00			CAP., FXD, CER DI: 1000PF, +80-20%, 4000V	72982	3904BW100C102Z
C1651	283-0327-00			CAP., FXD, CER DI: 1000PF, +80-20%, 4000V	72982	3904BW100C102Z
C1652	283-0327-00			CAP., FXD, CER DI: 1000PF, +80-20%, 4000V	72982	3904BW100C102Z
C1653	283-0000-00			CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C1656	283-0001-00			CAP., FXD, CER DI: 0.005UF, +100-0%, 500V	72982	831-559E502P
C1660	285-0572-00			CAP., FXD, PLSTC: 0.1UF, 20%, 200V	56289	410P10402
C1663	283-0327-00			CAP., FXD, CER DI: 1000PF, +80-20%, 4000V	72982	3904BW100C102Z
C1664	283-0327-00			CAP., FXD, CER DI: 1000PF, +80-20%, 4000V	72982	3904BW100C102Z
C1665	283-0041-00			CAP., FXD, CER DI: 0.0033UF, 5%, 500V	72982	841-541B332J
C1667	283-0327-00			CAP., FXD, CER DI: 1000PF, +80-20%, 4000V	72982	3904BW100C102Z
C1681	283-0327-00			CAP., FXD, CER DI: 1000PF, +80-20%, 4000V	72982	3904BW100C102Z
C1684	283-0327-00			CAP., FXD, CER DI: 1000PF, +80-20%, 4000V	72982	3904BW100C102Z
C1687	283-0327-00			CAP., FXD, CER DI: 1000PF, +80-20%, 4000V	72982	3904BW100C102Z
C1723	281-0564-00			CAP., FXD, CER DI: 24PF, 5%, 500V	72982	301-000C0G0240J
C1725	283-0317-00			CAP., FXD, CER DI: 1PF, +/-0.1PF, 500V	72982	861-518-COK0109B
C1728	283-0317-00			CAP., FXD, CER DI: 1PF, +/-0.1PF, 500V	72982	861-518-COK0109B
C1729	281-0512-00			CAP., FXD, CER DI: 27PF, +/-2.7PF, 500V	72982	308-000C0G0270K
C1732	283-0001-00			CAP., FXD, CER DI: 0.005UF, +100-0%, 500V	72982	831-559E502P
C1738	281-0523-00			CAP., FXD, CER DI: 100PF, +/-20PF, 500V	72982	301-000U2M0101M
C1739	283-0003-00	B010100	B010319	CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C1739	283-0068-00	B010320		CAP., FXD, CER DI: 0.01UF, +100-0%, 500V	56289	19C241
C1742	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1743	281-0526-00	B010100	B139999	CAP., FXD, CER DI: 1.5PF, +/-0.5PF, 500V	72982	301-000S2K0159D
C1743	281-0609-00	B140000		CAP., FXD, CER DI: 1PF, +/-0.1PF, 500V	72982	374-005COK0109B
C1744	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1748	290-0527-00			CAP., FXD, ELCTLT: 15UF, 20%, 20V	90201	TDC156M020FL

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Discont	Name & Description	Mfr Code	Mfr Part Number
C1749	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1751	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1755	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1756	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1762	281-0153-00			CAP., VAR, AIR DI: 1.7-10PF, 250V	74970	187-0106-005
C1764	281-0546-00			CAP., FXD, CER DI: 330PF, 10%, 500V	04222	7001-1380
C1765	281-0153-00			CAP., VAR, AIR DI: 1.7-10PF, 250V	74970	187-0106-005
C1766	281-0661-00			CAP., FXD, CER DI: 0.8PF, +/-0.1PF, 500V	72982	301-000COK0808B
C1771	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1774	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1775	281-0622-00			CAP., FXD, CER DI: 47PF, 1%, 500V	72982	308-000COG0470F
C1779	281-0550-00			CAP., FXD, CER DI: 120PF, 10%, 500V	04222	7001-1373
C1781	283-0317-00			CAP., FXD, CER DI: 1PF, +/-0.1PF, 500V	72982	861-518-COK0109B
C1782	281-0627-00			CAP., FXD, CER DI: 1PF, +/-0.25PF, 500V	72982	301-000COK0109C
C1786	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1787	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1788	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C1792	283-0068-00			CAP., FXD, CER DI: 0.01UF, +100-0%, 500V	56289	19C241
C1796	283-0000-00			CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C1812	283-0280-00			CAP., FXD, CER DI: 2200PF, 10%, 2000V	56289	562CBA202EH222KA
C1813	283-0280-00			CAP., FXD, CER DI: 2200PF, 10%, 2000V	56289	562CBA202EH222KA
C1814	283-0022-00			CAP., FXD, CER DI: 0.02UF, 1400VDCAC	80009	283-0022-00
C1822	290-0483-00			CAP., FXD, ELCTLT: 430UF, +50-10%, 200V	56289	36D7762
C1823	290-0483-00			CAP., FXD, ELCTLT: 430UF, +50-10%, 200V	56289	36D7762
C1824	283-0057-00			CAP., FXD, CER DI: 0.1UF, +80-20%, 200V	56289	274C10
C1825	283-0280-00			CAP., FXD, CER DI: 2200PF, 10%, 2000V	56289	562CBA202EH222KA
C1826	285-0981-00			CAP., FXD, PLSTC: 2.0UF, 10%, 400V	14752	C-2176-1
C1827	283-0280-00			CAP., FXD, CER DI: 2200PF, 10%, 2000V	56289	562CBA202EH222KA
C1829	283-0041-00			CAP., FXD, CER DI: 0.0033UF, 5%, 500V	72982	841-541B332J
C1834	290-0284-00			CAP., FXD, ELCTLT: 4.7UF, 10%, 35V	56289	150D475X9035B2
C1835	285-0980-00			CAP., FXD, PLSTC: 0.02UF, 5%, 1000V	56289	AF9A1G203J004
C1841	290-0284-00			CAP., FXD, ELCTLT: 4.7UF, 10%, 35V	56289	150D475X9035B2
C1848	290-0159-00			CAP., FXD, ELCTLT: 2UF, +50-10%, 150V	56289	30D205F150BB9
C1849	283-0078-00			CAP., FXD, CER DI: 0.001UF, 20%, 500V	56289	20C114A8
C1901	290-0573-00			CAP., FXD, ELCTLT: 2.7UF, 20%, 50V	56289	196D275X0050JA1
C1902	283-0003-00			CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C1904	283-0003-00			CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C1912	290-0524-00			CAP., FXD, ELCTLT: 4.7UF, 20%, 10V	90201	TDC475M010EL
C1914	281-0523-00			CAP., FXD, CER DI: 100PF, +/-20PF, 500V	72982	301-000U2M0101M
C1915	281-0523-00			CAP., FXD, CER DI: 100PF, +/-20PF, 500V	72982	301-000U2M0101M
C1918	290-0523-00	B010100	B029999	CAP., FXD, ELCTLT: 2.2UF, 20%, 20V	56289	196D225X0020HA1
C1918	290-0573-00	B030000		CAP., FXD, ELCTLT: 2.7UF, 20%, 50V	56289	196D275X0050JA1
C1919	283-0000-00	B010100	B139999	CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C1919	283-0594-00	B140000		CAP., FXD, MICA D: 0.001UF, 1%, 100V	00853	D151F102F0
C1921	283-0010-00			CAP., FXD, CER DI: 0.05UF, +100-20%, 50V	56289	273C20
C1924	283-0178-00	B010100	B059999	CAP., FXD, CER DI: 0.1UF, +80-20%, 100V	72982	8131N145651 104Z
C1924	290-0572-00	B060000		CAP., FXD, ELCTLT: 0.1UF, 20%, 50V	56289	196D104X0050HA1
C1940	283-0000-00			CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C1943	290-0572-00			CAP., FXD, ELCTLT: 0.1UF, 20%, 50V	56289	196D104X0050HA1
C1944	283-0003-00			CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C1951	283-0003-00			CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C2001	290-0159-00			CAP., FXD, ELCTLT: 2UF, +50-10%, 150V	56289	30D205F150BB9
C2002	290-0480-00			CAP., FXD, ELCTLT: 0.5UF, +50-10%, 200V	80009	290-0480-00
C2005	290-0194-00			CAP., FXD, ELCTLT: 10UF, +50-10%, 100V	56289	30D106F100DC4
C2006	290-0312-00			CAP., FXD, ELCTLT: 47UF, 10%, 35V	56289	150D476X9035S2
C2007	290-0312-00			CAP., FXD, ELCTLT: 47UF, 10%, 35V	56289	150D476X9035S2

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
C2008	290-0194-00			CAP., FXD, ELCTLT: 10UF, +50-10%, 100V	56289	30D106F100DC4
C2009	290-0194-00			CAP., FXD, ELCTLT: 10UF, +50-10%, 100V	56289	30D106F100DC4
C2011	290-0528-00			CAP., FXD, ELCTLT: 15UF, 20%, 50V	90201	TDC156M050WLC
C2012	290-0528-00			CAP., FXD, ELCTLT: 15UF, 20%, 50V	90201	TDC156M050WLC
C2013	290-0528-00			CAP., FXD, ELCTLT: 15UF, 20%, 50V	90201	TDC156M050WLC
C2015	290-0425-00			CAP., FXD, ELCTLT: 100UF, 20%, 20V	90201	THF107M020P1G
C2016	290-0425-00			CAP., FXD, ELCTLT: 100UF, 20%, 20V	90201	THF107M020P1G
C2018	290-0519-00			CAP., FXD, ELCTLT: 100UF, 20%, 20V	90201	TDC107M020WLD
C2019	290-0519-00			CAP., FXD, ELCTLT: 100UF, 20%, 20V	90201	TDC107M020WLD
C2021	290-0529-00			CAP., FXD, ELCTLT: 47UF, 20%, 20V	05397	T368C476M020AZ
C2023	290-0517-00			CAP., FXD, ELCTLT: 6.8UF, 20%, 35V	56289	196D685X0035KA1
C2025	290-0517-00			CAP., FXD, ELCTLT: 6.8UF, 20%, 35V	56289	196D685X0035KA1
C2035	290-0425-00			CAP., FXD, ELCTLT: 100UF, 20%, 20V	90201	THF107M020P1G
C2036	290-0425-00			CAP., FXD, ELCTLT: 100UF, 20%, 20V	90201	THF107M020P1G
C2038	290-0519-00			CAP., FXD, ELCTLT: 100UF, 20%, 20V	90201	TDC107M020WLD
C2039	290-0519-00			CAP., FXD, ELCTLT: 100UF, 20%, 20V	90201	TDC107M020WLD
C2042	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C2043	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C2045	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C2046	290-0420-00			CAP., FXD, ELCTLT: 0.68UF, 20%, 75V	56289	150D684X0075A2
C2047	283-0003-00			CAP., FXD, CER DI: 0.01UF, +80-20%, 150V	72982	855-558Z5U-103Z
C2052	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C2055	290-0517-00			CAP., FXD, ELCTLT: 6.8UF, 20%, 35V	56289	196D685X0035KA1
C2056	290-0527-00			CAP., FXD, ELCTLT: 15UF, 20%, 20V	90201	TDC156M020FL
C2062	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C2066	290-0527-00			CAP., FXD, ELCTLT: 15UF, 20%, 20V	90201	TDC156M020FL
C2072	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C2075	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C2076	290-0527-00			CAP., FXD, ELCTLT: 15UF, 20%, 20V	90201	TDC156M020FL
C2085	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C2086	290-0527-00			CAP., FXD, ELCTLT: 15UF, 20%, 20V	90201	TDC156M020FL
C2087	290-0517-00			CAP., FXD, ELCTLT: 6.8UF, 20%, 35V	56289	196D685X0035KA1
C2091	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C2092	283-0004-00			CAP., FXD, CER DI: 0.02UF, +80-20%, 150V	72982	855-558-Z5V0203Z
C2101	290-0529-00	B010100	B010434	CAP., FXD, ELCTLT: 47UF, 20%, 20V	05397	T368C476M020AZ
C2101	290-0519-00	B010435		CAP., FXD, ELCTLT: 100UF, 20%, 20V	90201	TDC107M020WLD
C2106	283-0000-00			CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C2108	285-0012-00			CAP., FXD, GL DI: 200PF, 2%, 500V	95275	VY13C201G
C2109	285-1006-00			CAP., FXD, PLSTC: 0.22UF, 2%, 50V	80009	285-1006-00
C2111	283-0000-00			CAP., FXD, CER DI: 0.001UF, +100-0%, 500V	72982	831-516E102P
C2117	290-0512-00	B010100	B010434	CAP., FXD, ELCTLT: 22UF, 20%, 15V	56289	196D226X0015KA1
C2117	290-0519-00	B010435		CAP., FXD, ELCTLT: 100UF, 20%, 20V	90201	TDC107M020WLD
C2139	283-0178-00			CAP., FXD, CER DI: 0.1UF, +80-20%, 100V	72982	8131N145651 104Z
CR6	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 50MA	80009	152-0141-02
CR32	152-0323-01	XB150000		SEMICONV DEVICE: SILICON, 35V, 100MA (CR32, 485, 485-1 ONLY)	80009	152-0323-01
CR33	152-0367-00	B010100	B149999	SEMICONV DEVICE: SILICON, 20V, 20PA (485, 485-1 ONLY)	80009	152-0367-00
CR33	152-0153-00	B150000	B155229	SEMICONV DEVICE: SILICON, 15V, 50MA (485, 485-1 ONLY)	80009	152-0153-00
CR33	152-0141-02	B155230		SEMICONV DEVICE: SILICON, 30V, 50MA (485, 485-1 ONLY. ADDED AS REQUIRED)	80009	152-0141-02
CR62	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 50MA (CR62, 485, 485-1 ONLY)	80009	152-0141-02
CR64	152-0075-00			SEMICONV DEVICE: GE, 25V, 40MA (CR64, 485, 485-1 ONLY)	80009	152-0075-00

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
CR65	152-0075-00			SEMICONV DEVICE:GE, 25V, 40MA (CR65, 485, 485-1 ONLY)	80009	152-0075-00
CR97	150-1004-00	B010100	B144079	LAMP, LED: RED, 2.5V, 15MA	08806	SSL-12
CR97	150-1040-03	B144080	B166699	LAMP, LED: RED, 5MA, 2.0V	80009	150-1040-03
CR97	150-1031-00	B166700		LT EMITTING DIO: RED, 650NM, 40MA MAX	53184	XC209R
CR98	150-1004-00	B010100	B144079	LAMP, LED: RED, 2.5V, 15MA	08806	SSL-12
CR98	150-1040-03	B144080	B166699	LAMP, LED: RED, 5MA, 2.0V	80009	150-1040-03
CR98	150-1031-00	B166700		LT EMITTING DIO: RED, 650NM, 40MA MAX	53184	XC209R
CR99	150-1004-00	B010100	B144079	LAMP, LED: RED, 2.5V, 15MA	08806	SSL-12
CR99	150-1040-03	B144080	B166699	LAMP, LED: RED, 5MA, 2.0V	80009	150-1040-03
CR99	150-1031-00	B166700		LT EMITTING DIO: RED, 650NM, 40MA MAX	53184	XC209R
CR201	152-0061-00	B010100	B049999	SEMICONV DEVICE: SILICON, 175V, 100MA	80009	152-0061-00
CR201	153-0051-00	B050000		SEMICONV DEVICE: SILICON, MATCHED SET	80009	153-0051-00
CR202	152-0061-00	B010100	B049999	SEMICONV DEVICE: SILICON, 175V, 100MA	80009	152-0061-00
CR202	153-0051-00	B050000		SEMICONV DEVICE: SILICON, MATCHED SET	80009	153-0051-00
CR203	152-0061-00	B010100	B049999	SEMICONV DEVICE: SILICON, 175V, 100MA	80009	152-0061-00
CR203	153-0051-00	B050000		SEMICONV DEVICE: SILICON, MATCHED SET	80009	153-0051-00
CR204	152-0061-00	B010100	B049999	SEMICONV DEVICE: SILICON, 175V, 100MA	80009	152-0061-00
CR204	153-0051-00	B050000		SEMICONV DEVICE: SILICON, MATCHED SET	80009	153-0051-00
CR291	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR301	152-0061-00	B010100	B049999	SEMICONV DEVICE: SILICON, 175V, 100MA	80009	152-0061-00
CR301	153-0051-00	B050000		SEMICONV DEVICE: SILICON, MATCHED SET	80009	153-0051-00
CR302	152-0061-00	B010100	B049999	SEMICONV DEVICE: SILICON, 175V, 100MA	80009	152-0061-00
CR302	153-0051-00	B050000		SEMICONV DEVICE: SILICON, MATCHED SET	80009	153-0051-00
CR303	152-0061-00	B010100	B049999	SEMICONV DEVICE: SILICON, 175V, 100MA	80009	152-0061-00
CR303	153-0051-00	B050000		SEMICONV DEVICE: SILICON, MATCHED SET	80009	153-0051-00
CR304	152-0061-00	B010100	B049999	SEMICONV DEVICE: SILICON, 175V, 100MA	80009	152-0061-00
CR304	153-0051-00	B050000		SEMICONV DEVICE: SILICON, MATCHED SET	80009	153-0051-00
CR410	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR542	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR562	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR682	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR711	152-0246-00			SEMICONV DEVICE: SILICON, 400PIV, 200MA	80009	152-0246-00
CR718	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR732	152-0322-00	XB070000	B099999X	SEMICONV DEVICE: SILICON, 15V, HOT CARRIER	80009	152-0322-00
CR734	152-0322-00	XB070000	B099999X	SEMICONV DEVICE: SILICON, 15V, HOT CARRIER	80009	152-0322-00
CR751	152-0177-00	B010100	B049999	SEMICONV DEVICE: TUNNEL, 10MA, 4PF	80009	152-0177-00
CR751	152-0177-02	B050000		SEMICONV DEVICE: TUNNEL, 10MA, +/-0.5MA, 2PF	80009	152-0177-02
CR762	152-0177-00			SEMICONV DEVICE: TUNNEL, 10MA, 4PF	80009	152-0177-00
CR772	152-0177-00			SEMICONV DEVICE: TUNNEL, 10MA, 4PF	80009	152-0177-00
CR781	152-0075-00			SEMICONV DEVICE: GE, 25V, 40MA	80009	152-0075-00
CR784	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR785	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR816	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR838	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 50NA (CR838, 485 ONLY)	80009	152-0141-02
CR839	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 50NA (CR839, 485 ONLY)	80009	152-0141-02
CR853	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR856	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR864	152-0151-00			SEMICONV DEVICE: SILICON, SW, W/HT SK	80009	152-0151-00
CR867	152-0153-00			SEMICONV DEVICE: SILICON, 15V, 50MA	80009	152-0153-00
CR868	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR879	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR886	152-0141-02			SEMICONV DEVICE: SILICON, 30V, 50NA	80009	152-0141-02

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
CR902	152-0307-00			SEMICON D DEVICE: SILICON, 300V, 0.13A	04713	SSD1150
CR935	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1011	152-0246-00			SEMICON D DEVICE: SILICON, 400PIV, 200MA	80009	152-0246-00
CR1052	152-0177-00	B010100	B049999	SEMICON D DEVICE: TUNNEL, 10MA, 4PF	80009	152-0177-00
CR1052	152-0177-02	B050000		SEMICON D DEVICE: TUNNEL, 10MA, +/-0.5MA, 2PF	80009	152-0177-02
CR1062	152-0177-00			SEMICON D DEVICE: TUNNEL, 10MA, 4PF	80009	152-0177-00
CR1070	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1071	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1098	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1104	152-0177-00			SEMICON D DEVICE: TUNNEL, 10MA, 4PF	80009	152-0177-00
CR1108	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1121	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1152	152-0153-00			SEMICON D DEVICE: SILICON, 15V, 50MA	80009	152-0153-00
CR1153	152-0153-00			SEMICON D DEVICE: SILICON, 15V, 50MA	80009	152-0153-00
CR1156	152-0333-00			SEMICON D DEVICE: SILICON, 55V, 200MA	80009	152-0333-00
CR1166	152-0333-00			SEMICON D DEVICE: SILICON, 55V, 200MA	80009	152-0333-00
CR1168	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1204	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1206	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1211	152-0153-00			SEMICON D DEVICE: SILICON, 15V, 50MA	80009	152-0153-00
CR1214	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1215	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1217	152-0153-00			SEMICON D DEVICE: SILICON, 15V, 50MA	80009	152-0153-00
CR1221	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1234	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1237	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1238	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1239	152-0245-00			SEMICON D DEVICE: SILICON, 10NA AT 5V	80009	152-0245-00
CR1242	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1272	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1273	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1311	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1321	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1336	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1356	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1358	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1359	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1366	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1400	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1431	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1482	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1491	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1492	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1494	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1495	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1504	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1526	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1530	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1531	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1532	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1533	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1534	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1535	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1536	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1538	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1539	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
CR1551	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1552	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1557	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1558	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1561	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1581	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1582	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1584	152-0075-00			SEMICON D DEVICE: GE, 25V, 40MA	80009	152-0075-00
CR1585	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1601	152-0409-00			SEMICON D DEVICE: SILICON, 12, 000V, 5MA	80009	152-0409-00
CR1602	152-0409-00			SEMICON D DEVICE: SILICON, 12, 000V, 5MA	80009	152-0409-00
CR1618	152-0066-00			SEMICON D DEVICE: SILICON, 400V, 750MA	80009	152-0066-00
CR1621	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1626	152-0242-00			SEMICON D DEVICE: SILICON, 225V, 200MA	80009	152-0242-00
CR1627	152-0242-00			SEMICON D DEVICE: SILICON, 225V, 200MA	80009	152-0242-00
CR1646	152-0242-00			SEMICON D DEVICE: SILICON, 225V, 200MA	80009	152-0242-00
CR1651	152-0242-00			SEMICON D DEVICE: SILICON, 225V, 200MA	80009	152-0242-00
CR1652	152-0242-00			SEMICON D DEVICE: SILICON, 225V, 200MA	80009	152-0242-00
CR1656	152-0242-00			SEMICON D DEVICE: SILICON, 225V, 200MA	80009	152-0242-00
CR1660	152-0242-00			SEMICON D DEVICE: SILICON, 225V, 200MA	80009	152-0242-00
CR1663	152-0242-00			SEMICON D DEVICE: SILICON, 225V, 200MA	80009	152-0242-00
CR1664	152-0242-00			SEMICON D DEVICE: SILICON, 225V, 200MA	80009	152-0242-00
CR1666	152-0242-00			SEMICON D DEVICE: SILICON, 225V, 200MA	80009	152-0242-00
CR1710	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1735	152-0107-00			SEMICON D DEVICE: SILICON, 400V, 400MA	80009	152-0107-00
CR1737	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1738	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1739	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1752	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1766	152-0233-00			SEMICON D DEVICE: SILICON, 85V, 100MA	80009	152-0233-00
CR1769	152-0061-00			SEMICON D DEVICE: SILICON, 175V, 100MA	80009	152-0061-00
CR1775	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1776	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1777	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1821	152-0396-01			SEMICON D DEVICE: SILICON, 400V, 3A	12969	652-821
CR1832	152-0061-00			SEMICON D DEVICE: SILICON, 175V, 100MA	80009	152-0061-00
CR1833	152-0061-00			SEMICON D DEVICE: SILICON, 175V, 100MA	80009	152-0061-00
CR1834	152-0400-00			SEMICON D DEVICE: SILICON, 400V, 1A	80009	152-0400-00
CR1842	152-0107-00			SEMICON D DEVICE: SILICON, 400V, 400MA	80009	152-0107-00
CR1843	152-0107-00			SEMICON D DEVICE: SILICON, 400V, 400MA	80009	152-0107-00
CR1844	152-0400-00			SEMICON D DEVICE: SILICON, 400V, 1A	80009	152-0400-00
CR1848	152-0107-00			SEMICON D DEVICE: SILICON, 400V, 400MA	80009	152-0107-00
CR1901	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1904	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1912	152-0141-02	B010100	B129999X	SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1923	152-0333-00			SEMICON D DEVICE: SILICON, 55V, 200MA	80009	152-0333-00
CR1924	152-0333-00			SEMICON D DEVICE: SILICON, 55V, 200MA	80009	152-0333-00
CR1925	152-0333-00			SEMICON D DEVICE: SILICON, 55V, 200MA	80009	152-0333-00
CR1931	152-0333-00			SEMICON D DEVICE: SILICON, 55V, 200MA	80009	152-0333-00
CR1932	152-0333-00			SEMICON D DEVICE: SILICON, 55V, 200MA	80009	152-0333-00
CR1933	152-0333-00			SEMICON D DEVICE: SILICON, 55V, 200MA	80009	152-0333-00
CR1934	152-0333-00			SEMICON D DEVICE: SILICON, 55V, 200MA	80009	152-0333-00
CR1943	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1958	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR1959	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR2001	152-0413-00			SEMICON D DEVICE: SILICON, 400V, 750MA	80009	152-0413-00

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Discont	Name & Description	Mfr Code	Mfr Part Number
CR2002	152-0413-00			SEMICON D DEVICE: SILICON, 400V, 750MA	80009	152-0413-00
CR2004	152-0413-00			SEMICON D DEVICE: SILICON, 400V, 750MA	80009	152-0413-00
CR2005	152-0413-00			SEMICON D DEVICE: SILICON, 400V, 750MA	80009	152-0413-00
CR2006	152-0413-00			SEMICON D DEVICE: SILICON, 400V, 750MA	80009	152-0413-00
CR2007	152-0413-00			SEMICON D DEVICE: SILICON, 400V, 750MA	80009	152-0413-00
CR2011	152-0414-00			SEMICON D DEVICE: SILICON, 200V, 0.75A	80009	152-0414-00
CR2012	152-0414-00			SEMICON D DEVICE: SILICON, 200V, 0.75A	80009	152-0414-00
CR2014	152-0412-00			SEMICON D DEVICE: SILICON, 50V, 3A	80009	152-0412-00
CR2015	152-0412-00			SEMICON D DEVICE: SILICON, 50V, 3A	80009	152-0412-00
CR2016	152-0412-00			SEMICON D DEVICE: SILICON, 50V, 3A	80009	152-0412-00
CR2017	152-0412-00			SEMICON D DEVICE: SILICON, 50V, 3A	80009	152-0412-00
CR2034	152-0412-00			SEMICON D DEVICE: SILICON, 50V, 3A	80009	152-0412-00
CR2035	152-0412-00			SEMICON D DEVICE: SILICON, 50V, 3A	80009	152-0412-00
CR2036	152-0412-00			SEMICON D DEVICE: SILICON, 50V, 3A	80009	152-0412-00
CR2037	152-0412-00			SEMICON D DEVICE: SILICON, 50V, 3A	80009	152-0412-00
CR2042	152-0061-00			SEMICON D DEVICE: SILICON, 175V, 100MA	80009	152-0061-00
CR2047	152-0141-02	B010100	B139999X	SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR2052	152-0141-02			SEMICON D DEVICE: SILICON, 30V, 50NA	80009	152-0141-02
CR2124	152-0322-00			SEMICON D DEVICE: SILICON, 15V, HOT CARRIER	80009	152-0322-00
CR2133	152-0322-00			SEMICON D DEVICE: SILICON, 15V, HOT CARRIER	80009	152-0322-00
DL1	119-0325-00			DELAY LINE, ELEC:	80009	119-0325-00
DL410	119-0302-00			DELAY LINE, ELEC:	80009	119-0302-00
DS96	150-0048-01			LAMP, INCAND: 5V, 0.06A, SEL	08806	683AS15
DS125	150-0048-01			LAMP, INCAND: 5V, 0.06A, SEL	08806	683AS15
DS290	150-0128-00			LAMP, INCAND: 6V, 200MA	71744	1784
DS291	150-0128-00			LAMP, INCAND: 6V, 200MA	71744	1784
DS630	150-0048-01			LAMP, INCAND: 5V, 0.06A, SEL	08806	683AS15
DS780	150-0048-01			LAMP, INCAND: 5V, 0.06A, SEL	08806	683AS15
DS781	150-0048-01			LAMP, INCAND: 5V, 0.06A, SEL	08806	683AS15
DS1668	150-0030-00			LAMP, GLOW: NEON, T-2, 60 TO 90 VOLTS	08806	A2B-T
DS1669	150-0030-00			LAMP, GLOW: NEON, T-2, 60 TO 90 VOLTS	08806	A2B-T
DS1684	150-0030-00			LAMP, GLOW: NEON, T-2, 60 TO 90 VOLTS	08806	A2B-T
DS1685	150-0030-00			LAMP, GLOW: NEON, T-2, 60 TO 90 VOLTS	08806	A2B-T
DS1687	150-0030-00			LAMP, GLOW: NEON, T-2, 60 TO 90 VOLTS	08806	A2B-T
DS1801	119-0181-00			SURGE VOLTAGE P: 230VAC, +/-15%	80009	119-0181-00
DS1802	119-0181-00			SURGE VOLTAGE P: 230VAC, +/-15%	80009	119-0181-00
DS1824	150-0035-00			LAMP, GLOW: 90V, 0.3MA	53944	A1B-3
F1801	159-0015-00			FUSE, CARTRIDGE: 3AG, 3A, 250V, FAST-BLOW	71400	ACC 3
J1	131-0679-00	B010100	B131949	CONNECTOR, RCPT, :BNC, MALE, 3 CONTACT	24931	28JR168-1
J1	131-0679-01	B131950		CONNECTOR, RCPT, :BNC, MALE, 3 CONTACT	24931	28JR168-1
J5	131-1003-00			CONN, RCPT, ELEC: CKT BD MT, 3 PRONG	80009	131-1003-00
J70	131-1003-00			CONN, RCPT, ELEC: CKT BD MT, 3 PRONG (J70, 485, 485-1 ONLY)	80009	131-1003-00
J101	131-1003-00			CONN, RCPT, ELEC: CKT BD MT, 3 PRONG	80009	131-1003-00
J129	131-1003-00			CONN, RCPT, ELEC: CKT BD MT, 3 PRONG	80009	131-1003-00
J149	131-1003-00			CONN, RCPT, ELEC: CKT BD MT, 3 PRONG	80009	131-1003-00
J200	131-1003-00			CONN, RCPT, ELEC: CKT BD MT, 3 PRONG	80009	131-1003-00
J300	131-1003-00			CONN, RCPT, ELEC: CKT BD MT, 3 PRONG	80009	131-1003-00
J410	131-1003-00			CONN, RCPT, ELEC: CKT BD MT, 3 PRONG	80009	131-1003-00
J415	131-1003-00			CONN, RCPT, ELEC: CKT BD MT, 3 PRONG	80009	131-1003-00
J430	131-1003-00			CONN, RCPT, ELEC: CKT BD MT, 3 PRONG	80009	131-1003-00
J435	131-1003-00			CONN, RCPT, ELEC: CKT BD MT, 3 PRONG	80009	131-1003-00
J566	131-1003-00			CONN, RCPT, ELEC: CKT BD MT, 3 PRONG	80009	131-1003-00
J568	131-1003-00			CONN, RCPT, ELEC: CKT BD MT, 3 PRONG	80009	131-1003-00

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
J572	131-1003-00			CONN, RCPT, ELEC:CKT BD MT, 3 PRONG	80009	131-1003-00
J620	131-1003-00			CONN, RCPT, ELEC:CKT BD MT, 3 PRONG	80009	131-1003-00
J625	131-1003-00			CONN, RCPT, ELEC:CKT BD MT, 3 PRONG	80009	131-1003-00
J701	131-0955-00			CONNECTOR, RCPT, :BNC, FEMALE, W/HARDWARE	13511	31-279
J762	131-1003-00			CONN, RCPT, ELEC:CKT BD MT, 3 PRONG	80009	131-1003-00
J763	131-1003-00			CONN, RCPT, ELEC:CKT BD MT, 3 PRONG	80009	131-1003-00
J781	131-0955-00			CONNECTOR, RCPT, :BNC, FEMALE, W/HARDWARE	13511	31-279
J813	131-1003-00			CONN, RCPT, ELEC:CKT BD MT, 3 PRONG	80009	131-1003-00
J814	131-1003-00			CONN, RCPT, ELEC:CKT BD MT, 3 PRONG	80009	131-1003-00
J816	131-1003-00			CONN, RCPT, ELEC:CKT BD MT, 3 PRONG	80009	131-1003-00
J842	131-1003-00			CONN, RCPT, ELEC:CKT BD MT, 3 PRONG (J842, 485 ONLY)	80009	131-1003-00
J843	131-1003-00			CONN, RCPT, ELEC:CKT BD MT, 3 PRONG (J843, 485 ONLY)	80009	131-1003-00
J948	131-1003-00			CONN, RCPT, ELEC:CKT BD MT, 3 PRONG	80009	131-1003-00
J949	131-0955-00			CONNECTOR, RCPT, :BNC, FEMALE, W/HARDWARE	13511	31-279
J1001	131-0955-00			CONNECTOR, RCPT, :BNC, FEMALE, W/HARDWARE	13511	31-279
J1063	131-1003-00			CONN, RCPT, ELEC:CKT BD MT, 3 PRONG	80009	131-1003-00
J1064	131-1003-00			CONN, RCPT, ELEC:CKT BD MT, 3 PRONG	80009	131-1003-00
J1116	131-1003-00			CONN, RCPT, ELEC:CKT BD MT, 3 PRONG	80009	131-1003-00
J1117	131-1003-00			CONN, RCPT, ELEC:CKT BD MT, 3 PRONG	80009	131-1003-00
J1119	131-0955-00			CONNECTOR, RCPT, :BNC, FEMALE, W/HARDWARE	13511	31-279
J1346	131-1003-00			CONN, RCPT, ELEC:CKT BD MT, 3 PRONG	80009	131-1003-00
J1549	131-1003-00			CONN, RCPT, ELEC:CKT BD MT, 3 PRONG	80009	131-1003-00
J1551	131-1003-00			CONN, RCPT, ELEC:CKT BD MT, 3 PRONG	80009	131-1003-00
J1554	131-1003-00			CONN, RCPT, ELEC:CKT BD MT, 3 PRONG	80009	131-1003-00
J1555	131-0861-00			TERM, QIK DISC:16-20 AWG, 0.22 W X 0.02 THK	00779	42617-2
J1557	131-1003-00			CONN, RCPT, ELEC:CKT BD MT, 3 PRONG	80009	131-1003-00
J1785	131-0771-00			CONN, RCPT, ELEC:4 CONT, QUICK DISCONNECT	0000A	ROA-304NYL
J1787	131-0771-00			CONN, RCPT, ELEC:4 CONT, QUICK DISCONNECT	0000A	ROA-304NYL
J2134	131-1003-00			CONN, RCPT, ELEC:CKT BD MT, 3 PRONG	80009	131-1003-00
J2135	131-0818-00			CONNECTOR, RCPT, :BNC, FEMALE	91836	KC19-153BNC
K1	148-0070-00	B010100	B159999	RELAY, ARMATURE:SPDT, 21VDC, 450MW, 3.5A, 30VDC (485, 485-1, 485-2 ONLY)	05587	A1558
K1	650-0563-00	B160000	B169999	CKT BOARD ASSY: (485, 485-1 ONLY)	80009	650-0563-00
K1	148-0129-01	B167000		RELAY ASSY:SPDT, 1A, 18VDC, 1130 OHM (485, 485-1 ONLY)	80009	148-0129-01
K1S1	-----			(PART OF K1)		
K1	650-0563-00	B160000		CKT BOARD ASSY: (485-2 ONLY)	80009	650-0563-00
K1	-----					
K410	148-0071-00	B010100	B159999	RELAY, ARMATURE:PLUG-IN, DPDT (485 ONLY)	99699	2X-A1538
K410	650-0562-00	B160000		CKT BOARD ASSY: (485 ONLY)	80009	650-0562-00
K410S1	-----			(PART OF K410)		
K410S2	-----			(PART OF K410)		
K879	148-0034-01			RELAY, ARMATURE:DPDT, 600 OHM, 15VDC	80009	148-0034-01
K1242	148-0034-01			RELAY, ARMATURE:DPDT, 600 OHM, 15VDC	80009	148-0034-01
L5	-----			(WIRE LEAD)		
L51	276-0507-00	XB030000		SHIELDING BEAD, :0.6UH	78488	57-0180-7D 500B
L94	108-0598-00			COIL, RF:200UH	80009	108-0598-00
L101	-----			(WIRE LEAD)		
L127	-----			(PART OF CIRCUIT BOARD)		
L149	276-0581-00			CORE, ADJ TUNING:	78488	57-1307

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
L201	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L204	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L211	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L240	108-0557-00			COIL, RF: 35NH	80009	108-0557-00
L241	108-0557-00			COIL, RF: 35NH	80009	108-0557-00
L242	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L245	-----			(PART OF CIRCUIT BOARD)		
L248	-----			(PART OF CIRCUIT BOARD)		
L262	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L266	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L290	276-0543-00	XB130000		SHLD BEAD, ELEK: FERRITE	80009	276-0543-00
L310	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L312	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L340	108-0557-00			COIL, RF: 35NH	80009	108-0557-00
L341	108-0557-00			COIL, RF: 35NH	80009	108-0557-00
L342	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L345	-----			(PART OF CIRCUIT BOARD)		
L348	-----			(PART OF CIRCUIT BOARD)		
L362	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L366	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L401	-----			(PART OF CIRCUIT BOARD)		
L405	-----			(PART OF CIRCUIT BOARD)		
L409	108-0733-00			COIL, RF: 113NH	80009	108-0733-00
L419	108-0538-00			COIL, RF: 2.7UH	76493	70F276A1
L421	-----			(PART OF CIRCUIT BOARD)		
L425	-----			(PART OF CIRCUIT BOARD)		
L501	-----			(PART OF CIRCUIT BOARD)		
L502	-----			(PART OF CIRCUIT BOARD)		
L505	-----			(PART OF CIRCUIT BOARD)		
L506	-----			(PART OF CIRCUIT BOARD)		
L511	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L521	-----			(PART OF CIRCUIT BOARD)		
L522	-----			(PART OF CIRCUIT BOARD)		
L525	-----			(PART OF CIRCUIT BOARD)		
L526	-----			(PART OF CIRCUIT BOARD)		
L531	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L548	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L559	108-0736-00			COIL, RF: 810NH	80009	108-0736-00
L581	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L583	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L584	108-0538-00			COIL, RF: 2.7UH	76493	70F276A1
L585	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L621	-----			(PART OF CIRCUIT BOARD)		
L625	-----			(PART OF CIRCUIT BOARD)		
L650	108-0182-00			COIL, RF: 0.3UH	80009	108-0182-00
L651(2)	276-0543-00			SHLD BEAD, ELEK: FERRITE	80009	276-0543-00
L652	108-0734-00			COIL, RF: 175NH	80009	108-0734-00
L653(2)	276-0543-00			SHLD BEAD, ELEK: FERRITE	80009	276-0543-00
L654	114-0289-00			COIL, RF: 0.15-0.35UH, CORE 276-0568-00	80009	114-0289-00
L655	108-0735-00			COIL, RF: 575NH	80009	108-0735-00
L656	108-0735-00			COIL, RF: 575NH	80009	108-0735-00
L695	108-0215-00			COIL, RF: 1.1UH	80009	108-0215-00
L697	108-0538-00			COIL, RF: 2.7UH	76493	70F276A1
L698	108-0538-00			COIL, RF: 2.7UH	76493	70F276A1
L731	-----			(PART OF CIRCUIT BOARD)		
L732	-----			(PART OF CIRCUIT BOARD)		

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
L735	-----	-----		(PART OF CIRCUIT BOARD)		
L736	-----	-----		(PART OF CIRCUIT BOARD)		
L746	-----	-----		(PART OF CIRCUIT BOARD)		
L747	-----	-----		(PART OF CIRCUIT BOARD)		
L748	-----	-----		(PART OF CIRCUIT BOARD)		
L749	-----	-----		(PART OF CIRCUIT BOARD)		
L753	108-0578-00			COIL, RF: FIXED, 45NH	80009	108-0578-00
L757	108-0249-00			COIL, RF: 12UH	76493	B-4992
L844	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L845	108-0249-00			COIL, RF: 12UH	76493	B-4992
L846	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L847	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L848	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L851	276-0507-00			SHIELDING BEAD, :0.6UH	78488	57-0180-7D 500B
L853	276-0507-00			SHIELDING BEAD, :0.6UH	78488	57-0180-7D 500B
L883	276-0528-00			SHIELDING BEAD, :0.1UH	02114	56-0590-65C/3B
L884	276-0528-00			SHIELDING BEAD, :0.1UH	02114	56-0590-65C/3B
L891	108-0146-00			COIL, RF: 5UH	80009	108-0146-00
L893	120-0285-00			XFMR, TOROID: 4 TURNS SINGLE	80009	120-0285-00
L942	276-0528-00			SHIELDING BEAD, :0.1UH	02114	56-0590-65C/3B
L943	276-0528-00			SHIELDING BEAD, :0.1UH	02114	56-0590-65C/3B
L1031	-----	-----		(PART OF CIRCUIT BOARD)		
L1032	-----	-----		(PART OF CIRCUIT BOARD)		
L1033	-----	-----		(PART OF CIRCUIT BOARD)		
L1034	-----	-----		(PART OF CIRCUIT BOARD)		
L1038	276-0528-00			SHIELDING BEAD, :0.1UH	02114	56-0590-65C/3B
L1041	-----	-----		(PART OF CIRCUIT BOARD)		
L1042	-----	-----		(PART OF CIRCUIT BOARD)		
L1043	-----	-----		(PART OF CIRCUIT BOARD)		
L1044	-----	-----		(PART OF CIRCUIT BOARD)		
L1055	108-0578-00			COIL, RF: FIXED, 45NH	80009	108-0578-00
L1057	108-0249-00			COIL, RF: 12UH	76493	B-4992
L1099	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L1130	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L1131	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L1133	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L1134	108-0249-00			COIL, RF: 12UH	76493	B-4992
L1137	108-0245-00			COIL, RF: 3.9UH	80009	108-0245-00
L1156	276-0507-00			SHIELDING BEAD, :0.6UH	78488	57-0180-7D 500B
L1157	276-0507-00			SHIELDING BEAD, :0.6UH	78488	57-0180-7D 500B
L1192	276-0507-00			SHIELDING BEAD, :0.6UH	78488	57-0180-7D 500B
L1202	276-0507-00			SHIELDING BEAD, :0.6UH	78488	57-0180-7D 500B
L1231	276-0528-00			SHIELDING BEAD, :0.1UH	02114	56-0590-65C/3B
L1232	276-0528-00			SHIELDING BEAD, :0.1UH	02114	56-0590-65C/3B
L1251	108-0146-00			COIL, RF: 5UH	80009	108-0146-00
L1252	120-0285-00			XFMR, TOROID: 4 TURNS SINGLE	80009	120-0285-00
L1346	114-0222-00			COIL, RF: 2-6UH, CORE 276-0568-00	80009	114-0222-00
L1578	108-0538-00			COIL, RF: 2.7UH	76493	70F276A1
L1748	108-0538-00			COIL, RF: 2.7UH	76493	70F276A1
L1790	108-0711-00			COIL, RF: TRACE ROTATION	80009	108-0711-00
L1794	108-0710-00			COIL, RF: Y AXIS ALIGNMENT	80009	108-0710-00
L1812	108-0728-00			COIL, RF: 116UF	80009	108-0728-00
L1813	108-0728-00			COIL, RF: 116UF	80009	108-0728-00
L1825	108-0742-00			COIL, RF: 83UH, TOROIDAL	80009	108-0742-00
L1835	108-0709-00			COIL, RF: 1.6MH	80009	108-0709-00
L2008	108-0646-00			COIL, RF: 80UH	80009	108-0646-00

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
L2009	108-0646-00			COIL, RF: 80UH	80009	108-0646-00
L2018	108-0680-00			COIL, RF: 27UH	80009	108-0680-00
L2019	108-0680-00			COIL, RF: 27UH	80009	108-0680-00
L2038	108-0680-00			COIL, RF: 27UH	80009	108-0680-00
L2039	108-0680-00			COIL, RF: 27UH	80009	108-0680-00
L2101	120-0285-00			XFMR, TOROID: 4 TURNS SINGLE	80009	120-0285-00
L2117	108-0538-00			COIL, RF: 2.7UH	76493	70F276A1
LR202	108-0367-00			COIL, RF: 1UH	80009	108-0367-00
LR203	108-0367-00			COIL, RF: 1UH	80009	108-0367-00
LR239	108-0729-00			COIL, RF: 195NH	80009	108-0729-00
LR261	108-0729-00			COIL, RF: 195NH	80009	108-0729-00
LR264	108-0729-00			COIL, RF: 195NH	80009	108-0729-00
LR302	108-0367-00			COIL, RF: 1UH	80009	108-0367-00
LR303	108-0367-00			COIL, RF: 1UH	80009	108-0367-00
LR339	108-0729-00			COIL, RF: 195NH	80009	108-0729-00
LR361	108-0729-00			COIL, RF: 195NH	80009	108-0729-00
LR364	108-0729-00			COIL, RF: 195NH	80009	108-0729-00
LR652	108-0407-00			COIL, RF: 20NH	80009	108-0407-00
LR654	108-0407-00			COIL, RF: 20NH	80009	108-0407-00
LR655	108-0407-00			COIL, RF: 20NH	80009	108-0407-00
LR656	108-0407-00			COIL, RF: 20NH	80009	108-0407-00
LR690	108-0685-00			COIL, RF: 80NH	80009	108-0685-00
LR692	108-0325-00			COIL, RF: 0.5UH	80009	108-0325-00
LR694	108-0685-00			COIL, RF: 80NH	80009	108-0685-00
LR902	108-0298-00			COIL, RF: FIXED, 235NH	80009	108-0298-00
M2089	149-0030-00	B010100	B069999X	METER, T TOTLZ: ELAPSED TIME, DC, CKT BD MT	18583	120-LC
Q1	151-0188-00	XB155790		TRANSISTOR: SILICON, PNP (Q1, 485, 485-1 ONLY)	80009	151-0188-00
Q34A, B	151-1032-00			TRANSISTOR: SILICON, FET, DUAL (Q34A, B, 485, 485-1 ONLY)	80009	151-1032-00
Q40	151-0367-00			TRANSISTOR: SILICON, NPN, SEL FROM 3571TP (Q40, 485, 485-1 ONLY)	80009	151-0367-00
Q50	151-0367-00			TRANSISTOR: SILICON, NPN, SEL FROM 3571TP (Q50, 485, 485-1 ONLY)	80009	151-0367-00
Q52	151-0271-00			TRANSISTOR: SILICON, PNP (Q52, 485, 485-1 ONLY)	80009	151-0271-00
Q56	151-0212-00			TRANSISTOR: SILICON, NPN (Q56, 485, 485-1 ONLY)	80009	151-0212-00
Q60	153-0604-00	B010100	B143554	TRANSISTOR: SILICON, NPN (485, 485-1 ONLY)	80009	153-0604-00
Q60	153-0645-00	B143555	B149999	TRANSISTOR: MATCHED SET (Q60, Q62, Q70 FURNISHED AS A MATCHED SET) 485, 485-1 ONLY)	80009	153-0645-00
Q60	151-0271-00	B150000		TRANSISTOR: SILICON, PNP (485, 485-1 ONLY)	80009	151-0271-00
Q62	153-0604-00	B010100	B143554	TRANSISTOR: SILICON, NPN (485, 485-1 ONLY)	80009	153-0604-00
Q62	153-0645-00	B143555	B149999	TRANSISTOR: MATCHED SET (Q62, Q60, Q70 FURNISHED AS A MATCHED SET. 485, 485-1 ONLY)	80009	153-0645-00
Q62	151-0271-00	B150000		TRANSISTOR: SILICON, PNP (485, 485-1 ONLY)	80009	151-0271-00
Q70	153-0604-00	B010100	B143554	TRANSISTOR: SILICON, NPN (485, 485-1 ONLY)	80009	153-0604-00
Q70	153-0645-00	B143555	B149999	TRANSISTOR: MATCHED SET (Q70, Q60, Q62 FURNISHED AS A MATCHED SET) 485, 485-1 ONLY)	80009	153-0645-00

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
Q70	151-0271-00	B150000		TRANSISTOR: SILICON, PNP	80009	151-0271-00
Q70	-----			(485,485-1 ONLY)		
Q274	151-0224-00			TRANSISTOR: SILICON, NPN	80009	151-0224-00
Q284	151-0224-00			TRANSISTOR: SILICON, NPN	80009	151-0224-00
Q290	151-0260-00			TRANSISTOR: SILICON, NPN	80009	151-0260-00
Q374	151-0224-00			TRANSISTOR: SILICON, NPN	80009	151-0224-00
Q384	151-0224-00			TRANSISTOR: SILICON, NPN	80009	151-0224-00
Q416	151-0224-00			TRANSISTOR: SILICON, NPN	80009	151-0224-00
Q436	151-0224-00			TRANSISTOR: SILICON, NPN	80009	151-0224-00
Q440	151-0333-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS918	80009	151-0333-00
Q444	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q454	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q456	151-0333-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS918	80009	151-0333-00
Q460	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q462	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q518	151-0224-00			TRANSISTOR: SILICON, NPN	80009	151-0224-00
Q538	151-0224-00			TRANSISTOR: SILICON, NPN	80009	151-0224-00
Q544	151-0271-00			TRANSISTOR: SILICON, PNP	80009	151-0271-00
Q546	151-0221-00			TRANSISTOR: SILICON, PNP	80009	151-0221-00
Q552	151-0221-00			TRANSISTOR: SILICON, PNP	80009	151-0221-00
Q556	151-0221-00			TRANSISTOR: SILICON, PNP	80009	151-0221-00
Q564	151-0271-00			TRANSISTOR: SILICON, PNP	80009	151-0271-00
Q572	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q576	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q682	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q686	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q688	151-0503-00			SCR: SILICON, TO-92	04713	2N5060
Q712A, B	151-1042-00			SEMICON DVC SE: MATCHED PAIR FET	80009	151-1042-00
Q716	151-0362-00			TRANSISTOR: SILICON, PNP, SEL FROM 2N4258	80009	151-0362-00
Q728	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q768	151-0223-00			TRANSISTOR: SILICON, NPN	80009	151-0223-00
Q778	151-0223-00			TRANSISTOR: SILICON, NPN	80009	151-0223-00
Q792	151-0367-00			TRANSISTOR: SILICON, NPN, SEL FROM 3571TP	80009	151-0367-00
Q794	151-0367-00			TRANSISTOR: SILICON, NPN, SEL FROM 3571TP	80009	151-0367-00
Q802	151-0221-00			TRANSISTOR: SILICON, PNP	80009	151-0221-00
Q804	151-0221-00			TRANSISTOR: SILICON, PNP	80009	151-0221-00
Q810	151-0367-00			TRANSISTOR: SILICON, NPN, SEL FROM 3571TP	80009	151-0367-00
Q816	151-0223-00			TRANSISTOR: SILICON, NPN	80009	151-0223-00
Q822	151-0221-00			TRANSISTOR: SILICON, PNP	80009	151-0221-00
Q852	151-0367-00			TRANSISTOR: SILICON, NPN, SEL FROM 3571TP	80009	151-0367-00
Q854	151-0283-00			TRANSISTOR: SILICON, NPN	07263	S032790
Q856	151-0221-00			TRANSISTOR: SILICON, PNP	80009	151-0221-00
Q858	151-0289-00			TRANSISTOR: SILICON, PNP	80009	151-0289-00
Q862	151-0354-00			TRANSISTOR: SILICON, PNP, DUAL	32293	ITS1200A
Q866	151-0224-00			TRANSISTOR: SILICON, NPN	80009	151-0224-00
Q868	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q884	151-1042-00			SEMICON DVC SE: MATCHED PAIR FET	80009	151-1042-00
Q886						
Q888	151-0223-00	B010100	B010299	TRANSISTOR: SILICON, NPN	80009	151-0223-00
Q888	151-0437-00	B010300		TRANSISTOR: SILICON, NPN, SEL FROM 2N5769	80009	151-0437-00
Q892	151-0133-00	B010100	B010299	TRANSISTOR: SILICON, PNP	80009	151-0133-00
Q892	151-0301-00	B010300		TRANSISTOR: SILICON, PNP	04713	2N2907A
Q896	151-0133-00	B010100	B010299	TRANSISTOR: SILICON, PNP	80009	151-0133-00
Q896	151-0301-00	B010300		TRANSISTOR: SILICON, PNP	04713	2N2907A

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
Q902A, B	151-0139-00			TRANSISTOR: SILICON, NPN	80009	151-0139-00
Q904	151-0224-00			TRANSISTOR: SILICON, NPN	80009	151-0224-00
Q906	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q908	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q914	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q934	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q936	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q942	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q944	151-0224-00			TRANSISTOR: SILICON, NPN	80009	151-0224-00
Q1012A, B	151-1042-00			SEMICON DVC SE: MATCHED PAIR FET	80009	151-1042-00
Q1016	151-0362-00			TRANSISTOR: SILICON, PNP, SEL FROM 2N4258	80009	151-0362-00
Q1028	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q1068	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q1070	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q1072	151-0223-00			TRANSISTOR: SILICON, NPN	80009	151-0223-00
Q1074	151-0221-00			TRANSISTOR: SILICON, PNP	80009	151-0221-00
Q1078	151-0223-00			TRANSISTOR: SILICON, NPN	80009	151-0223-00
Q1082	151-0367-00			TRANSISTOR: SILICON, NPN, SEL FROM 3571TP	80009	151-0367-00
Q1084	151-0221-00			TRANSISTOR: SILICON, PNP	80009	151-0221-00
Q1092	151-0221-00			TRANSISTOR: SILICON, PNP	80009	151-0221-00
Q1096	151-0221-00			TRANSISTOR: SILICON, PNP	80009	151-0221-00
Q1102	151-0219-00			TRANSISTOR: SILICON, PNP	80009	151-0219-00
Q1106	151-0367-00			TRANSISTOR: SILICON, NPN, SEL FROM 3571TP	80009	151-0367-00
Q1108	151-0223-00			TRANSISTOR: SILICON, NPN	80009	151-0223-00
Q1110	151-0367-00			TRANSISTOR: SILICON, NPN, SEL FROM 3571TP	80009	151-0367-00
Q1114	151-0367-00			TRANSISTOR: SILICON, NPN, SEL FROM 3571TP	80009	151-0367-00
Q1121	151-0221-00			TRANSISTOR: SILICON, PNP	80009	151-0221-00
Q1124	151-0221-00			TRANSISTOR: SILICON, PNP	80009	151-0221-00
Q1154	151-0160-00			TRANSISTOR: SILICON, NPN	80009	151-0160-00
Q1164	151-0285-00			TRANSISTOR: SILICON, PNP	80009	151-0285-00
Q1168	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q1172	151-0124-00			TRANSISTOR: SILICON, NPN, SEL FROM 2N3501	80009	151-0124-00
Q1174	151-0270-00			TRANSISTOR: SILICON, PNP	80009	151-0270-00
Q1182	151-0124-00			TRANSISTOR: SILICON, NPN, SEL FROM 2N3501	80009	151-0124-00
Q1184	151-0270-00			TRANSISTOR: SILICON, PNP	80009	151-0270-00
Q1192	151-0127-00			TRANSISTOR: SILICON, NPN	80009	151-0127-00
Q1196	151-0127-00			TRANSISTOR: SILICON, NPN	80009	151-0127-00
Q1202	151-0367-00			TRANSISTOR: SILICON, NPN, SEL FROM 3571TP	80009	151-0367-00
Q1204	151-0221-00			TRANSISTOR: SILICON, PNP	80009	151-0221-00
Q1206	151-0283-00			TRANSISTOR: SILICON, NPN	07263	S032790
Q1208	151-0289-00			TRANSISTOR: SILICON, PNP	80009	151-0289-00
Q1212	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q1218	151-0224-00			TRANSISTOR: SILICON, NPN	80009	151-0224-00
Q1222	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q1232	151-1042-00			SEMICON DVC SE: MATCHED PAIR FET	80009	151-1042-00
Q1234						
Q1236	151-0223-00	B010100	B010299	TRANSISTOR: SILICON, NPN	80009	151-0223-00
Q1236	151-0437-00	B010300		TRANSISTOR: SILICON, NPN, SEL FROM 2N5769	80009	151-0437-00
Q1238	151-0224-00			TRANSISTOR: SILICON, NPN	80009	151-0224-00
Q1252	151-0133-00	B010100	B010299	TRANSISTOR: SILICON, PNP	80009	151-0133-00
Q1252	151-0301-00	B010300		TRANSISTOR: SILICON, PNP	04713	2N2907A
Q1266	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q1268	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q1272	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q1302	151-0224-00			TRANSISTOR: SILICON, NPN	80009	151-0224-00
Q1304	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
Q1306	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q1312	151-0223-00			TRANSISTOR: SILICON, NPN	80009	151-0223-00
Q1318	151-0221-00			TRANSISTOR: SILICON, PNP	80009	151-0221-00
Q1322	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q1328	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q1331	151-0224-00			TRANSISTOR: SILICON, NPN	80009	151-0224-00
Q1336	151-0223-00	B010100	B010301	TRANSISTOR: SILICON, NPN	80009	151-0223-00
Q1336	151-0127-00	B010302		TRANSISTOR: SILICON, NPN	80009	151-0127-00
Q1338	151-0127-00			TRANSISTOR: SILICON, NPN	80009	151-0127-00
Q1342	151-0224-00			TRANSISTOR: SILICON, NPN	80009	151-0224-00
Q1356	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q1358	151-0223-00			TRANSISTOR: SILICON, NPN	80009	151-0223-00
Q1362	151-0223-00			TRANSISTOR: SILICON, NPN	80009	151-0223-00
Q1364	151-0221-00			TRANSISTOR: SILICON, PNP	80009	151-0221-00
Q1366	151-0224-00			TRANSISTOR: SILICON, NPN	80009	151-0224-00
Q1372	151-0221-00			TRANSISTOR: SILICON, PNP	80009	151-0221-00
Q1374	151-0221-00			TRANSISTOR: SILICON, PNP	80009	151-0221-00
Q1378	151-0223-00			TRANSISTOR: SILICON, NPN	80009	151-0223-00
Q1482	151-0301-00			TRANSISTOR: SILICON, PNP	04713	2N2907A
Q1504	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q1520	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q1544	151-0341-00			TRANSISTOR: SILICON, NPN	80009	151-0341-00
Q1546	151-0219-00			TRANSISTOR: SILICON, PNP	80009	151-0219-00
Q1548	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q1566	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q1568	151-0341-00			TRANSISTOR: SILICON, NPN	80009	151-0341-00
Q1582	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q1590	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q1594	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q1614	151-0279-00			TRANSISTOR: SILICON, NPN	80009	151-0279-00
Q1618	151-0280-00			TRANSISTOR: SILICON, PNP	80009	151-0280-00
Q1716	151-0219-00			TRANSISTOR: SILICON, PNP	80009	151-0219-00
Q1718	151-0219-00			TRANSISTOR: SILICON, PNP	80009	151-0219-00
Q1728	151-0279-00			TRANSISTOR: SILICON, NPN	80009	151-0279-00
Q1732	151-0280-00			TRANSISTOR: SILICON, PNP	80009	151-0280-00
Q1736	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q1742	151-0220-00			TRANSISTOR: SILICON, PNP	80009	151-0220-00
Q1748	151-0160-00			TRANSISTOR: SILICON, NPN	80009	151-0160-00
Q1750	151-0271-00			TRANSISTOR: SILICON, PNP	80009	151-0271-00
Q1752	151-0124-00			TRANSISTOR: SILICON, NPN, SEL FROM 2N3501	80009	151-0124-00
Q1772	151-0270-00			TRANSISTOR: SILICON, PNP	80009	151-0270-00
Q1774	151-0192-00			TRANSISTOR: SILICON, NPN, SEL FROM MPS6521	80009	151-0192-00
Q1834	151-0368-00			TRANSISTOR: SILICON, NPN	80009	151-0368-00
Q1840	151-0260-00			TRANSISTOR: SILICON, NPN	80009	151-0260-00
Q1844	151-0368-00			TRANSISTOR: SILICON, NPN	80009	151-0368-00
Q1846	151-0519-00			SCR: SILICON	04713	SCR5016K
Q1900	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q1902	151-0302-00			TRANSISTOR: SILICON, NPN	80009	151-0302-00
Q2046	151-0136-00			TRANSISTOR: SILICON, NPN	80009	151-0136-00
Q2056	151-0260-00			TRANSISTOR: SILICON, NPN	80009	151-0260-00
Q2066	151-0334-00			TRANSISTOR: SILICON, NPN	80009	151-0334-00
Q2076	151-0335-00	B010100	B143849	TRANSISTOR: SILICON, PNP	80009	151-0335-00
Q2076	151-0324-00	B143850		TRANSISTOR: SILICON, PNP	80009	151-0324-00
Q2086	151-0134-00			TRANSISTOR: SILICON, PNP	80009	151-0134-00
Q2106	151-0219-00	B010100	B142363	TRANSISTOR: SILICON, PNP	80009	151-0219-00

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
Q2106	151-0410-00	B142364		TRANSISTOR:SILICON,PNP	80009	151-0410-00
Q2112	151-0219-00	B010100	B142363	TRANSISTOR:SILICON,PNP	80009	151-0219-00
Q2112	151-0410-00	B142364		TRANSISTOR:SILICON,PNP	80009	151-0410-00
Q2114	151-0212-00			TRANSISTOR:SILICON,NPN	80009	151-0212-00
Q2124	151-0212-00			TRANSISTOR:SILICON,NPN	80009	151-0212-00
R1	317-0100-00	B010100	B155789	RES.,FXD,CMPSN:10 OHM,5%,0.125W (485,485-1 ONLY)	01121	BB1005
R1	317-0047-00	B155790		RES.,FXD,CMPSN:4.7 OHM,5%,0.125W (485,485-1 ONLY)	01121	BB47G5
R3	317-0100-00			RES.,FXD,CMPSN:10 OHM,5%,0.125W (R3, 485,485-1 ONLY)	01121	BB1005
R4	315-0681-00	XB155790		RES.,FXD,CMPSN:680 OHM,5%,0.25W (R4, 485,485-1 ONLY)	01121	CB6815
R5	315-0752-00	XB155790		RES.,FXD,CMPSN:7.5K OHM,5%,0.25W (R5, 485,485-1 ONLY)	01121	CB7525
R6	317-0361-00			RES.,FXD,CMPSN:360 OHM,5%,0.125W	01121	BB3615
R12	315-0201-00			RES.,FXD,CMPSN:200 OHM,5%,0.25W (R12, 485,485-1 ONLY)	01121	CB2015
R14	317-0680-00			RES.,FXD,CMPSN:68 OHM,5%,0.125W (R14, 485,485-1 ONLY)	01121	BB6805
R16	317-0105-00			RES.,FXD,CMPSN:1M OHM,5%,0.125W (R16, 485,485-1 ONLY)	01121	BB1055
R17	307-0106-00			RES.,FXD,CMPSN:4.7 OHM,5%,0.25W (R17, 485,485-1 ONLY)	01121	CB47G5
R18	317-0620-00			RES.,FXD,CMPSN:62 OHM,5%,0.125W (R18, 485,485-1 ONLY)	01121	BB6205
R23	317-0100-00			RES.,FXD,CMPSN:10 OHM,5%,0.125W (R23, 485,485-1 ONLY)	01121	BB1005
R26	317-0240-00			RES.,FXD,CMPSN:24 OHM,5%,0.125W (R26, 485,485-1 ONLY)	01121	BB2405
R27	317-0120-00			RES.,FXD,CMPSN:12 OHM,5%,0.125W (R27, 485,485-1 ONLY)	01121	BB1205
R28	317-0120-00			RES.,FXD,CMPSN:12 OHM,5%,0.125W (R28, 485,485-1 ONLY)	01121	BB1205
R29	317-0100-00			RES.,FXD,CMPSN:10 OHM,5%,0.125W (R29, 485,485-1 ONLY)	01121	BB1005
R31	322-0481-01			RES.,FXD,FILM:1M OHM,0.5%,0.25W (R31, 485,485-1 ONLY)	75042	CEBT0-1004D
R32	317-0100-00			RES.,FXD,CMPSN:10 OHM,5%,0.125W (R32, 485,485-1 ONLY)	01121	BB1005
R33	315-0474-00			RES.,FXD,CMPSN:470K OHM,5%,0.25W (R33, 485,485-1 ONLY)	01121	CB4745
R36	325-0048-00			RES.,FXD,FILM:1M OHM,1%,0.2W (R36, 485,485-1 ONLY)	75042	MMCT0-21ROF
R38	325-0048-00			RES.,FXD,FILM:1M OHM,1%,0.2W (R38, 485,485-1 ONLY)	75042	MMCT0-21ROF
R40	317-0122-00			RES.,FXD,CMPSN:1.2K OHM,5%,0.125W (R40, 485,485-1 ONLY)	01121	BB1225
R42	317-0393-00			RES.,FXD,CMPSN:39K OHM,5%,0.125W (R42, 485,485-1 ONLY)	01121	BB3935
R43	317-0560-00			RES.,FXD,CMPSN:56 OHM,5%,0.125W (R43, 485,485-1 ONLY)	01121	BB5605
R45	311-1035-00			RES.,VAR,NONWIR:50K OHM,10%,0.50W (R45, 485,485-1 ONLY)	73138	82-40-0
R46	315-0395-00			RES.,FXD,CMPSN:3.9M OHM,5%,0.25W (R46, 485,485-1 ONLY)	01121	CB3955

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Discont	Name & Description	Mfr Code	Mfr Part Number
R47	317-0824-00			RES., FXD, CMPSN: 820K OHM, 5%, 0.125W (R47, 485, 485-1 ONLY)	01121	BB8245
R49	317-0390-00			RES., FXD, CMPSN: 39 OHM, 5%, 0.125W (R49, 485, 485-1 ONLY)	01121	BB3905
R50	317-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.125W (R50, 485, 485-1 ONLY)	01121	BB1015
R51	317-0122-00			RES., FXD, CMPSN: 1.2K OHM, 5%, 0.125W (R51, 485, 485-1 ONLY)	01121	BB1225
R53	311-0643-00			RES., VAR, NONWIR: 50 OHM, 10%, 0.50W (R53, 485, 485-1 ONLY)	73138	82-33-2
R54	317-0910-00			RES., FXD, CMPSN: 91 OHM, 5%, 0.125W (R54, 485, 485-1 ONLY)	01121	BB9105
R55	311-0605-00			RES., VAR, NONWIR: 200 OHM, 10%, 0.50W (R55, 485, 485-1 ONLY)	73138	82-23-1
R56	317-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.125W (R56, 485, 485-1 ONLY)	01121	BB1525
R57	317-0431-00			RES., FXD, CMPSN: 430 OHM, 5%, 0.125W (R57, 485, 485-1 ONLY)	01121	BB4315
R59	317-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.125W (R59, 485, 485-1 ONLY)	01121	BB1015
R60	317-0390-00			RES., FXD, CMPSN: 39 OHM, 5%, 0.125W (R60, 485, 485-1 ONLY)	01121	BB3905
R61	317-0027-00			RES., FXD, CMPSN: 2.7 OHM, 5%, 0.125W (R61, 485, 485-1 ONLY)	01121	BB2R705
R62	317-0362-00			RES., FXD, CMPSN: 3.6K OHM, 5%, 0.125W (R62, 485, 485-1 ONLY)	01121	BB3625
R63	317-0390-00			RES., FXD, CMPSN: 39 OHM, 5%, 0.125W (R63, 485, 485-1 ONLY)	01121	BB3905
R64	317-0561-00			RES., FXD, CMPSN: 560 OHM, 5%, 0.125W (R64, 485, 485-1 ONLY)	01121	BB5615
R65	317-0332-00			RES., FXD, CMPSN: 3.3K OHM, 5%, 0.125W (R65, 485, 485-1 ONLY)	01121	BB3325
R66	317-0330-00	B010100	B020432X	RES., FXD, CMPSN: 33 OHM, 5%, 0.125W (485, 485-1 ONLY)	01121	BB3305
R66	317-0330-00	XB020436		RES., FXD, CMPSN: 33 OHM, 5%, 0.125W (R485, 485-1 ONLY)	01121	BB3305
R67	317-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.125W (R67, 485, 485-1 ONLY)	01121	BB5105
R68	317-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.125W (R68, 485, 485-1 ONLY)	01121	BB1025
R69	317-0470-00			RES., FXD, CMPSN: 47 OHM, 5%, 0.125W (R69, 485, 485-1 ONLY)	01121	BB4705
R70	317-0330-00			RES., FXD, CMPSN: 33 OHM, 5%, 0.125W (R70, 485, 485-1 ONLY)	01121	BB3305
R71	317-0911-00			RES., FXD, CMPSN: 910 OHM, 5%, 0.125W (R71, 485, 485-1 ONLY)	01121	BB9115
R72	301-0820-00			RES., FXD, CMPSN: 82 OHM, 5%, 0.50W (R72, 485, 485-1 ONLY)	01121	EB8205
R74	317-0047-00			RES., FXD, CMPSN: 4.7 OHM, 5%, 0.125W (R74, 485, 485-1 ONLY)	01121	BB47G5
R75	317-0393-00			RES., FXD, CMPSN: 39K OHM, 5%, 0.125W (R75, 485, 485-1 ONLY)	01121	BB3935
R76	315-0205-00			RES., FXD, CMPSN: 2M OHM, 5%, 0.25W (R76, 485, 485-1 ONLY)	01121	CB2055
R77	317-0304-00			RES., FXD, CMPSN: 300K OHM, 5%, 0.125W (R77, 485, 485-1 ONLY)	01121	BB3045

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R78	311-0698-00 -----			RES., VAR, NONWIR: 1M OHM, 0.50W (R78, 485, 485-1 ONLY)	73138	82-36-0
R81	321-0260-00 -----			RES., FXD, FILM: 4.99K OHM, 1%, 0.125W (R81, 485, 485-1 ONLY)	91637	MFF1816G49900F
R82	315-0100-00 -----			RES., FXD, CMPSN: 10 OHM, 5%, 0.25W (R82, 485, 485-1 ONLY)	01121	CB1005
R83	315-0103-00 -----			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W (R83, 485, 485-1 ONLY)	01121	CB1035
R84	321-0094-00			RES., FXD, FILM: 93.1 OHM, 1%, 0.125W	91637	MFF1816G93R10F
R87	317-0201-00	B010100	B109999	RES., FXD, CMPSN: 200 OHM, 5%, 0.125W	01121	BB2015
R87	317-0181-00	B110000		RES., FXD, CMPSN: 180 OHM, 5%, 0.125W	01121	BB1815
R90	311-0566-00			RES., VAR, NONWIR: 5K OHM, 20%	12697	381-CM39672
R93	315-0621-00	B010100	B166699	RES., FXD, CMPSN: 620 OHM, 5%, 0.25W	01121	CB6215
R93	315-0331-00	B166700		RES., FXD, CMPSN: 330 OHM, 5%, 0.25W	01121	CB3315
R96	317-0220-00			RES., FXD, CMPSN: 22 OHM, 5%, 0.125W	01121	BB2205
R101	317-0394-00			RES., FXD, CMPSN: 390K OHM, 5%, 0.125W	01121	BB3945
R102	317-0394-00			RES., FXD, CMPSN: 390K OHM, 5%, 0.125W	01121	BB3945
R104	317-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.125W	01121	BB5105
R107	321-0286-00			RES., FXD, FILM: 9.31K OHM, 1%, 0.125W	91637	MFF1816G93100F
R111	322-0692-03			RES., FXD, FILM: 122.2 OHM, 0.25%, 0.25W	91637	MFF1421D122R2C
R112	322-0692-03			RES., FXD, FILM: 122.2 OHM, 0.25%, 0.25W	91637	MFF1421D122R2C
R113	321-0938-03			RES., FXD, FILM: 247.5 OHM, 0.25%, 0.125W	91637	MFF1816D247R5C
R114	321-0939-03			RES., FXD, FILM: 122.2 OHM, 0.25%, 0.125W	91637	MFF1816D122R2C
R115	321-0939-03			RES., FXD, FILM: 122.2 OHM, 0.25%, 0.125W	91637	MFF1816D122R2C
R121	321-0939-03			RES., FXD, FILM: 122.2 OHM, 0.25%, 0.125W	91637	MFF1816D122R2C
R122	321-0939-03			RES., FXD, FILM: 122.2 OHM, 0.25%, 0.125W	91637	MFF1816D122R2C
R123	321-0938-03			RES., FXD, FILM: 247.5 OHM, 0.25%, 0.125W	91637	MFF1816D247R5C
R124	321-0939-03			RES., FXD, FILM: 122.2 OHM, 0.25%, 0.125W	91637	MFF1816D122R2C
R125	321-0939-03			RES., FXD, FILM: 122.2 OHM, 0.25%, 0.125W	91637	MFF1816D122R2C
R127	317-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.125W	01121	BB5105
R131	321-0808-03			RES., FXD, FILM: 800 OHM, 0.25%, 0.125W	91637	MFF1816D300R0C
R132	321-0808-03			RES., FXD, FILM: 800 OHM, 0.25%, 0.125W	91637	MFF1816D300R0C
R133	321-0085-03			RES., FXD, FILM: 75 OHM, 0.25%, 0.125W	24546	NC55C75R0C
R134	321-0085-03			RES., FXD, FILM: 75 OHM, 0.25%, 0.125W	24546	NC55C75R0C
R135	321-0114-03			RES., FXD, FILM: 150 OHM, 0.25%, 0.125W	91637	MFF1816D150R0C
R141	321-0940-03			RES., FXD, FILM: 116.7 OHM, 0.25%, 0.125W	91637	MFF1816D116R7C
R143	325-0108-00			RES., FXD, FILM: 105 OHM, 0.5%, 0.05W	14298	AME50-C105R0D
R144	325-0108-00			RES., FXD, FILM: 105 OHM, 0.5%, 0.05W	14298	AME50-C105R0D
R145	321-0940-03			RES., FXD, FILM: 116.7 OHM, 0.25%, 0.125W	91637	MFF1816D116R7C
R201	323-0172-06			RES., FXD, FILM: 604 OHM, 0.25%, 0.50W	91637	MFF1226C604R0C
R204	323-0172-06			RES., FXD, FILM: 604 OHM, 0.25%, 0.50W	91637	MFF1226C604R0C
R205	316-0101-00			RES., FXD, CMPSN: 100 OHM, 10%, 0.25W	01121	CB1011
R206	311-1228-00			RES., VAR, NONWIR: 10K OHM, 20%, 0.50W	32997	3386F-T04-103
R207	315-0153-00			RES., FXD, CMPSN: 15K OHM, 5%, 0.25W	01121	CB1535
R208	311-0635-00			RES., VAR, NONWIR: 1K OHM, 10%, 0.50W	73138	82-32-0
R209	321-0073-00			RES., FXD, FILM: 56.2 OHM, 1%, 0.125W	91637	MFF1816G56R20F
R212	321-0136-00	B010100	B119999	RES., FXD, FILM: 255 OHM, 1%, 0.125W	91637	MFF1816G255R0F
R212	321-0139-00	B120000		RES., FXD, FILM: 274 OHM, 1%, 0.125W	91637	MFF1816G274R0F
R213	321-0136-00	B010100	B119999	RES., FXD, FILM: 255 OHM, 1%, 0.125W	91637	MFF1816G255R0F
R213	321-0139-00	B120000		RES., FXD, FILM: 274 OHM, 1%, 0.125W	91637	MFF1816G274R0F
R214	311-0605-00			RES., VAR, NONWIR: 200 OHM, 10%, 0.50W	73138	82-23-1
R215	311-0643-00	B010100	B119999	RES., VAR, NONWIR: 50 OHM, 10%, 0.50W	73138	82-33-2
R215	311-1007-00	B120000		RES., VAR, NONWIR: 20 OHM, 20%, 0.50W	73138	82-38-0
R217	315-0430-00			RES., FXD, CMPSN: 43 OHM, 5%, 0.25W	01121	CB4305
R220	311-0091-00			RES., VAR, NONWIR: 1K OHM, 10%, 0.50W	01121	W-3083E

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Discont	Name & Description	Mfr Code	Mfr Part Number
R221	315-0681-00	B010100	B144129	RES., FXD, CMPSN: 680 OHM, 5%, 0.25W	01121	CB6815
R221	315-0621-00	B144130		RES., FXD, CMPSN: 620 OHM, 5%, 0.25W	01121	CB6215
R223	315-0562-00			RES., FXD, CMPSN: 5.6K OHM, 5%, 0.25W	01121	CB5625
R225	321-0273-00			RES., FXD, FILM: 6.81K OHM, 1%, 0.125W	91637	MFF1816G68100F
R226	321-0320-00			RES., FXD, FILM: 21K OHM, 1%, 0.125W	91637	MFF1816G21001F
R227	321-0273-00			RES., FXD, FILM: 6.81K OHM, 1%, 0.125W	91637	MFF1816G68100F
R228	321-0246-00			RES., FXD, FILM: 3.57K OHM, 1%, 0.125W	91637	MFF1816G35700F
R230	311-0091-00			RES., VAR, NONWIR: 1K OHM, 10%, 0.50W	01121	W-3083E
R240	311-0978-00			RES., VAR, NONWIR: 250 OHM, 10%, 0.50W	80740	62-67-3
R242	307-0115-00			RES., FXD, CMPSN: 7.5 OHM, 5%, 0.25W	01121	CB75G5
R244	325-0053-00			RES., FXD, FILM: 50 OHM, 1%, 0.05W	03888	PME50C50R00F
R247	325-0053-00			RES., FXD, FILM: 50 OHM, 1%, 0.05W	03888	PME50C50R00F
R250	311-0643-00			RES., VAR, NONWIR: 50 OHM, 10%, 0.50W	73138	82-33-2
R251	321-0124-00			RES., FXD, FILM: 191 OHM, 1%, 0.125W	91637	MFF1816G191R0F
R252	321-0124-00			RES., FXD, FILM: 191 OHM, 1%, 0.125W	91637	MFF1816G191R0F
R253	317-0112-00			RES., FXD, CMPSN: 1.1K OHM, 5%, 0.125W	01121	BB1125
R254	317-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.125W	01121	BB1025
R255	311-0635-00			RES., VAR, NONWIR: 1K OHM, 10%, 0.50W	73138	82-32-0
R257	317-0112-00			RES., FXD, CMPSN: 1.1K OHM, 5%, 0.125W	01121	BB1125
R262	315-0243-00			RES., FXD, CMPSN: 24K OHM, 5%, 0.25W	01121	CB2435
R265	321-0174-00			RES., FXD, FILM: 634 OHM, 1%, 0.125W	91637	MFF1816G634R0F
R266	321-0149-00			RES., FXD, FILM: 348 OHM, 1%, 0.125W	91637	MFF1816G348R0F
R267	315-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.25W	01121	CB5105
R268	315-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.25W	01121	CB5105
R269	315-0300-00	B010100	B049999	RES., FXD, CMPSN: 30 OHM, 5%, 0.25W	01121	CB3005
R269	315-0430-00	B050000		RES., FXD, CMPSN: 43 OHM, 5%, 0.25W	01121	CB4305
R270	311-1197-00			RES., VAR, NONWIR: 20K OHM, 10%, 1W	12697	381-CM39696
R271	321-0330-00	B010100	B049999	RES., FXD, FILM: 26.7K OHM, 1%, 0.125W	91637	MFF1816G26701F
R271	321-0332-00	B050000		RES., FXD, FILM: 28K OHM, 1%, 0.125W	91637	MFF1816G28001F
R272	321-0220-00			RES., FXD, FILM: 1.91K OHM, 1%, 0.125W	91637	MFF1816G19100F
R273	315-0752-00			RES., FXD, CMPSN: 7.5K OHM, 5%, 0.25W	01121	CB7525
R274	321-0189-00			RES., FXD, FILM: 909 OHM, 1%, 0.125W	91637	MFF1816G909R0F
R275	311-0633-00			RES., VAR, NONWIR: 5K OHM, 10%, 0.50W	73138	82-30-0
R276	321-0193-00			RES., FXD, FILM: 1K OHM, 1%, 0.125W	91637	MFF1816G10000F
R279	321-0097-00			RES., FXD, FILM: 100 OHM, 1%, 0.125W	91637	MFF1816G100R0F
R282	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R284	321-0189-00			RES., FXD, FILM: 909 OHM, 1%, 0.125W	91637	MFF1816G909R0F
R286	321-0193-00			RES., FXD, FILM: 1K OHM, 1%, 0.125W	91637	MFF1816G10000F
R287	315-0271-00			RES., FXD, CMPSN: 270 OHM, 5%, 0.25W	01121	CB2715
R289	315-0363-00			RES., FXD, CMPSN: 36K OHM, 5%, 0.25W	01121	CB3635
R290	311-0702-00			RES., VAR, NONWIR: 250 OHM, 10%, 0.50W	12697	382-CM39823
R291	301-0431-00			RES., FXD, CMPSN: 430 OHM, 5%, 0.50W	01121	EB4315
R301	323-0172-06			RES., FXD, FILM: 604 OHM, 0.25%, 0.50W	91637	MFF1226C604ROC
R304	323-0172-06			RES., FXD, FILM: 604 OHM, 0.25%, 0.50W	91637	MFF1226C604ROC
R305	316-0101-00			RES., FXD, CMPSN: 100 OHM, 10%, 0.25W	01121	CB1011
R306	311-1228-00			RES., VAR, NONWIR: 10K OHM, 20%, 0.50W	32997	3386F-T04-103
R307	315-0153-00			RES., FXD, CMPSN: 15K OHM, 5%, 0.25W	01121	CB1535
R308	311-0635-00			RES., VAR, NONWIR: 1K OHM, 10%, 0.50W	73138	82-32-0
R309	321-0073-00			RES., FXD, FILM: 56.2 OHM, 1%, 0.125W	91637	MFF1816G56R20F
R310	311-0622-00	B010100	B119999	RES., VAR, NONWIR: 100 OHM, 10%, 0.50W	32997	3326H-G48-101
R310	311-0643-00	B120000		RES., VAR, NONWIR: 50 OHM, 10%, 0.50W	73138	82-33-2
R312	311-0622-00	B010100	B119999	RES., VAR, NONWIR: 100 OHM, 10%, 0.50W	32997	3326H-G48-101
R312	311-0643-00	B120000		RES., VAR, NONWIR: 50 OHM, 10%, 0.50W	73138	82-33-2
R313	321-0132-00	B010100	B119999	RES., FXD, FILM: 232 OHM, 1%, 0.125W	91637	MFF1816G232R0F
R313	321-0136-00	B120000		RES., FXD, FILM: 255 OHM, 1%, 0.125W	91637	MFF1816G255R0F

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R314	321-0132-00	B010100	B119999	RES., FXD, FILM: 232 OHM, 1%, 0.125W	91637	MFF1816G232ROF
R314	321-0136-00	B120000		RES., FXD, FILM: 255 OHM, 1%, 0.125W	91637	MFF1816G255ROF
R315	311-0605-00			RES., VAR, NONWIR: 200 OHM, 10%, 0.50W	73138	82-23-1
R316	315-0430-00			RES., FXD, CMPSN: 43 OHM, 5%, 0.25W	01121	CB4305
R317	321-0254-00			RES., FXD, FILM: 4.32K OHM, 1%, 0.125W	91637	MFF1816G43200F
R318	311-0660-00			RES., VAR, NONWIR: TRMR, 200K OHM, 0.5W	73138	82-35-0
R319	321-0254-00			RES., FXD, FILM: 4.32K OHM, 1%, 0.125W	91637	MFF1816G43200F
R320	315-0224-00			RES., FXD, CMPSN: 220K OHM, 5%, 0.25W	01121	CB2245
R321	315-0681-00	B010100	B144129	RES., FXD, CMPSN: 680 OHM, 5%, 0.25W	01121	CB6815
R321	315-0621-00	B144130		RES., FXD, CMPSN: 620 OHM, 5%, 0.25W	01121	CB6215
R323	315-0562-00			RES., FXD, CMPSN: 5.6K OHM, 5%, 0.25W	01121	CB5625
R325	321-0273-00			RES., FXD, FILM: 6.81K OHM, 1%, 0.125W	91637	MFF1816G68100F
R326	321-0320-00			RES., FXD, FILM: 21K OHM, 1%, 0.125W	91637	MFF1816G21001F
R327	321-0273-00			RES., FXD, FILM: 6.81K OHM, 1%, 0.125W	91637	MFF1816G68100F
R328	321-0320-00			RES., FXD, FILM: 21K OHM, 1%, 0.125W	91637	MFF1816G21001F
R332	321-0339-00			RES., FXD, FILM: 33.2K OHM, 1%, 0.125W	91637	MFF1816G33201F
R333	321-0308-00			RES., FXD, FILM: 15.8K OHM, 1%, 0.125W	91637	MFF1816G15801F
R340	311-0978-00			RES., VAR, NONWIR: 250 OHM, 10%, 0.50W	80740	62-67-3
R342	307-0115-00			RES., FXD, CMPSN: 7.5 OHM, 5%, 0.25W	01121	CB75G5
R344	325-0053-00			RES., FXD, FILM: 50 OHM, 1%, 0.05W	03888	PME50C50R00F
R347	325-0053-00			RES., FXD, FILM: 50 OHM, 1%, 0.05W	03888	PME50C50R00F
R350	311-0643-00			RES., VAR, NONWIR: 50 OHM, 10%, 0.50W	73138	82-33-2
R353	321-0124-00			RES., FXD, FILM: 191 OHM, 1%, 0.125W	91637	MFF1816G191ROF
R354	321-0124-00			RES., FXD, FILM: 191 OHM, 1%, 0.125W	91637	MFF1816G191ROF
R355	317-0112-00			RES., FXD, CMPSN: 1.1K OHM, 5%, 0.125W	01121	BB1125
R356	317-0112-00			RES., FXD, CMPSN: 1.1K OHM, 5%, 0.125W	01121	BB1125
R357	317-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.125W	01121	BB1025
R358	311-0635-00			RES., VAR, NONWIR: 1K OHM, 10%, 0.50W	73138	82-32-0
R362	315-0243-00			RES., FXD, CMPSN: 24K OHM, 5%, 0.25W	01121	CB2435
R365	321-0174-00			RES., FXD, FILM: 634 OHM, 1%, 0.125W	91637	MFF1816G634ROF
R366	321-0149-00			RES., FXD, FILM: 348 OHM, 1%, 0.125W	91637	MFF1816G348ROF
R367	315-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.25W	01121	CB5105
R368	315-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.25W	01121	CB5105
R369	315-0300-00	B010100	B049999	RES., FXD, CMPSN: 30 OHM, 5%, 0.25W	01121	CB3005
R369	315-0430-00	B050000		RES., FXD, CMPSN: 43 OHM, 5%, 0.25W	01121	CB4305
R370	311-1197-00			RES., VAR, NONWIR: 20K OHM, 10%, 1W	12697	381-CM39696
R371	321-0330-00	B010100	B049999	RES., FXD, FILM: 26.7K OHM, 1%, 0.125W	91637	MFF1816G26701F
R371	321-0332-00	B050000		RES., FXD, FILM: 28K OHM, 1%, 0.125W	91637	MFF1816G28001F
R372	321-0220-00			RES., FXD, FILM: 1.91K OHM, 1%, 0.125W	91637	MFF1816G19100F
R373	315-0752-00			RES., FXD, CMPSN: 7.5K OHM, 5%, 0.25W	01121	CB7525
R374	321-0189-00			RES., FXD, FILM: 909 OHM, 1%, 0.125W	91637	MFF1816G909ROF
R375	311-0633-00			RES., VAR, NONWIR: 5K OHM, 10%, 0.50W	73138	82-30-0
R376	321-0193-00			RES., FXD, FILM: 1K OHM, 1%, 0.125W	91637	MFF1816G10000F
R379	321-0097-00			RES., FXD, FILM: 100 OHM, 1%, 0.125W	91637	MFF1816G100ROF
R382	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R384	321-0189-00			RES., FXD, FILM: 909 OHM, 1%, 0.125W	91637	MFF1816G909ROF
R386	321-0193-00			RES., FXD, FILM: 1K OHM, 1%, 0.125W	91637	MFF1816G10000F
R387	315-0271-00			RES., FXD, CMPSN: 270 OHM, 5%, 0.25W	01121	CB2715
R389	315-0363-00			RES., FXD, CMPSN: 36K OHM, 5%, 0.25W	01121	CB3635
R403	321-0114-00			RES., FXD, FILM: 150 OHM, 1%, 0.125W	91637	MFF1816G150ROF
R404	321-0114-00			RES., FXD, FILM: 150 OHM, 1%, 0.125W	91637	MFF1816G150ROF
R407	317-0100-00			RES., FXD, CMPSN: 10 OHM, 5%, 0.125W	01121	BB1005
R408	317-0100-00			RES., FXD, CMPSN: 10 OHM, 5%, 0.125W	01121	BB1005
R409	317-0241-00			RES., FXD, CMPSN: 240 OHM, 5%, 0.125W	01121	BB2415
R411	321-0001-00			RES., FXD, FILM: 10 OHM, 1%, 0.125W	75042	CEAT0-10R00F

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R412	321-0016-00			RES., FXD, FILM: 14.3 OHM, 1%, 0.125W	91637	MFF1816G14R30F
R413	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R414	321-0175-00			RES., FXD, FILM: 649 OHM, 1%, 0.125W	91637	MFF1816G649R0F
R415	321-0126-00			RES., FXD, FILM: 200 OHM, 1%, 0.125W	91637	MFF1816G200R0F
R416	321-0184-00			RES., FXD, FILM: 806 OHM, 1%, 0.125W	91637	MFF1816G806R0F
R417	321-0122-00			RES., FXD, FILM: 182 OHM, 1%, 0.125W	91637	MFF1816G182R0F
R418	321-0097-00			RES., FXD, FILM: 100 OHM, 1%, 0.125W	91637	MFF1816G100R0F
R419	321-0097-00			RES., FXD, FILM: 100 OHM, 1%, 0.125W	91637	MFF1816G100R0F
R423	321-0114-00			RES., FXD, FILM: 150 OHM, 1%, 0.125W	91637	MFF1816G150R0F
R424	321-0114-00			RES., FXD, FILM: 150 OHM, 1%, 0.125W	91637	MFF1816G150R0F
R427	317-0100-00			RES., FXD, CMPSN: 10 OHM, 5%, 0.125W	01121	BB1005
R428	317-0100-00			RES., FXD, CMPSN: 10 OHM, 5%, 0.125W	01121	BB1005
R433	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R434	321-0175-00			RES., FXD, FILM: 649 OHM, 1%, 0.125W	91637	MFF1816G649R0F
R435	321-0126-00			RES., FXD, FILM: 200 OHM, 1%, 0.125W	91637	MFF1816G200R0F
R436	321-0184-00			RES., FXD, FILM: 806 OHM, 1%, 0.125W	91637	MFF1816G806R0F
R437	321-0122-00			RES., FXD, FILM: 182 OHM, 1%, 0.125W	91637	MFF1816G182R0F
R438	321-0101-00			RES., FXD, FILM: 110 OHM, 1%, 0.125W	91637	MFF1816G110R0F
R439	321-0101-00			RES., FXD, FILM: 110 OHM, 1%, 0.125W	91637	MFF1816G110R0F
R440	321-0197-00			RES., FXD, FILM: 1.1K OHM, 1%, 0.125W	91637	MFF1816G11000F
R441	321-0292-00			RES., FXD, FILM: 10.7K OHM, 1%, 0.125W	91637	MFF1816G10701F
R442	321-0254-00			RES., FXD, FILM: 4.32K OHM, 1%, 0.125W	91637	MFF1816G43200F
R444	321-0260-00			RES., FXD, FILM: 4.99K OHM, 1%, 0.125W	91637	MFF1816G49900F
R446	321-0218-00			RES., FXD, FILM: 1.82K OHM, 1%, 0.125W	91637	MFF1816G18200F
R448	321-0260-00			RES., FXD, FILM: 4.99K OHM, 1%, 0.125W	91637	MFF1816G49900F
R449	315-0164-00			RES., FXD, CMPSN: 160K OHM, 5%, 0.25W	01121	CB1645
R450	311-0642-00			RES., VAR, NONWIR: 20K OHM, 20%, 0.50W	12697	382-CM39820
R451	321-0300-00			RES., FXD, FILM: 13K OHM, 1%, 0.125W	91637	MFF1816G13001F
R452	321-0222-00			RES., FXD, FILM: 2K OHM, 1%, 0.125W	91637	MFF1816G20000F
R453	321-0218-00			RES., FXD, FILM: 1.82K OHM, 1%, 0.125W	91637	MFF1816G18200F
R454	321-0254-00			RES., FXD, FILM: 4.32K OHM, 1%, 0.125W	91637	MFF1816G43200F
R456	321-0197-00			RES., FXD, FILM: 1.1K OHM, 1%, 0.125W	91637	MFF1816G11000F
R457	321-0292-00			RES., FXD, FILM: 10.7K OHM, 1%, 0.125W	91637	MFF1816G10701F
R458	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R461	321-0240-00			RES., FXD, FILM: 3.09K OHM, 1%, 0.125W	91637	MFF1816G30900F
R464	321-0293-00			RES., FXD, FILM: 11K OHM, 1%, 0.125W	91637	MFF1816G11001F
R465	315-0302-00			RES., FXD, CMPSN: 3K OHM, 5%, 0.25W	01121	CB3025
R466	321-0289-00			RES., FXD, FILM: 10K OHM, 1%, 0.125W	91637	MFF1816G10001F
R468	315-0622-00			RES., FXD, CMPSN: 6.2K OHM, 5%, 0.25W	01121	CB6225
R503	321-0126-00			RES., FXD, FILM: 200 OHM, 1%, 0.125W	91637	MFF1816G200R0F
R504	321-0126-00			RES., FXD, FILM: 200 OHM, 1%, 0.125W	91637	MFF1816G200R0F
R505	311-0635-00			RES., VAR, NONWIR: 1K OHM, 10%, 0.50W	73138	82-32-0
R508	321-0068-00			RES., FXD, FILM: 49.9 OHM, 1%, 0.125W	91637	MFF1816G49R90F
R509	321-0068-00			RES., FXD, FILM: 49.9 OHM, 1%, 0.125W	91637	MFF1816G49R90F
R511	321-0051-00			RES., FXD, FILM: 33.2 OHM, 1%, 0.125W	91637	MFF1816G33R20F
R512	307-0109-00			RES., FXD, CMPSN: 8.2 OHM, 5%, 0.25W	01121	CB82G5
R513	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R514	321-0175-00			RES., FXD, FILM: 649 OHM, 1%, 0.125W	91637	MFF1816G649R0F
R515	321-0126-00			RES., FXD, FILM: 200 OHM, 1%, 0.125W	91637	MFF1816G200R0F
R516	321-0184-00			RES., FXD, FILM: 806 OHM, 1%, 0.125W	91637	MFF1816G806R0F
R517	321-0122-00			RES., FXD, FILM: 182 OHM, 1%, 0.125W	91637	MFF1816G182R0F
R518	321-0097-00			RES., FXD, FILM: 100 OHM, 1%, 0.125W	91637	MFF1816G100R0F
R523	321-0126-00			RES., FXD, FILM: 200 OHM, 1%, 0.125W	91637	MFF1816G200R0F
R524	321-0126-00			RES., FXD, FILM: 200 OHM, 1%, 0.125W	91637	MFF1816G200R0F
R525	315-0221-00			RES., FXD, CMPSN: 220 OHM, 5%, 0.25W	01121	CB2215
R528	321-0068-00			RES., FXD, FILM: 49.9 OHM, 1%, 0.125W	91637	MFF1816G49R90F

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Discont	Name & Description	Mfr Code	Mfr Part Number
R529	321-0068-00			RES., FXD, FILM: 49.9 OHM, 1%, 0.125W	91637	MFF1816G49R90F
R531	321-0051-00			RES., FXD, FILM: 33.2 OHM, 1%, 0.125W	91637	MFF1816G33R20F
R532	307-0109-00			RES., FXD, CMPSN: 8.2 OHM, 5%, 0.25W	01121	CB82G5
R533	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R534	321-0175-00			RES., FXD, FILM: 649 OHM, 1%, 0.125W	91637	MFF1816G649R0F
R535	321-0126-00			RES., FXD, FILM: 200 OHM, 1%, 0.125W	91637	MFF1816G200R0F
R536	321-0184-00			RES., FXD, FILM: 806 OHM, 1%, 0.125W	91637	MFF1816G806R0F
R537	321-0122-00			RES., FXD, FILM: 182 OHM, 1%, 0.125W	91637	MFF1816G182R0F
R538	321-0097-00			RES., FXD, FILM: 100 OHM, 1%, 0.125W	91637	MFF1816G100R0F
R541	321-0097-00			RES., FXD, FILM: 100 OHM, 1%, 0.125W	91637	MFF1816G100R0F
R542	321-0097-00			RES., FXD, FILM: 100 OHM, 1%, 0.125W	91637	MFF1816G100R0F
R543	315-0330-00			RES., FXD, CMPSN: 33 OHM, 5%, 0.25W	01121	CB3305
R544	321-0114-00			RES., FXD, FILM: 150 OHM, 1%, 0.125W	91637	MFF1816G150R0F
R545	317-0111-00			RES., FXD, CMPSN: 110 OHM, 5%, 0.125W	01121	BB1115
R546	321-0114-00			RES., FXD, FILM: 150 OHM, 1%, 0.125W	91637	MFF1816G150R0F
R547	321-0140-00			RES., FXD, FILM: 280 OHM, 1%, 0.125W	91637	MFF1816G280R0F
R549	321-0129-00			RES., FXD, FILM: 215 OHM, 1%, 0.125W	91637	MFF1816G215R0F
R550	317-0301-00			RES., FXD, CMPSN: 300 OHM, 5%, 0.125W	01121	BB3015
R552	315-0471-00			RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715
R553	315-0223-00			RES., FXD, CMPSN: 22K OHM, 5%, 0.25W	01121	CB2235
R554	315-0223-00			RES., FXD, CMPSN: 22K OHM, 5%, 0.25W	01121	CB2235
R555	315-0471-00			RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715
R556	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R557	321-1087-01			RES., FXD, FILM: 79.6 OHM, 0.5%, 0.125W	91637	MFF1816G79R60D
R558	315-0222-00			RES., FXD, CMPSN: 2.2K OHM, 5%, 0.25W	01121	CB2225
R559	321-1087-01			RES., FXD, FILM: 79.6 OHM, 0.5%, 0.125W	91637	MFF1816G79R60D
R560	311-1227-00			RES., VAR, NONWIR: 5K OHM, 20%, 0.50W	32997	3386F-T04-502
R562	321-0139-00			RES., FXD, FILM: 274 OHM, 1%, 0.125W	91637	MFF1816G274R0F
R563	315-0430-00	B010100	B089999	RES., FXD, CMPSN: 43 OHM, 5%, 0.25W	01121	CB4305
R563	315-0470-00	B090000		RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705
R565	315-0430-00	B010100	B089999	RES., FXD, CMPSN: 43 OHM, 5%, 0.25W	01121	CB4305
R565	315-0470-00	B090000		RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705
R566	321-0152-00			RES., FXD, FILM: 374 OHM, 1%, 0.125W	91637	MFF1816G374R0F
R567	321-0193-00			RES., FXD, FILM: 1K OHM, 1%, 0.125W	91637	MFF1816G10000F
R568	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R570	321-0222-00			RES., FXD, FILM: 2K OHM, 1%, 0.125W	91637	MFF1816G20000F
R571	321-0168-00			RES., FXD, FILM: 549 OHM, 1%, 0.125W	91637	MFF1816G549R0F
R572	307-0108-00			RES., FXD, CMPSN: 6.8 OHM, 5%, 0.25W	80009	307-0108-00
R574	315-0620-00			RES., FXD, CMPSN: 62 OHM, 5%, 0.25W	01121	CB6205
R575	311-1222-00			RES., VAR, NONWIR: 100 OHM, 20%, 0.50W	32997	3386F-T04-101
R576	321-0168-00			RES., FXD, FILM: 549 OHM, 1%, 0.125W	91637	MFF1816G549R0F
R577	315-0221-00			RES., FXD, CMPSN: 220 OHM, 5%, 0.25W	01121	CB2215
R578	321-0222-00			RES., FXD, FILM: 2K OHM, 1%, 0.125W	91637	MFF1816G20000F
R579	321-0193-00			RES., FXD, FILM: 1K OHM, 1%, 0.125W	91637	MFF1816G10000F
R600	311-1007-00			RES., VAR, NONWIR: 20 OHM, 20%, 0.50W	73138	82-38-0
R601	315-0751-00			RES., FXD, CMPSN: 750 OHM, 5%, 0.25W	01121	CB7515
R602	322-0091-00			RES., FXD, FILM: 86.6 OHM, 1%, 0.25W	91637	MFF1421G86R60F
R603	321-0097-00			RES., FXD, FILM: 100 OHM, 1%, 0.125W	91637	MFF1816G100R0F
R604	321-0097-00			RES., FXD, FILM: 100 OHM, 1%, 0.125W	91637	MFF1816G100R0F
R606	311-0607-00			RES., VAR, NONWIR: 10K OHM, 10%, 0.50W	73138	82P-59-4-103K
R607	311-0633-00			RES., VAR, NONWIR: 5K OHM, 10%, 0.50W	73138	82-30-0
R608	311-1265-00			RES., VAR, NONWIR: 2K OHM, 10%, 0.50W	32997	3329P-L58-202
R609	311-1265-00			RES., VAR, NONWIR: 2K OHM, 10%, 0.50W	32997	3329P-L58-202
R610	321-0300-00			RES., FXD, FILM: 13K OHM, 1%, 0.125W	91637	MFF1816G13001F
R611	317-0200-00			RES., FXD, CMPSN: 20 OHM, 5%, 0.125W	01121	BB2005
R612	317-0200-00			RES., FXD, CMPSN: 20 OHM, 5%, 0.125W	01121	BB2005

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R613	311-1265-00			RES., VAR, NONWIR: 2K OHM, 10%, 0.50W	32997	3329P-L58-202
R614	311-1265-00			RES., VAR, NONWIR: 2K OHM, 10%, 0.50W	32997	3329P-L58-202
R615	311-0605-00			RES., VAR, NONWIR: 200 OHM, 10%, 0.50W	73138	82-23-1
R616	321-0300-00			RES., FXD, FILM: 13K OHM, 1%, 0.125W	91637	MFF1816G13001F
R621	321-0068-00			RES., FXD, FILM: 49.9 OHM, 1%, 0.125W	91637	MFF1816G49R90F
R622	315-0561-00			RES., FXD, CMPSN: 560 OHM, 5%, 0.25W	01121	CB5615
R623	315-0821-00			RES., FXD, CMPSN: 820 OHM, 5%, 0.25W	01121	CB8215
R624	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R625	321-0068-00			RES., FXD, FILM: 49.9 OHM, 1%, 0.125W	91637	MFF1816G49R90F
R626	316-0104-00	B010100	B039999X	RES., FXD, CMPSN: 100K OHM, 10%, 0.25W	01121	CB1041
R627	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R629	311-0635-00			RES., VAR, NONWIR: 1K OHM, 10%, 0.50W	73138	82-32-0
R633	321-0160-00			RES., FXD, FILM: 453 OHM, 1%, 0.125W	91637	MFF1816G453ROF
R634	321-0168-00			RES., FXD, FILM: 549 OHM, 1%, 0.125W	91637	MFF1816G549ROF
R635	315-0221-00			RES., FXD, CMPSN: 220 OHM, 5%, 0.25W	01121	CB2215
R636	315-0822-00			RES., FXD, CMPSN: 8.2K OHM, 5%, 0.25W	01121	CB8225
R637	315-0221-00			RES., FXD, CMPSN: 220 OHM, 5%, 0.25W	01121	CB2215
R638	315-0822-00			RES., FXD, CMPSN: 8.2K OHM, 5%, 0.25W	01121	CB8225
R639	316-0470-00			RES., FXD, CMPSN: 47 OHM, 10%, 0.25W	01121	CB4701
R640	321-0280-00			RES., FXD, FILM: 8.06K OHM, 1%, 0.125W	91637	MFF1816G80600F
R641	321-0280-00			RES., FXD, FILM: 8.06K OHM, 1%, 0.125W	91637	MFF1816G80600F
R642	321-0068-00			RES., FXD, FILM: 49.9 OHM, 1%, 0.125W	91637	MFF1816G49R90F
R643	323-0145-00			RES., FXD, FILM: 316 OHM, 1%, 0.50W	91637	MFF1226G316ROF
R645	317-0121-00			RES., FXD, CMPSN: 120 OHM, 5%, 0.125W	01121	BB1215
R646	323-0145-00			RES., FXD, FILM: 316 OHM, 1%, 0.50W	91637	MFF1226G316ROF
R647	321-0068-00			RES., FXD, FILM: 49.9 OHM, 1%, 0.125W	91637	MFF1816G49R90F
R649	316-0104-00			RES., FXD, CMPSN: 100K OHM, 10%, 0.25W	01121	CB1041
R650	315-0391-00			RES., FXD, CMPSN: 390 OHM, 5%, 0.25W	01121	CB3915
R652	321-0068-03			RES., FXD, FILM: 49.9 OHM, 0.25%, 0.125W	91637	MFF1816D49R90C
R654	321-0068-03			RES., FXD, FILM: 49.9 OHM, 0.25%, 0.125W	91637	MFF1816D49R90C
R655	321-0068-03			RES., FXD, FILM: 49.9 OHM, 0.25%, 0.125W	91637	MFF1816D49R90C
R656	321-0068-03			RES., FXD, FILM: 49.9 OHM, 0.25%, 0.125W	91637	MFF1816D49R90C
R657	321-0025-00			RES., FXD, FILM: 17.8 OHM, 1%, 0.125W	91637	MFF1816G17R80F
R658	323-0055-00			RES., FXD, FILM: 36.5 OHM, 1%, 0.50W	91637	MFF1226G38R00F
R663	322-0097-00			RES., FXD, FILM: 100 OHM, 1%, 0.25W	75042	CEBT0-1000F
R664	322-0097-00			RES., FXD, FILM: 100 OHM, 1%, 0.25W	75042	CEBT0-1000F
R666	322-0097-00			RES., FXD, FILM: 100 OHM, 1%, 0.25W	75042	CEBT0-1000F
R667	322-0097-00			RES., FXD, FILM: 100 OHM, 1%, 0.25W	75042	CEBT0-1000F
R672	321-0105-00			RES., FXD, FILM: 121 OHM, 1%, 0.125W	91637	MFF1816G121ROF
R673	321-0189-00			RES., FXD, FILM: 909 OHM, 1%, 0.125W	91637	MFF1816G909ROF
R681	321-0336-00			RES., FXD, FILM: 30.9 OHM, 1%, 0.125W	91637	MFF1816G30901F
R682	321-0228-00			RES., FXD, FILM: 2.32K OHM, 1%, 0.125W	91637	MFF1816G23200F
R683	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R684	315-0330-00			RES., FXD, CMPSN: 33 OHM, 5%, 0.25W	01121	CB3305
R685	315-0202-00			RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R686	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R687	315-0511-00			RES., FXD, CMPSN: 510 OHM, 5%, 0.25W	01121	CB5115
R691	307-0292-00	B010100	B142299	RES., FXD, FILM: 182.5 OHM	80009	307-0292-00
R691	307-0292-09	B142300		RES., FXD, FILM: 181 OHM, (NOM VALUE), SEL	80009	307-0292-09
R696	307-0113-00			RES., FXD, CMPSN: 5.1 OHM, 5%, 0.25W	01121	CB51G5
R701	315-0240-00			RES., FXD, CMPSN: 24 OHM, 5%, 0.25W	01121	CB2405
R702	317-0471-00			RES., FXD, CMPSN: 470 OHM, 5%, 0.125W	01121	BB4715
R703	322-0621-00			RES., FXD, FILM: 900K OHM, 1%, 0.25W	75042	CEBT0-9003F
R704	321-0389-00			RES., FXD, FILM: 110K OHM, 1%, 0.125W	91637	MFF1816G11002F
R705	301-0104-00			RES., FXD, CMPSN: 100K OHM, 5%, 0.5W	01121	EB1045
R706	315-0750-00			RES., FXD, CMPSN: 75 OHM, 5%, 0.25W	01121	CB7505

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R707	317-0510-00	XB020000		RES., FXD, CMPSN: 51 OHM, 5%, 0.125W	01121	BB5105
R708	301-0104-00		RES., FXD, CMPSN: 100K OHM, 5%, 0.5W	01121	EB1045	
R709	322-0621-00		RES., FXD, FILM: 900K OHM, 1%, 0.25W	75042	CEBT0-9003F	
R711	317-0101-00		RES., FXD, CMPSN: 100 OHM, 5%, 0.125W	01121	BB1015	
R714	315-0621-00		RES., FXD, CMPSN: 620 OHM, 5%, 0.25W	01121	CB6215	
R717	315-0471-00		RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715	
R718	315-0153-00			RES., FXD, CMPSN: 15K OHM, 5%, 0.25W (R718, 485 ONLY)	01121	CB1535
R719	321-0158-00		RES., FXD, FILM: 432 OHM, 1%, 0.125W	91637	MFF1816G432ROF	
R720	311-1192-00		RES., VAR, NONWIR: 10K OHM, 20%, 1W (R720, FURNISHED AS A UNIT WITH S720)	71590	BA-232-001	
R721	315-0102-00		RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025	
R723	315-0390-00		RES., FXD, CMPSN: 39 OHM, 5%, 0.25W	01121	CB3905	
R724	315-0222-00		RES., FXD, CMPSN: 2.2K OHM, 5%, 0.25W	01121	CB2225	
R725	311-0644-00		RES., VAR, NONWIR: 20K OHM, 10%, 0.50W	73138	MODEL 82P	
R727	317-0330-00		RES., FXD, CMPSN: 33 OHM, 5%, 0.125W	01121	BB3305	
R728	315-0471-00		RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715	
R729	317-0101-00		RES., FXD, CMPSN: 100 OHM, 5%, 0.125W	01121	BB1015	
R731	321-0082-00		RES., FXD, FILM: 69.8 OHM, 1%, 0.125W	91637	MFF1816G69R80F	
R732	321-0147-00		RES., FXD, FILM: 332 OHM, 1%, 0.125W	91637	MFF1816G332ROF	
R733	317-0240-00		RES., FXD, CMPSN: 24 OHM, 5%, 0.125W	01121	BB2405	
R734	317-0390-00	XB050000		RES., FXD, CMPSN: 39 OHM, 5%, 0.125W	01121	BB3905
R735	321-0147-00		RES., FXD, FILM: 332 OHM, 1%, 0.125W	91637	MFF1816G332ROF	
R736	321-0082-00		RES., FXD, FILM: 69.8 OHM, 1%, 0.125W	91637	MFF1816G69R80F	
R738	315-0431-00			RES., FXD, CMPSN: 430 OHM, 5%, 0.25W	01121	CB4315
R739	315-0561-00		RES., FXD, CMPSN: 560 OHM, 5%, 0.25W	01121	CB5615	
R741	315-0822-00		RES., FXD, CMPSN: 8.2K OHM, 5%, 0.25W	01121	CB8225	
R742	315-0332-00		RES., FXD, CMPSN: 3.3K OHM, 5%, 0.25W	01121	CB3325	
R743	315-0201-00		RES., FXD, CMPSN: 200 OHM, 5%, 0.25W	01121	CB2015	
R744	317-0300-00		RES., FXD, CMPSN: 30 OHM, 5%, 0.125W	01121	BB3005	
R745	321-0079-00		RES., FXD, FILM: 64.9 OHM, 1%, 0.125W	91637	MFF1816G64R90F	
R746	321-0082-00		RES., FXD, FILM: 69.8 OHM, 1%, 0.125W	91637	MFF1816G69R80F	
R747	321-0177-00		RES., FXD, FILM: 681 OHM, 1%, 0.125W	91637	MFF1816G681ROF	
R748	321-0177-00		RES., FXD, FILM: 681 OHM, 1%, 0.125W	91637	MFF1816G681ROF	
R749	321-0082-00		RES., FXD, FILM: 69.8 OHM, 1%, 0.125W	91637	MFF1816G69R80F	
R750	315-0201-00		RES., FXD, CMPSN: 200 OHM, 5%, 0.25W	01121	CB2015	
R751	317-0330-00		RES., FXD, CMPSN: 33 OHM, 5%, 0.125W	01121	BB3305	
R752	317-0330-00		RES., FXD, CMPSN: 33 OHM, 5%, 0.125W	01121	BB3305	
R753	317-0392-00		RES., FXD, CMPSN: 3.9K OHM, 5%, 0.125W	01121	BB3925	
R754	317-0300-00		RES., FXD, CMPSN: 30 OHM, 5%, 0.125W	01121	BB3005	
R755	311-0643-00		RES., VAR, NONWIR: 50 OHM, 10%, 0.50W	73138	82-33-2	
R756	317-0161-00		RES., FXD, CMPSN: 160 OHM, 5%, 0.125W	01121	BB1615	
R757	317-0161-00		RES., FXD, CMPSN: 160 OHM, 5%, 0.125W	01121	BB1615	
R760	317-0101-00		RES., FXD, CMPSN: 100 OHM, 5%, 0.125W	01121	BB1015	
R761	315-0101-00		RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015	
R762	317-0910-00		RES., FXD, CMPSN: 91 OHM, 5%, 0.125W	01121	BB9105	
R764	317-0101-00		RES., FXD, CMPSN: 100 OHM, 5%, 0.125W	01121	BB1015	
R765	311-0607-00		RES., VAR, NONWIR: 10K OHM, 10%, 0.50W	73138	82P-59-4-103K	
R766	321-0233-00	B010100 B049999 B050000		RES., FXD, FILM: 2.61K OHM, 1%, 0.125W	91637	MFF1816G26100F
R766	321-0229-00		RES., FXD, FILM: 2.37K OHM, 1%, 0.125W	91637	MFF1816G23700F	
R767	315-0201-00		RES., FXD, CMPSN: 200 OHM, 5%, 0.25W	01121	CB2015	
R768	321-0212-00		RES., FXD, FILM: 1.58K OHM, 1%, 0.125W	91637	MFF1816G15800F	
R769	315-0102-00		RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025	
R771	315-0182-00		RES., FXD, CMPSN: 1.8K OHM, 5%, 0.25W	01121	CB1825	
R772	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R773	317-0201-00			RES., FXD, CMPSN: 200 OHM, 5%, 0.125W	01121	BB2015
R774	317-0511-00			RES., FXD, CMPSN: 510 OHM, 5%, 0.125W	01121	BB5115
R775	311-0607-00	B010100	B129999	RES., VAR, NONWIR: 10K OHM, 10%, 0.50W	73138	82P-59-4-103K
R775	311-0633-00	B130000		RES., VAR, NONWIR: 5K OHM, 10%, 0.50W	73138	82-30-0
R776	321-0248-00	B010100	B129999	RES., FXD, FILM: 3.74K OHM, 1%, 0.125W	91637	MFF1816G37400F
R776	321-0232-00	B130000		RES., FXD, FILM: 2.55K OHM, 1%, 0.125W	91637	MFF1816G25500F
R778	321-0232-00	B010100	B129999	RES., FXD, FILM: 2.55K OHM, 1%, 0.125W	91637	MFF1816G25500F
R778	321-0239-00	B130000		RES., FXD, FILM: 3.01K OHM, 1%, 0.125W	91637	MFF1816G30100F
R781	315-0471-00			RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715
R782	315-0390-00			RES., FXD, CMPSN: 39 OHM, 5%, 0.25W	01121	CB3905
R783	315-0390-00			RES., FXD, CMPSN: 39 OHM, 5%, 0.25W	01121	CB3905
R784	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R787	315-0184-00	B010100	B149999	RES., FXD, CMPSN: 180K OHM, 5%, 0.25W	01121	CB1845
R787	315-0224-00	B150000		RES., FXD, CMPSN: 220K OHM, 5%, 0.25W	01121	CB2245
R791	315-0302-00			RES., FXD, CMPSN: 3K OHM, 5%, 0.25W	01121	CB3025
R792	315-0201-00			RES., FXD, CMPSN: 200 OHM, 5%, 0.25W	01121	CB2015
R793	321-0159-00			RES., FXD, FILM: 442 OHM, 1%, 0.125W	91637	MFF1816G442ROF
R796	321-0157-00			RES., FXD, FILM: 422 OHM, 1%, 0.125W	91637	MFF1816G422ROF
R799	315-0332-00			RES., FXD, CMPSN: 3.3K OHM, 5%, 0.25W	01121	CB3325
R801	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R802	321-0225-00			RES., FXD, FILM: 2.15K OHM, 1%, 0.125W	91637	MFF1816G21500F
R803	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R811	315-0100-00			RES., FXD, CMPSN: 10 OHM, 5%, 0.25W	01121	CB1005
R812	315-0751-00			RES., FXD, CMPSN: 750 OHM, 5%, 0.25W	01121	CB7515
R813	315-0391-00	B010100	B010209	RES., FXD, CMPSN: 390 OHM, 5%, 0.25W	01121	CB3915
R813	315-0331-00	B010210		RES., FXD, CMPSN: 330 OHM, 5%, 0.25W	01121	CB3315
R814	315-0911-00			RES., FXD, CMPSN: 910 OHM, 5%, 0.25W	01121	CB9115
R821	315-0202-00			RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R822	315-0511-00			RES., FXD, CMPSN: 510 OHM, 5%, 0.25W	01121	CB5115
R823	315-0132-00			RES., FXD, CMPSN: 1.3K OHM, 5%, 0.25W	01121	CB1325
R826	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R827	315-0153-00			RES., FXD, CMPSN: 15K OHM, 5%, 0.25W	01121	CB1535
R828	315-0241-00			RES., FXD, CMPSN: 240 OHM, 5%, 0.25W	01121	CB2415
R830	311-0643-00			RES., VAR, NONWIR: 50 OHM, 10%, 0.50W (R830, 485 ONLY)	73138	82-33-2
R831	321-0155-00			RES., FXD, FILM: 402 OHM, 1%, 0.125W (R831, 485 ONLY)	91637	MFF1816G402ROF
R832	321-0155-00			RES., FXD, FILM: 402 OHM, 1%, 0.125W (R832, 485 ONLY)	91637	MFF1816G402ROF
R833A	321-0158-00			RES., FXD, FILM: 432 OHM, 1%, 0.125W (R833A, 485 ONLY)	91637	MFF1816G432ROF
R833B	321-0158-00			RES., FXD, FILM: 432 OHM, 1%, 0.125W (R833B, 485-1, 485-2 ONLY)	91637	MFF1816G432ROF
R834A	317-0301-00			RES., FXD, CMPSN: 300 OHM, 5%, 0.125W (R834A, 485 ONLY)	01121	BB3015
R834B	317-0301-00			RES., FXD, CMPSN: 300 OHM, 5%, 0.125W (R834B, 485-1, 485-2 ONLY)	01121	BB3015
R835	315-0911-00			RES., FXD, CMPSN: 910 OHM, 5%, 0.25W (R835, 485 ONLY)	01121	CB9115
R836	315-0911-00			RES., FXD, CMPSN: 910 OHM, 5%, 0.25W (R836, 485 ONLY)	01121	CB9115
R840	315-0241-00			RES., FXD, CMPSN: 240 OHM, 5%, 0.25W (R840, 485 ONLY)	01121	CB2415
R841	321-0143-00			RES., FXD, FILM: 301 OHM, 1%, 0.125W (R841, 485 ONLY)	91637	MFF1816G301ROF

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff Dscont	Name & Description	Mfr Code	Mfr Part Number
R842	321-0143-00		RES., FXD, FILM: 301 OHM, 1%, 0.125W (R842, 485 ONLY)	91637	MFF1816G301ROF
R843	315-0621-00		RES., FXD, CMPSN: 620 OHM, 5%, 0.25W	01121	CB6215
R844	315-0681-00		RES., FXD, CMPSN: 680 OHM, 5%, 0.25W	01121	CB6815
R845	315-0241-00		RES., FXD, CMPSN: 240 OHM, 5%, 0.25W	01121	CB2415
R851	321-0291-00		RES., FXD, FILM: 10.5K OHM, 1%, 0.125W	91637	MFF1816G10501F
R852	315-0181-00		RES., FXD, CMPSN: 180 OHM, 5%, 0.25W	01121	CB1815
R853	321-0183-00		RES., FXD, FILM: 787 OHM, 1%, 0.125W	91637	MFF1816G787ROF
R854	315-0124-00		RES., FXD, CMPSN: 120K OHM, 5%, 0.25W	01121	CB1245
R856	315-0562-00		RES., FXD, CMPSN: 5.6K OHM, 5%, 0.25W	01121	CB5625
R857	315-0681-00		RES., FXD, CMPSN: 680 OHM, 5%, 0.25W	01121	CB6815
R861	315-0101-00		RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R862	315-0182-00		RES., FXD, CMPSN: 1.8K OHM, 5%, 0.25W	01121	CB1825
R863	311-1224-00		RES., VAR, NONWIR: 500 OHM, 20%, 0.50W	32997	3386F-T04-501
R865	321-0149-00		RES., FXD, FILM: 348 OHM, 1%, 0.125W	91637	MFF1816G348ROF
R866	315-0102-00		RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R867	321-0201-00		RES., FXD, FILM: 1.21K OHM, 1%, 0.125W	91637	MFF1816G12100F
R868	321-0258-00		RES., FXD, FILM: 4.75K OHM, 1%, 0.125W	91637	MFF1816G47500F
R869	321-0379-00		RES., FXD, FILM: 86.6K OHM, 1%, 0.125W	91637	MFF1816G86601F
R873	323-0318-07		RES., FXD, FILM: 20K OHM, 0.1%, 0.50W	91637	MFF1226C20001B
R874	315-0101-00		RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R876	315-0221-00		RES., FXD, CMPSN: 220 OHM, 5%, 0.25W	01121	CB2215
R877	317-0330-00		RES., FXD, CMPSN: 33 OHM, 5%, 0.125W	01121	BB3305
R878	317-0330-00		RES., FXD, CMPSN: 33 OHM, 5%, 0.125W	01121	BB3305
R891	321-0064-00		RES., FXD, FILM: 45.3 OHM, 1%, 0.125W	91637	MFF1816G45R30F
R892	315-0202-00		RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R894	321-0258-00		RES., FXD, FILM: 4.75K OHM, 1%, 0.125W	91637	MFF1816G47500F
R896	321-0152-00		RES., FXD, FILM: 374 OHM, 1%, 0.125W	91637	MFF1816G374ROF
R898	311-1216-00		RES., VAR, NONWIR: 200K OHM, 20%, 0.50W (R898, FURNISHED AS A UNIT WITH S898)	01121	11M714
R900	315-0471-00		RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715
R901	315-0151-00		RES., FXD, CMPSN: 150 OHM, 5%, 0.25W	01121	CB1515
R902	315-0151-00		RES., FXD, CMPSN: 150 OHM, 5%, 0.25W	01121	CB1515
R903	315-0101-00		RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R904	321-0205-00		RES., FXD, FILM: 1.33K OHM, 1%, 0.125W	91637	MFF1816G13300F
R905	315-0101-00		RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R906	315-0822-00		RES., FXD, CMPSN: 8.2K OHM, 5%, 0.25W	01121	CB8225
R908	315-0683-00		RES., FXD, CMPSN: 68K OHM, 5%, 0.25W	01121	CB6835
R909	315-0222-00		RES., FXD, CMPSN: 2.2K OHM, 5%, 0.25W	01121	CB2225
R910	315-0243-00		RES., FXD, CMPSN: 24K OHM, 5%, 0.25W	01121	CB2435
R911	315-0272-00		RES., FXD, CMPSN: 2.7K OHM, 5%, 0.25W	01121	CB2725
R912	315-0102-00		RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R913	315-0103-00		RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R914	315-0302-00		RES., FXD, CMPSN: 3K OHM, 5%, 0.25W	01121	CB3025
R915	315-0103-00		RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R916	321-0309-00		RES., FXD, FILM: 16.2K OHM, 1%, 0.125W	91637	MFF1816G16201F
R917	321-0210-00		RES., FXD, FILM: 1.5K OHM, 1%, 0.125W	91637	MFF1816G15000F
R918	311-1268-00		RES., VAR, NONWIR: 10K OHM, 10%, 0.50W	32997	3329P-L58-103
R919	321-0382-00		RES., FXD, FILM: 93.1K OHM, 1%, 0.125W	91637	MFF1816G93101F
R920	311-1458-00		RES., VAR, WW: 50K OHM, 5%	73138	7266-322-0
R925	311-1270-00		RES., VAR, NONWIR: 12K OHM, 10%, 0.5W	32997	3329P-L58-253
R926	321-0335-00		RES., FXD, FILM: 30.1K OHM, 1%, 0.125W	91637	MFF1816G30101F
R927	321-0308-00		RES., FXD, FILM: 15.8K OHM, 1%, 0.125W	91637	MFF1816G15801F
R929	321-0241-00		RES., FXD, FILM: 3.16K OHM, 1%, 0.125W	91637	MFF1816G31600F
R931	321-0304-00		RES., FXD, FILM: 14.3K OHM, 1%, 0.125W	91637	MFF1816G14301F
R932	321-0256-00		RES., FXD, FILM: 4.53K OHM, 1%, 0.125W	91637	MFF1816G45300F

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R933	315-0470-00			RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705
R934	321-0262-00			RES., FXD, FILM: 5.23K OHM, 1%, 0.125W	91637	MFF1816G52300F
R935	315-0222-00			RES., FXD, CMPSN: 2.2K OHM, 5%, 0.25W	01121	CB2225
R936	315-0562-00			RES., FXD, CMPSN: 5.6K OHM, 5%, 0.25W	01121	CB5625
R937	321-0254-00			RES., FXD, FILM: 4.32K OHM, 1%, 0.125W	91637	MFF1816G43200F
R938	315-0470-00			RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705
R939	321-0307-00			RES., FXD, FILM: 15.4K OHM, 1%, 0.125W	91637	MFF1816G15401F
R941	321-0288-00			RES., FXD, FILM: 9.76K OHM, 1%, 0.125W	91637	MFF1816G97600F
R942	321-0323-00			RES., FXD, FILM: 22.6K OHM, 1%, 0.125W	91637	MFF1816G22601F
R944	315-0223-00			RES., FXD, CMPSN: 22K OHM, 5%, 0.25W	01121	CB2235
R945	315-0470-00			RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705
R946	307-0106-00			RES., FXD, CMPSN: 4.7 OHM, 5%, 0.25W	01121	CB4765
R947	315-0472-00			RES., FXD, CMPSN: 4.7K OHM, 5%, 0.25W	01121	CB4725
R948	321-0289-00			RES., FXD, FILM: 10K OHM, 1%, 0.125W	91637	MFF1816G10001F
R949	323-0192-00			RES., FXD, FILM: 976 OHM, 1%, 0.50W	75042	CECTO-9760F
R961	321-0385-00			RES., FXD, FILM: 100K OHM, 1%, 0.125W	91637	MFF1816G10002F
R962	321-0680-00			RES., FXD, FILM: 35.3K OHM, 0.5%, 0.125W	91637	MFF1816D35301D
R965	321-0091-00			RES., FXD, FILM: 86.6 OHM, 1%, 0.125W	91637	MFF1816G86R60F
R967	315-0100-00	XB130000		RES., FXD, CMPSN: 10 OHM, 5%, 0.25W	01121	CB1005
R1001	315-0240-00			RES., FXD, CMPSN: 24 OHM, 5%, 0.25W	01121	CB2405
R1002	317-0471-00			RES., FXD, CMPSN: 470 OHM, 5%, 0.125W	01121	BB4715
R1003	322-0621-00			RES., FXD, FILM: 900K OHM, 1%, 0.25W	75042	CEBTO-9003F
R1004	321-0389-00			RES., FXD, FILM: 110K OHM, 1%, 0.125W	91637	MFF1816G11002F
R1005	301-0104-00			RES., FXD, CMPSN: 100K OHM, 5%, 0.5W	01121	EB1045
R1006	315-0750-00			RES., FXD, CMPSN: 75 OHM, 5%, 0.25W	01121	CB7505
R1007	317-0510-00	XB020000		RES., FXD, CMPSN: 51 OHM, 5%, 0.125W	01121	BB5105
R1008	301-0104-00			RES., FXD, CMPSN: 100K OHM, 5%, 0.5W	01121	EB1045
R1009	322-0621-00			RES., FXD, FILM: 900K OHM, 1%, 0.25W	75042	CEBTO-9003F
R1011	315-0131-00			RES., FXD, CMPSN: 130 OHM, 5%, 0.25W	01121	CB1315
R1012	315-0621-00			RES., FXD, CMPSN: 620 OHM, 5%, 0.25W	01121	CB6215
R1013	315-0621-00			RES., FXD, CMPSN: 620 OHM, 5%, 0.25W	01121	CB6215
R1015	315-0471-00			RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715
R1016	317-0330-00			RES., FXD, CMPSN: 33 OHM, 5%, 0.125W	01121	BB3305
R1017	321-0158-00			RES., FXD, FILM: 432 OHM, 1%, 0.125W	91637	MFF1816G432R0F
R1018	321-0158-00			RES., FXD, FILM: 432 OHM, 1%, 0.125W	91637	MFF1816G432R0F
R1019	317-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.125W	01121	BB1015
R1020	311-1192-00			RES., VAR, NONWIR: 10K OHM, 20%, 1W (R1020, FURNISHED AS A UNIT WITH S1020)	71590	BA-232-001
R1021	317-0150-00			RES., FXD, CMPSN: 15 OHM, 5%, 0.125W	01121	BB1505
R1022	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R1023	315-0390-00			RES., FXD, CMPSN: 39 OHM, 5%, 0.25W	01121	CB3905
R1024	315-0332-00			RES., FXD, CMPSN: 3.3K OHM, 5%, 0.25W	01121	CB3325
R1025	311-1230-00			RES., VAR, NONWIR: 20K OHM, 20%, 0.50W	32997	3386F-T04-203
R1026	317-0330-00			RES., FXD, CMPSN: 33 OHM, 5%, 0.125W	01121	BB3305
R1027	315-0431-00			RES., FXD, CMPSN: 430 OHM, 5%, 0.25W	01121	CB4315
R1028	315-0561-00			RES., FXD, CMPSN: 560 OHM, 5%, 0.25W	01121	CB5615
R1029	315-0471-00			RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715
R1030	315-0390-00			RES., FXD, CMPSN: 39 OHM, 5%, 0.25W	01121	CB3905
R1031	321-0082-00			RES., FXD, FILM: 69.8 OHM, 1%, 0.125W	91637	MFF1816G69R80F
R1032	321-0147-00			RES., FXD, FILM: 332 OHM, 1%, 0.125W	91637	MFF1816G332R0F
R1033	321-0147-00			RES., FXD, FILM: 332 OHM, 1%, 0.125W	91637	MFF1816G332R0F
R1034	321-0082-00			RES., FXD, FILM: 69.8 OHM, 1%, 0.125W	91637	MFF1816G69R80F
R1035	317-0390-00	XB050000		RES., FXD, CMPSN: 39 OHM, 5%, 0.125W	01121	BB3905
R1037	315-0681-00			RES., FXD, CMPSN: 680 OHM, 5%, 0.25W	01121	CB6815
R1038	315-0301-00			RES., FXD, CMPSN: 300 OHM, 5%, 0.25W	01121	CB3015
R1039	315-0241-00			RES., FXD, CMPSN: 240 OHM, 5%, 0.25W	01121	CB2415
R1040	321-0079-00			RES., FXD, FILM: 64.9 OHM, 1%, 0.125W	91637	MFF1816G64R90F

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R1041	321-0082-00			RES., FXD, FILM: 69.8 OHM, 1%, 0.125W	91637	MFF1816G69R80F
R1042	321-0177-00			RES., FXD, FILM: 681 OHM, 1%, 0.125W	91637	MFF1816G681R0F
R1043	321-0177-00			RES., FXD, FILM: 681 OHM, 1%, 0.125W	91637	MFF1816G681R0F
R1044	321-0082-00			RES., FXD, FILM: 69.8 OHM, 1%, 0.125W	91637	MFF1816G69R80F
R1045	315-0560-00			RES., FXD, CMPSN: 56 OHM, 5%, 0.25W	01121	CB5605
R1047	315-0822-00			RES., FXD, CMPSN: 8.2K OHM, 5%, 0.25W	01121	CB8225
R1048	315-0201-00			RES., FXD, CMPSN: 200 OHM, 5%, 0.25W	01121	CB2015
R1049	315-0332-00			RES., FXD, CMPSN: 3.3K OHM, 5%, 0.25W	01121	CB3325
R1050	315-0201-00			RES., FXD, CMPSN: 200 OHM, 5%, 0.25W	01121	CB2015
R1051	317-0330-00			RES., FXD, CMPSN: 33 OHM, 5%, 0.125W	01121	BB3305
R1052	317-0330-00			RES., FXD, CMPSN: 33 OHM, 5%, 0.125W	01121	BB3305
R1053	315-0392-00			RES., FXD, CMPSN: 3.9K OHM, 5%, 0.25W	01121	CB3925
R1054	317-0300-00			RES., FXD, CMPSN: 30 OHM, 5%, 0.125W	01121	BB3005
R1055	311-0643-00			RES., VAR, NONWIR: 50 OHM, 10%, 0.50W	73138	82-33-2
R1056	317-0161-00			RES., FXD, CMPSN: 160 OHM, 5%, 0.125W	01121	BB1615
R1057	315-0161-00			RES., FXD, CMPSN: 160 OHM, 5%, 0.25W	01121	CB1615
R1061	317-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.125W	01121	BB1015
R1062	317-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.125W	01121	BB1015
R1063	317-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.125W	01121	BB1015
R1064	317-0910-00			RES., FXD, CMPSN: 91 OHM, 5%, 0.125W	01121	BB9105
R1065	311-0607-00			RES., VAR, NONWIR: 10K OHM, 10%, 0.50W	73138	82P-59-4-103K
R1066	321-0239-00			RES., FXD, FILM: 3.01K OHM, 1%, 0.125W	91637	MFF1816G30100F
R1067	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1068	321-0222-00			RES., FXD, FILM: 2K OHM, 1%, 0.125W	91637	MFF1816G20000F
R1069	317-0511-00			RES., FXD, CMPSN: 510 OHM, 5%, 0.125W	01121	BB5115
R1070	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1071	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1072	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R1073	321-0239-00			RES., FXD, FILM: 3.01K OHM, 1%, 0.125W	91637	MFF1816G30100F
R1074	321-0239-00	B010100	B049999	RES., FXD, FILM: 3.01K OHM, 1%, 0.125W	91637	MFF1816G30100F
R1074	321-0235-00	B050000		RES., FXD, FILM: 2.74K OHM, 1%, 0.125W	91637	MFF1816G27400F
R1075	311-0607-00			RES., VAR, NONWIR: 10K OHM, 10%, 0.50W	73138	82P-59-4-103K
R1076	321-0235-00			RES., FXD, FILM: 2.74K OHM, 1%, 0.125W	91637	MFF1816G27400F
R1077	317-0201-00			RES., FXD, CMPSN: 200 OHM, 5%, 0.125W	01121	BB2015
R1078	321-0256-00			RES., FXD, FILM: 4.53K OHM, 1%, 0.125W	91637	MFF1816G45300F
R1079	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R1081	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1082	321-0185-00			RES., FXD, FILM: 825 OHM, 1%, 0.125W	91637	MFF1816G825R0F
R1083	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1084	315-0470-00			RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705
R1085	317-0512-00	XB060000		RES., FXD, CMPSN: 5.1K OHM, 5%, 0.125	01121	BB5125
R1086	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1087	321-0240-00			RES., FXD, FILM: 3.09K OHM, 1%, 0.125W	91637	MFF1816G30900F
R1089	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1090	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1091	315-0241-00			RES., FXD, CMPSN: 240 OHM, 5%, 0.25W	01121	CB2415
R1092	315-0271-00			RES., FXD, CMPSN: 270 OHM, 5%, 0.25W	01121	CB2715
R1093	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1094	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1096	315-0100-00			RES., FXD, CMPSN: 10 OHM, 5%, 0.25W	01121	CB1005
R1097	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1098	315-0201-00			RES., FXD, CMPSN: 200 OHM, 5%, 0.25W	01121	CB2015
R1101	315-0473-00			RES., FXD, CMPSN: 47K OHM, 5%, 0.25W	01121	CB4735
R1102	315-0473-00			RES., FXD, CMPSN: 47K OHM, 5%, 0.25W	01121	CB4735

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R1103	321-0177-00			RES., FXD, FILM: 681 OHM, 1%, 0.125W	91637	MFF1816G681ROF
R1104	321-0326-00			RES., FXD, FILM: 24.3K OHM, 1%, 0.125W	91637	MFF1816G24301F
R1105	317-0201-00			RES., FXD, CMPSN: 200 OHM, 5%, 0.125W	01121	BB2015
R1106	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1107	321-0159-00			RES., FXD, FILM: 442 OHM, 1%, 0.125W	91637	MFF1816G442ROF
R1108	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R1111	315-0242-00			RES., FXD, CMPSN: 2.4K OHM, 5%, 0.25W	01121	CB2425
R1112	315-0151-00			RES., FXD, CMPSN: 150 OHM, 5%, 0.25W	01121	CB1515
R1114	321-0155-00			RES., FXD, FILM: 402 OHM, 1%, 0.125W	91637	MFF1816G402ROF
R1115	315-0100-00			RES., FXD, CMPSN: 10 OHM, 5%, 0.25W	01121	CB1005
R1116	315-0391-00	B010100	B010209	RES., FXD, CMPSN: 390 OHM, 5%, 0.25W	01121	CB3915
R1116	315-0331-00	B010210		RES., FXD, CMPSN: 330 OHM, 5%, 0.25W	01121	CB3315
R1117	315-0242-00			RES., FXD, CMPSN: 2.4K OHM, 5%, 0.25W	01121	CB2425
R1119	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R1121	315-0751-00			RES., FXD, CMPSN: 750 OHM, 5%, 0.25W	01121	CB7515
R1123	321-0225-00			RES., FXD, FILM: 2.15K OHM, 1%, 0.125W	91637	MFF1816G21500F
R1126	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1127	315-0242-00			RES., FXD, CMPSN: 2.4K OHM, 5%, 0.25W	01121	CB2425
R1129	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1150	311-1223-00			RES., VAR, NONWIR: 250 OHM, 10%, 0.50W	32997	3386F-T04-251
R1151	323-0164-00	B010100	B039999	RES., FXD, FILM: 499 OHM, 1%, 0.50W	75042	CECTO-4990F
R1151	323-0163-00	B040000	B143554	RES., FXD, FILM: 487 OHM, 1%, 0.50W	75042	CECTO-4870F
R1151	323-0166-00	B143555		RES., FXD, FILM: 523 OHM, 1%, 0.50W	75042	CECTO-5230F
R1152	323-0172-00	B010100	B039999	RES., FXD, FILM: 604 OHM, 1%, 0.50W	91637	MFF1226G604ROF
R1152	323-0183-00	B040000	B143554	RES., FXD, FILM: 787 OHM, 1%, 0.50W	75042	CECTO-7870F
R1152	323-0177-00	B143555		RES., FXD, FILM: 680 OHM, 1%, 0.50W	91637	MFF1226G681ROF
R1154	315-0112-00			RES., FXD, CMPSN: 1.1K OHM, 5%, 0.25W	01121	CB1125
R1156	301-0271-00			RES., FXD, CMPSN: 270 OHM, 5%, 0.50W	01121	EB2715
R1161	323-0164-00	B010100	B039999	RES., FXD, FILM: 499 OHM, 1%, 0.50W	75042	CECTO-4990F
R1161	323-0163-00	B040000	B143554	RES., FXD, FILM: 487 OHM, 1%, 0.50W	75042	CECTO-4870F
R1161	323-0166-00	B143555		RES., FXD, FILM: 523 OHM, 1%, 0.50W	75042	CECTO-5230F
R1162	323-0172-00	B010100	B039999	RES., FXD, FILM: 604 OHM, 1%, 0.50W	91637	MFF1226G604ROF
R1162	323-0183-00	B040000	B143554	RES., FXD, FILM: 787 OHM, 1%, 0.50W	75042	CECTO-7870F
R1162	323-0177-00	B143555		RES., FXD, FILM: 680 OHM, 1%, 0.50W	91637	MFF1226G681ROF
R1164	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1165	301-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.50W	01121	EB1015
R1166	301-0131-00			RES., FXD, CMPSN: 130 OHM, 5%, 0.50W	01121	EB1315
R1167	315-0362-00			RES., FXD, CMPSN: 3.6K OHM, 5%, 0.25W	01121	CB3625
R1168	315-0122-00			RES., FXD, CMPSN: 1.2K OHM, 5%, 0.25W	01121	CB1225
R1169	301-0331-00			RES., FXD, CMPSN: 330 OHM, 5%, 0.50W	01121	EB3315
R1171	301-0682-00			RES., FXD, CMPSN: 6.8K OHM, 5%, 0.50W	01121	EB6825
R1172	301-0682-00			RES., FXD, CMPSN: 6.8K OHM, 5%, 0.50W	01121	EB6825
R1173	301-0182-00			RES., FXD, CMPSN: 1.8K OHM, 5%, 0.5W	01121	EB1825
R1174	315-0470-00			RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705
R1175	321-0279-00	B010100	B039999	RES., FXD, FILM: 7.87K OHM, 1%, 0.125W	91637	MFF1816G78700F
R1175	321-0275-00	B040000		RES., FXD, FILM: 7.15K OHM, 1%, 0.125W	91637	MFF1816G71500F
R1176	322-0297-00			RES., FXD, FILM: 12.1K OHM, 1%, 0.25W	75042	CEBT0-1212F
R1177	323-0302-00			RES., FXD, FILM: 13.7K OHM, 1%, 0.50W	75042	CECTO-1372F
R1178	321-0197-00			RES., FXD, FILM: 1.1K OHM, 1%, 0.125W	91637	MFF1816G11000F
R1179	315-0560-00			RES., FXD, CMPSN: 56 OHM, 5%, 0.25W	01121	CB5605
R1181	301-0682-00			RES., FXD, CMPSN: 6.8K OHM, 5%, 0.50W	01121	EB6825
R1182	301-0682-00			RES., FXD, CMPSN: 6.8K OHM, 5%, 0.50W	01121	EB6825
R1183	301-0182-00			RES., FXD, CMPSN: 1.8K OHM, 5%, 0.5W	01121	EB1825
R1184	315-0470-00			RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705
R1187	323-0302-00			RES., FXD, FILM: 13.7K OHM, 1%, 0.50W	75042	CECTO-1372F
R1188	321-0197-00			RES., FXD, FILM: 1.1K OHM, 1%, 0.125W	91637	MFF1816G11000F

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R1189	315-0560-00			RES., FXD, CMPSN: 56 OHM, 5%, 0.25W	01121	CB5605
R1192	315-0121-00			RES., FXD, CMPSN: 120 OHM, 5%, 0.25W	01121	CB1215
R1193	315-0392-00			RES., FXD, CMPSN: 3.9K OHM, 5%, 0.25W	01121	CB3925
R1194	322-0133-00			RES., FXD, FILM: 237 OHM, 1%, 0.25W	75042	CEBTO-2370F
R1196	315-0121-00			RES., FXD, CMPSN: 120 OHM, 5%, 0.25W	01121	CB1215
R1197	315-0392-00			RES., FXD, CMPSN: 3.9K OHM, 5%, 0.25W	01121	CB3925
R1198	322-0133-00			RES., FXD, FILM: 237 OHM, 1%, 0.25W	75042	CEBTO-2370F
R1201	321-0291-00			RES., FXD, FILM: 10.5K OHM, 1%, 0.125W	91637	MFF1816G10501F
R1202	315-0181-00			RES., FXD, CMPSN: 180 OHM, 5%, 0.25W	01121	CB1815
R1203	315-0681-00			RES., FXD, CMPSN: 680 OHM, 5%, 0.25W	01121	CB6815
R1204	315-0562-00			RES., FXD, CMPSN: 5.6K OHM, 5%, 0.25W	01121	CB5625
R1206	321-0183-00			RES., FXD, FILM: 787 OHM, 1%, 0.125W	91637	MFF1816G787ROF
R1207	317-0560-00			RES., FXD, CMPSN: 56 OHM, 5%, 0.125W	01121	BB5605
R1209	315-0623-00			RES., FXD, CMPSN: 62K OHM, 5%, 0.25W	01121	CB6235
R1214	315-0182-00			RES., FXD, CMPSN: 1.8K OHM, 5%, 0.25W	01121	CB1825
R1216	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R1217	321-0149-00			RES., FXD, FILM: 348 OHM, 1%, 0.125W	91637	MFF1816G348ROF
R1218	321-0201-00			RES., FXD, FILM: 1.21K OHM, 1%, 0.125W	91637	MFF1816G12100F
R1219	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1221	321-0258-00			RES., FXD, FILM: 4.75K OHM, 1%, 0.125W	91637	MFF1816G47500F
R1222	321-0340-00			RES., FXD, FILM: 34K OHM, 1%, 0.125W	91637	MFF1816G34001F
R1223	323-0636-07			RES., FXD, FILM: 50K OHM, 0.1%, 0.50W	91637	MFF1226C50001B
R1226	311-1226-00			RES., VAR, NONWIR: 2.5K OHM, 20%, 0.50W	32997	3386F-T04-252
R1227	323-0280-00	B010100	B010285	RES., FXD, FILM: 8.06K OHM, 1%, 0.50W	75042	CECTO-8061F
R1227	323-0278-00	B010286		RES., FXD, FILM: 7.68K OHM, 1%, 0.50W	75042	CECTO-7681F
R1228	311-1226-00			RES., VAR, NONWIR: 2.5K OHM, 20%, 0.50W	32997	3386F-T04-252
R1229	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1235	315-0470-00	XB143555	B144449X	RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705
R1236	315-0472-00	XB144450		RES., FXD, CMPSN: 4.7K OHM, 5%, 0.25W	01121	CB4725
R1237	315-0242-00			RES., FXD, CMPSN: 2.4K OHM, 5%, 0.25W	01121	CB2425
R1238	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R1239	315-0272-00			RES., FXD, CMPSN: 2.7K OHM, 5%, 0.25W	01121	CB2725
R1240	317-0330-00			RES., FXD, CMPSN: 33 OHM, 5%, 0.125W	01121	BB3305
R1241	315-0221-00			RES., FXD, CMPSN: 220 OHM, 5%, 0.25W	01121	CB2215
R1242	317-0330-00			RES., FXD, CMPSN: 33 OHM, 5%, 0.125W	01121	BB3305
R1251	321-0054-00			RES., FXD, FILM: 35.7 OHM, 5%, 0.125W	91637	MFF1816G35R70F
R1252	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R1254	321-0248-00			RES., FXD, FILM: 3.74K OHM, 1%, 0.125W	91637	MFF1816G37400F
R1257	321-0142-00			RES., FXD, FILM: 294 OHM, 1%, 0.125W	91637	MFF1816G294ROF
R1261	321-0304-00			RES., FXD, FILM: 14.3K OHM, 1%, 0.125W	91637	MFF1816G14301F
R1262	321-0256-00			RES., FXD, FILM: 4.53K OHM, 1%, 0.125W	91637	MFF1816G45300F
R1263	315-0470-00			RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705
R1264	321-0262-00			RES., FXD, FILM: 5.23K OHM, 1%, 0.125W	91637	MFF1816G52300F
R1266	315-0562-00			RES., FXD, CMPSN: 5.6K OHM, 5%, 0.25W	01121	CB5625
R1267	321-0307-00			RES., FXD, FILM: 15.4K OHM, 1%, 0.125W	91637	MFF1816G15401F
R1268	315-0470-00			RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705
R1269	321-0254-00			RES., FXD, FILM: 4.32K OHM, 1%, 0.125W	91637	MFF1816G43200F
R1271	315-0331-00			RES., FXD, CMPSN: 330 OHM, 5%, 0.25W	01121	CB3315
R1272	315-0202-00			RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R1300	311-1197-00			RES., VAR, NONWIR: 20K OHM, 10%, 1W	12697	381-CM39696
R1301	315-0470-00			RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705
R1302	315-0912-00			RES., FXD, CMPSN: 9.1K OHM, 5%, 0.25W	01121	CB9125
R1303	321-0216-00			RES., FXD, FILM: 1.74K OHM, 1%, 0.125W	91637	MFF1816G17400F
R1306	321-0216-00			RES., FXD, FILM: 1.74K OHM, 1%, 0.125W	91637	MFF1816G17400F
R1307	321-0228-00			RES., FXD, FILM: 2.32K OHM, 1%, 0.125W	91637	MFF1816G23200F
R1308	311-1224-00			RES., VAR, NONWIR: 500 OHM, 20%, 0.50W	32997	3386F-T04-501

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Discont	Name & Description	Mfr Code	Mfr Part Number
R1313	321-0326-00			RES., FXD, FILM: 24.3K OHM, 1%, 0.125W	91637	MFF1816G24301F
R1314	321-0250-00			RES., FXD, FILM: 3.92K OHM, 1%, 0.125W	91637	MFF1816G39200F
R1321	321-0230-00			RES., FXD, FILM: 2.43K OHM, 1%, 0.125W	91637	MFF1816G24300F
R1322	321-0231-00			RES., FXD, FILM: 2.49K OHM, 1%, 0.125W	91637	MFF1816G24900F
R1325	311-1228-00			RES., VAR, NONWIR: 10K OHM, 20%, 0.50W	32997	3386F-T04-103
R1326	321-0295-00			RES., FXD, FILM: 11.5K OHM, 1%, 0.125W	91637	MFF1816G11501F
R1327	321-0234-00			RES., FXD, FILM: 2.67K OHM, 1%, 0.125W	91637	MFF1816G26700F
R1328	321-0246-00			RES., FXD, FILM: 3.57K OHM, 1%, 0.125W	91637	MFF1816G35700F
R1329	321-0299-00			RES., FXD, FILM: 12.7K OHM, 1%, 0.125W	91637	MFF1816G12701F
R1331	315-0243-00			RES., FXD, CMPSN: 24K OHM, 5%, 0.25W	01121	CB2435
R1333	315-0203-00			RES., FXD, CMPSN: 20K OHM, 5%, 0.25W	01121	CB2035
R1335	315-0202-00			RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R1336	315-0100-00			RES., FXD, CMPSN: 10 OHM, 5%, 0.25W	01121	CB1005
R1338	315-0681-00			RES., FXD, CMPSN: 680 OHM, 5%, 0.25W	01121	CB6815
R1341	315-0911-00			RES., FXD, CMPSN: 910 OHM, 5%, 0.25W	01121	CB9115
R1342	315-0332-00			RES., FXD, CMPSN: 3.3K OHM, 5%, 0.25W	01121	CB3325
R1343	321-0250-00			RES., FXD, FILM: 3.92K OHM, 1%, 0.125W	91637	MFF1816G39200F
R1344	321-0326-00			RES., FXD, FILM: 24.3K OHM, 1%, 0.125W	91637	MFF1816G24301F
R1348	311-1222-00			RES., VAR, NONWIR: 100 OHM, 20%, 0.50W	32997	3386F-T04-101
R1354	321-0085-00			RES., FXD, FILM: 75 OHM, 1%, 0.125W	91637	MFF1816G75R00F
R1355	311-1225-00			RES., VAR, NONWIR: 1K OHM, 20%, 0.50W	32997	3386F-T04-102
R1356	315-0162-00			RES., FXD, CMPSN: 1.6K OHM, 5%, 0.25W	01121	CB1625
R1357	321-0225-00			RES., FXD, FILM: 2.15K OHM, 1%, 0.125W	91637	MFF1816G21500F
R1361	315-0820-00			RES., FXD, CMPSN: 82 OHM, 5%, 0.25W	01121	CB8205
R1362	315-0132-00			RES., FXD, CMPSN: 1.3K OHM, 5%, 0.25W	01121	CB1325
R1364	321-0161-00	B010100	B049999	RES., FXD, FILM: 464 OHM, 1%, 0.125W	91637	MFF1816G464R0F
R1364	321-0164-00	B050000		RES., FXD, FILM: 499 OHM, 1%, 0.125W	91637	MFF1816G499R0F
R1365	315-0271-00			RES., FXD, CMPSN: 270 OHM, 5%, 0.25W	01121	CB2715
R1366	311-0605-00			RES., VAR, NONWIR: 200 OHM, 10%, 0.50W	73138	82-23-1
R1367	315-0122-00			RES., FXD, CMPSN: 1.2K OHM, 5%, 0.25W	01121	CB1225
R1368	301-0511-00			RES., FXD, CMPSN: 510 OHM, 5%, 0.50W	01121	EB5115
R1369	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1371	315-0110-00			RES., FXD, CMPSN: 11 OHM, 5%, 0.25W	01121	CB1105
R1372	321-0117-00			RES., FXD, FILM: 162 OHM, 1%, 0.125W	91637	MFF1816G162R0F
R1373	323-0102-00			RES., FXD, FILM: 113 OHM, 1%, 0.50W	75042	CECTO-1130F
R1374	321-0117-00			RES., FXD, FILM: 162 OHM, 1%, 0.125W	91637	MFF1816G162R0F
R1375	317-0680-00			RES., FXD, CMPSN: 68 OHM, 5%, 0.125W	01121	BB6805
R1400	311-0566-00			RES., VAR, NONWIR: 5K OHM, 20%	12697	381-CM39672
R1401	315-0681-00			RES., FXD, CMPSN: 680 OHM, 5%, 0.25W	01121	CB6815
R1402	315-0303-00			RES., FXD, CMPSN: 30K OHM, 5%, 0.25W	01121	CB3035
R1407	315-0153-00			RES., FXD, CMPSN: 15K OHM, 5%, 0.25W	01121	CB1535
R1409	323-0793-07			RES., FXD, FILM: 2.5M OHM, 0.1%, 0.50W	91637	MFF1226C25003B
R1410	323-0498-07			RES., FXD, FILM: 1.5M OHM, 0.1%, 0.50W	91637	MFF1226C15003B
R1411	323-0740-07			RES., FXD, FILM: 500K OHM, 0.1%, 0.50W	91637	MFF1226C50002B
R1412	323-0742-07			RES., FXD, FILM: 250K OHM, 0.1%, 0.50W	91637	MFF1226C25002B
R1413	323-0636-07			RES., FXD, FILM: 50K OHM, 0.1%, 0.50W	91637	MFF1226C50001B
R1414	323-0385-07			RES., FXD, FILM: 100K OHM, 0.1%, 0.50W	91637	MFF1226C10002B
R1415	323-0792-07			RES., FXD, FILM: 60K OHM, 0.1%, 0.50W	91637	MFF1226C60001B
R1416	323-0318-07			RES., FXD, FILM: 20K OHM, 0.1%, 0.50W	91637	MFF1226C20001B
R1418	323-0745-07			RES., FXD, FILM: 5M OHM, 0.1%, 0.50W	03888	PME-655MEG
R1419	325-0106-00			RES., FXD, FILM: 15M OHM, 0.1%, 0.50W	03888	PME-7015MEG
R1421	321-0386-00			RES., FXD, FILM: 102K OHM, 1%, 0.125W	91637	MFF1816G10202F
R1422	315-0434-00			RES., FXD, CMPSN: 430K OHM, 5%, 0.25W	01121	CB4345
R1431	315-0244-00			RES., FXD, CMPSN: 240K OHM, 5%, 0.25W	01121	CB2445
R1437	321-0261-00			RES., FXD, FILM: 5.11K OHM, 1%, 0.125W	91637	MFF1816G51100F
R1441	321-0181-00			RES., FXD, FILM: 750 OHM, 1%, 0.125W	91637	MFF1816G750R0F

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R1450	323-0289-00	B010100	B010285	RES., FXD, FILM: 10K OHM, 1%, 0.50W	75042	CECT0-1002F
R1450	323-0292-00	B010286		RES., FXD, FILM: 10.7K OHM, 1%, 0.50W	91637	MFF1226G10701F
R1451	323-0793-07			RES., FXD, FILM: 2.5M OHM, 0.1%, 0.50W	91637	MFF1226C25003B
R1452	323-0498-07			RES., FXD, FILM: 1.5M OHM, 0.1%, 0.50W	91637	MFF1226C15003B
R1453	323-0740-07			RES., FXD, FILM: 500K OHM, 0.1%, 0.50W	91637	MFF1226C50002B
R1454	323-0742-07			RES., FXD, FILM: 250K OHM, 0.1%, 0.50W	91637	MFF1226C25002B
R1455	323-0402-07			RES., FXD, FILM: 150K OHM, 0.1%, 0.50W	91637	MFF1226C15002B
R1456	323-0636-07			RES., FXD, FILM: 50K OHM, 0.1%, 0.50W	91637	MFF1226C5
R1458	323-0745-07			RES., FXD, FILM: 5M OHM, 0.1%, 0.50W	03888	PME-655MEG
R1459	325-0106-00			RES., FXD, FILM: 15M OHM, 0.1%, 0.50W	03888	PME-7015MEG
R1461	321-0347-00			RES., FXD, FILM: 40.2K OHM, 1%, 0.125W	91637	MFF1816G40201F
R1462	321-0393-00			RES., FXD, FILM: 121K OHM, 1%, 0.125W	91637	MFF1816G12102F
R1463	315-0204-00			RES., FXD, CMPSN: 200K OHM, 5%, 0.25W	01121	CB2045
R1481	323-0140-00			RES., FXD, FILM: 280 OHM, 1%, 0.50W	75042	CECT0-2800F
R1482	315-0470-00			RES., FXD, CMPSN: 47 OHM, 5%, 0.25W	01121	CB4705
R1484	323-0140-00			RES., FXD, FILM: 280 OHM, 1%, 0.50W	75042	CECT0-2800F
R1486	321-0216-00			RES., FXD, FILM: 1.74K OHM, 1%, 0.125W	91637	MFF1816G17400F
R1487	315-0363-00			RES., FXD, CMPSN: 36K OHM, 5%, 0.25W	01121	CB3635
R1488	321-0201-00			RES., FXD, FILM: 1.21K OHM, 1%, 0.125W	91637	MFF1816G12100F
R1497	321-0062-00			RES., FXD, FILM: 43.2 OHM, 1%, 0.125W	91637	MFF1816G43R20F
R1499	301-0160-00			RES., FXD, CMPSN: 16 OHM, 5%, 0.50W	01121	EB1605
R1501	315-0473-00			RES., FXD, CMPSN: 47K OHM, 5%, 0.25W	01121	CB4735
R1503	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1506	315-0203-00			RES., FXD, CMPSN: 20K OHM, 5%, 0.25W	01121	CB2035
R1507	315-0512-00			RES., FXD, CMPSN: 5.1K OHM, 5%, 0.25W	01121	CB5125
R1509	315-0393-00			RES., FXD, CMPSN: 39K OHM, 5%, 0.25W	01121	CB3935
R1511	315-0104-00			RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R1512	315-0153-00			RES., FXD, CMPSN: 15K OHM, 5%, 0.25W	01121	CB1535
R1516	315-0434-00			RES., FXD, CMPSN: 430K OHM, 5%, 0.25W	01121	CB4345
R1517	315-0153-00			RES., FXD, CMPSN: 15K OHM, 5%, 0.25W	01121	CB1535
R1518	315-0153-00			RES., FXD, CMPSN: 15K OHM, 5%, 0.25W	01121	CB1535
R1519	315-0822-00			RES., FXD, CMPSN: 8.2K OHM, 5%, 0.25W	01121	CB8225
R1521	315-0361-00			RES., FXD, CMPSN: 360 OHM, 5%, 0.25W	01121	CB3615
R1522	315-0222-00			RES., FXD, CMPSN: 2.2K OHM, 5%, 0.25W	01121	CB2225
R1523	315-0911-00			RES., FXD, CMPSN: 910 OHM, 5%, 0.25W	01121	CB9115
R1524	315-0623-00			RES., FXD, CMPSN: 62K OHM, 5%, 0.25W	01121	CB6235
R1526	315-0121-00			RES., FXD, CMPSN: 120 OHM, 5%, 0.25W	01121	CB1215
R1531	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1534	315-0684-00			RES., FXD, CMPSN: 680K OHM, 5%, 0.25W	01121	CB6845
R1536	316-0225-00			RES., FXD, CMPSN: 2.2M OHM, 10%, 0.25W	01121	CB2251
R1538	315-0153-00			RES., FXD, CMPSN: 15K OHM, 5%, 0.25W	01121	CB1535
R1539	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1541	315-0683-00			RES., FXD, CMPSN: 68K OHM, 5%, 0.25W	01121	CB6835
R1542	315-0154-00			RES., FXD, CMPSN: 150K OHM, 5%, 0.25W	01121	CB1545
R1544	315-0332-00			RES., FXD, CMPSN: 3.3K OHM, 5%, 0.25W	01121	CB3325
R1545	315-0682-00			RES., FXD, CMPSN: 6.8K OHM, 5%, 0.25W	01121	CB6825
R1546	315-0333-00			RES., FXD, CMPSN: 33K OHM, 5%, 0.25W	01121	CB3335
R1547	315-0392-00			RES., FXD, CMPSN: 3.9K OHM, 5%, 0.25W	01121	CB3925
R1548	315-0682-00			RES., FXD, CMPSN: 6.8K OHM, 5%, 0.25W	01121	CB6825
R1549	315-0222-00			RES., FXD, CMPSN: 2.2K OHM, 5%, 0.25W	01121	CB2225
R1551	315-0152-00			RES., FXD, CMPSN: 1.5K OHM, 5%, 0.25W	01121	CB1525
R1552	315-0512-00			RES., FXD, CMPSN: 5.1K OHM, 5%, 0.25W	01121	CB5125
R1553	315-0622-00			RES., FXD, CMPSN: 6.2K OHM, 5%, 0.25W	01121	CB6225
R1554	315-0300-00			RES., FXD, CMPSN: 30 OHM, 5%, 0.25W	01121	CB3005
R1555	315-0622-00			RES., FXD, CMPSN: 6.2K OHM, 5%, 0.25W	01121	CB6225

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R1557	301-0511-00			RES., FXD, CMPSN: 510 OHM, 5%, 0.50W	01121	EB5115
R1558	321-0217-00			RES., FXD, FILM: 1.78K OHM, 1%, 0.125W	91637	MFF1816G17800F
R1559	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1560	311-0635-00			RES., VAR, NONWIR: 1K OHM, 10%, 0.50W	73138	82-32-0
R1561	321-0241-00	B010100	B146225	RES., FXD, FILM: 3.16K OHM, 1%, 0.125W	91637	MFF1816G31600F
R1561	321-0240-00	B142666		RES., FXD, FILM: 3.09K OHM, 1%, 0.125W	91637	MFF1816G30900F
R1563	321-0295-00			RES., FXD, FILM: 11.5K OHM, 1%, 0.125W	91637	MFF1816G11501F
R1564	321-0253-00	B010100	B129999	RES., FXD, FILM: 4.22K OHM, 1%, 0.125W	91637	MFF1816G42200F
R1564	321-0250-00	B130000		RES., FXD, FILM: 3.92K OHM, 1%, 0.125W	91637	MFF1816G39200F
R1567	321-0206-00			RES., FXD, FILM: 1.37K OHM, 1%, 0.125W	91637	MFF1816G13700F
R1568	315-0823-00			RES., FXD, CMPSN: 82K OHM, 5%, 0.25W	01121	CB8235
R1569	311-0310-00			RES., VAR, NONWIR: 5K OHM, 20%, 0.50W	01121	W-7350A
R1570	311-0608-00			RES., VAR, NONWIR: 2K OHM, 10%, 0.75W	01121	W8156
R1571	315-0124-00			RES., FXD, CMPSN: 120K OHM, 5%, 0.25W	01121	CB1245
R1572	321-0243-00			RES., FXD, FILM: 3.32K OHM, 1%, 0.125W	91637	MFF1816G33200F
R1573	321-0243-00			RES., FXD, FILM: 3.32K OHM, 1%, 0.125W	91637	MFF1816G33200F
R1574	321-0254-00			RES., FXD, FILM: 4.32K OHM, 1%, 0.125W	91637	MFF1816G43200F
R1575	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1576	315-0473-00			RES., FXD, CMPSN: 47K OHM, 5%, 0.25W	01121	CB4735
R1577	315-0104-00			RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R1579	307-0106-00	B010100	B139999	RES., FXD, CMPSN: 4.7 OHM, 5%, 0.25W	01121	CB47G5
R1579	317-0100-00	B140000		RES., FXD, CMPSN: 10 OHM, 5%, 0.125W	01121	BB1005
R1581	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1582	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1583	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1584	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1585	315-0223-00			RES., FXD, CMPSN: 22K OHM, 5%, 0.25W	01121	CB2235
R1586	315-0471-00			RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715
R1587	315-0392-00			RES., FXD, CMPSN: 3.9K OHM, 5%, 0.25W	01121	CB3925
R1588	315-0912-00			RES., FXD, CMPSN: 9.1K OHM, 5%, 0.25W	01121	CB9125
R1589	315-0752-00			RES., FXD, CMPSN: 7.5K OHM, 5%, 0.25W	01121	CB7525
R1590	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R1591	315-0203-00			RES., FXD, CMPSN: 20K OHM, 5%, 0.25W	01121	CB2035
R1592	315-0911-00			RES., FXD, CMPSN: 910 OHM, 5%, 0.25W	01121	CB9115
R1593	315-0203-00			RES., FXD, CMPSN: 20K OHM, 5%, 0.25W	01121	CB2035
R1594	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R1595	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R1596	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R1597	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R1598	315-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.25W	01121	CB5105
R1599	315-0510-00			RES., FXD, CMPSN: 51 OHM, 5%, 0.25W	01121	CB5105
R1600	316-0471-00			RES., FXD, CMPSN: 470 OHM, 10%, 0.25W	01121	CB4711
R1601	301-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.50W	01121	EB1025
R1602	301-0153-00			RES., FXD, CMPSN: 15K OHM, 5%, 0.50W	01121	EB1535
R1603	301-0624-00			RES., FXD, CMPSN: 620K OHM, 5%, 0.50W	01121	EB6245
R1604	301-0624-00			RES., FXD, CMPSN: 620K OHM, 5%, 0.50W	01121	EB6245
R1605	301-0155-00			RES., FXD, CMPSN: 1.5M OHM, 5%, 0.50W	01121	EB1555
R1606	301-0155-00			RES., FXD, CMPSN: 1.5M OHM, 5%, 0.50W	01121	EB1555
R1608	301-0155-00			RES., FXD, CMPSN: 1.5M OHM, 5%, 0.50W	01121	EB1555
R1609	301-0155-00			RES., FXD, CMPSN: 1.5M OHM, 5%, 0.50W	01121	EB1555
R1611	315-0392-00			RES., FXD, CMPSN: 3.9K OHM, 5%, 0.25W	01121	CB3925
R1612	315-0392-00			RES., FXD, CMPSN: 3.9K OHM, 5%, 0.25W	01121	CB3925
R1613	301-0472-00			RES., FXD, CMPSN: 4.7K OHM, 5%, 0.50W	01121	EB4725
R1614	301-0331-00			RES., FXD, CMPSN: 330 OHM, 5%, 0.50W	01121	EB3315
R1616	315-0150-00			RES., FXD, CMPSN: 15 OHM, 5%, 0.25W	01121	CB1505
R1618	315-0150-00			RES., FXD, CMPSN: 15 OHM, 5%, 0.25W	01121	CB1505

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R1619	321-0231-00			RES., FXD, FILM: 2.49K OHM, 1%, 0.125W	91637	MFF1816G24900F
R1621	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R1622	321-0294-00			RES., FXD, FILM: 11.3K OHM, 1%, 0.125W	91637	MFF1816G11301F
R1623	321-0419-00			RES., FXD, FILM: 226K OHM, 1%, 0.125W	91637	MFF1816G22602F
R1624	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R1625	311-1254-00			RES., VAR, NONWIR: 1M OHM, 20%, 0.50W	32997	3386F-T05-105
R1626	315-0395-00			RES., FXD, CMPSN: 3.9M OHM, 5%, 0.25W	01121	CB3955
R1627	315-0474-00			RES., FXD, CMPSN: 470K OHM, 5%, 0.25W	01121	CB4745
R1633	301-0272-00			RES., FXD, CMPSN: 2.7K OHM, 5%, 0.50W	01121	EB2725
R1640	311-0254-00			RES., VAR, NONWIR: 5M OHM, 10%, 1W	12697	CM29709
R1641	301-0116-00			RES., FXD, CMPSN: 11M OHM, 5%, 0.50W	01121	EB1165
R1642A	307-0386-00			RES., FXD, FILM: HYBRID, HV	80009	307-0386-00
R1642B						
R1642C						
R1642D						
R1646	315-0393-00			RES., FXD, CMPSN: 39K OHM, 5%, 0.25W	01121	CB3935
R1651	315-0226-00			RES., FXD, CMPSN: 22M OHM, 5%, 0.25W	01121	CB2265
R1656	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R1660	311-1230-00			RES., VAR, NONWIR: 20K OHM, 20%, 0.50W	32997	3386F-T04-203
R1661	321-0306-00			RES., FXD, FILM: 15K OHM, 1%, 0.125W	91637	MFF1816G15001F
R1666	315-0393-00			RES., FXD, CMPSN: 39K OHM, 5%, 0.25W	01121	CB3935
R1667	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1668	315-0104-00			RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R1669	315-0226-00			RES., FXD, CMPSN: 22M OHM, 5%, 0.25W	01121	CB2265
R1681	301-0683-00			RES., FXD, CMPSN: 68K OHM, 5%, 0.50W	01121	EB6835
R1682	301-0225-00			RES., FXD, CMPSN: 2.2M OHM, 5%, 0.50W	01121	EB2255
R1684	301-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.50W	01121	EB1035
R1685	301-0105-00			RES., FXD, CMPSN: 1M OHM, 5%, 0.50W	01121	EB1055
R1687	316-0473-00			RES., FXD, CMPSN: 47K OHM, 10%, 0.25W	01121	CB4731
R1700	311-1035-00			RES., VAR, NONWIR: 50K OHM, 10%, 0.50W	73138	82-40-0
R1701	321-0352-00			RES., FXD, FILM: 45.3K OHM, 1%, 0.125W	91637	MFF1816G45301F
R1702	321-0352-00			RES., FXD, FILM: 45.3K OHM, 1%, 0.125W	91637	MFF1816G45301F
R1703	321-0283-00			RES., FXD, FILM: 8.66K OHM, 1%, 0.125W	91637	MFF1816G86600F
R1704	321-0295-00			RES., FXD, FILM: 11.5K OHM, 1%, 0.125W	91637	MFF1816G11501F
R1706	321-0294-00			RES., FXD, FILM: 11.3K OHM, 1%, 0.125W	91637	MFF1816G11301F
R1708	321-0272-00			RES., FXD, FILM: 6.65K OHM, 1%, 0.125W	91637	MFF1816G66500F
R1709	321-0314-00			RES., FXD, FILM: 18.2K OHM, 1%, 0.125W	91637	MFF1816G18201F
R1710	311-0633-00			RES., VAR, NONWIR: 5K OHM, 10%, 0.50W	73138	82-30-0
R1711	321-0281-00	B010100	B059999	RES., FXD, FILM: 8.25K OHM, 1%, 0.125W	91637	MFF1816G82500F
R1711	321-0272-00	B060000		RES., FXD, FILM: 6.65K OHM, 1%, 0.125W	91637	MFF1816G66500F
R1712	321-0310-00	B010100	B059999	RES., FXD, FILM: 16.5K OHM, 1%, 0.125W	91637	MFF1816G16501F
R1712	321-0301-00	B060000		RES., FXD, FILM: 13.3K OHM, 1%, 0.125W	91637	MFF1816G13301F
R1714	321-0289-00			RES., FXD, FILM: 10K OHM, 1%, 0.125W	91637	MFF1816G10001F
R1715	321-0294-00			RES., FXD, FILM: 11.3K OHM, 1%, 0.125W	91637	MFF1816G11301F
R1717	301-0301-00			RES., FXD, CMPSN: 300 OHM, 5%, 0.50W	01121	EB3015
R1718	315-0751-00			RES., FXD, CMPSN: 750 OHM, 5%, 0.25W	01121	CB7515
R1721	321-0340-00			RES., FXD, FILM: 34K OHM, 1%, 0.125W	91637	MFF1816G34001F
R1722	321-0307-00			RES., FXD, FILM: 15.4K OHM, 1%, 0.125W	91637	MFF1816G15401F
R1723	315-0182-00			RES., FXD, CMPSN: 1.8K OHM, 5%, 0.25W	01121	CB1825
R1725	321-0432-00			RES., FXD, FILM: 309K OHM, 1%, 0.125W	91637	MFF1816G30902F
R1727	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R1728	315-0100-00			RES., FXD, CMPSN: 10 OHM, 5%, 0.25W	01121	CB1005
R1729	315-0275-00			RES., FXD, CMPSN: 2.7M OHM, 5%, 0.25W	01121	CB2755
R1731	321-0305-00			RES., FXD, FILM: 14.7K OHM, 1%, 0.125W	91637	MFF1816G14701F
R1732	322-0609-00			RES., FXD, FILM: 33.3K OHM, 1%, 0.25W	75042	CEBTO-3333F
R1734	315-0220-00			RES., FXD, CMPSN: 22 OHM, 5%, 0.25W	01121	CB2205

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R1735	321-0154-00			RES., FXD, FILM: 392 OHM, 1%, 0.125W	91637	MFF1816G392ROF
R1737	321-0405-00			RES., FXD, FILM: 162K OHM, 1%, 0.125W	91637	MFF1816G16202F
R1738	321-0310-00			RES., FXD, FILM: 16.5K OHM, 1%, 0.125W	91637	MFF1816G16501F
R1741	315-0361-00			RES., FXD, CMPSN: 360 OHM, 5%, 0.25W	01121	CB3615
R1742	315-0100-00			RES., FXD, CMPSN: 10 OHM, 5%, 0.25W	01121	CB1005
R1745	315-0241-00			RES., FXD, CMPSN: 240 OHM, 5%, 0.25W	01121	CB2415
R1746	315-0220-00			RES., FXD, CMPSN: 22 OHM, 5%, 0.25W	01121	CB2205
R1749	315-0751-00			RES., FXD, CMPSN: 750 OHM, 5%, 0.25W	01121	CB7515
R1751	315-0220-00			RES., FXD, CMPSN: 22 OHM, 5%, 0.25W	01121	CB2205
R1752	315-0240-00			RES., FXD, CMPSN: 24 OHM, 5%, 0.25W	01121	CB2405
R1754	315-0472-00			RES., FXD, CMPSN: 4.7K OHM, 5%, 0.25W	01121	CB4725
R1755	315-0202-00			RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R1761	315-0244-00			RES., FXD, CMPSN: 240K OHM, 5%, 0.25W	01121	CB2445
R1762	321-0222-00			RES., FXD, FILM: 2K OHM, 1%, 0.125W	91637	MFF1816G20000F
R1765	311-0609-00			RES., VAR, NONWIR: 2K OHM, 10%, 0.50W	73138	82-26-0
R1766	323-0314-00			RES., FXD, FILM: 18.2K OHM, 1%, 0.50W	75042	CECT0-1822F
R1768	315-0205-00			RES., FXD, CMPSN: 2M OHM, 5%, 0.25W	01121	CB2055
R1769	321-0350-00			RES., FXD, FILM: 4.2K OHM, 1%, 0.125W	91637	MFF1816G43201F
R1771	321-0303-00			RES., FXD, FILM: 14K OHM, 1%, 0.125W	91637	MFF1816G14001F
R1773	321-0164-00			RES., FXD, FILM: 499 OHM, 1%, 0.125W	91637	MFF1816G499ROF
R1774	315-0121-00			RES., FXD, CMPSN: 120 OHM, 5%, 0.25W	01121	CB1215
R1776	321-0321-00			RES., FXD, FILM: 21.5K OHM, 1%, 0.125W	91637	MFF1816G21501F
R1777	321-0363-00			RES., FXD, FILM: 59K OHM, 1%, 0.125W	91637	MFF1816G59001F
R1778	322-0643-00			RES., FXD, FILM: 600K OHM, 1%, 0.25W	75042	CEBTO-6003F
R1779	315-0304-00			RES., FXD, CMPSN: 300K OHM, 5%, 0.25W	01121	CB3045
R1781	315-0752-00			RES., FXD, CMPSN: 7.5K OHM, 5%, 0.25W	01121	CB7525
R1782	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R1790	311-0963-00			RES., VAR, WW: PNL, 5K OHM, 0.25W	01121	W-7577A
R1792	311-1235-00			RES., VAR, NONWIR: 100K OHM, 20%, 0.50W	32997	3386F-T04-104
R1794	311-1227-00			RES., VAR, NONWIR: 5K OHM, 20%, 0.50W	32997	3386F-T04-502
R1796	311-1226-00			RES., VAR, NONWIR: 2.5K OHM, 20%, 0.50W	32997	3386F-T04-252
R1797	321-0297-00			RES., FXD, FILM: 12.1K OHM, 1%, 0.125W	91637	MFF1816G12101F
R1798	321-0352-00			RES., FXD, FILM: 45.3K OHM, 1%, 0.125W	91637	MFF1816G45301F
R1799	311-1099-00			RES., VAR, NONWIR: 100K OHM, 0.5W	01121	WA1G040S104AZ
R1801	315-0753-00			RES., FXD, CMPSN: 75K OHM, 5%, 0.25W	01121	CB7535
R1802	301-0154-00			RES., FXD, CMPSN: 150K OHM, 5%, 0.50W	01121	EB1545
R1803	315-0753-00			RES., FXD, CMPSN: 75K OHM, 5%, 0.25W	01121	CB7535
R1804	315-0911-00			RES., FXD, CMPSN: 910 OHM, 5%, 0.25W	01121	CB9115
R1805	316-0471-00			RES., FXD, CMPSN: 470 OHM, 10%, 0.25W	01121	CB4711
R1806	315-0753-00			RES., FXD, CMPSN: 75K OHM, 5%, 0.25W	01121	CB7535
R1811	301-0225-00			RES., FXD, CMPSN: 2.2M OHM, 5%, 0.50W	01121	EB2255
R1812	301-0431-00			RES., FXD, CMPSN: 430 OHM, 5%, 0.50W	01121	EB4315
R1813	301-0431-00			RES., FXD, CMPSN: 430 OHM, 5%, 0.50W	01121	EB4315
R1814	301-0151-00			RES., FXD, CMPSN: 150 OHM, 5%, 0.50W	01121	EB1515
R1822	301-0184-00			RES., FXD, CMPSN: 180K OHM, 5%, 0.50W	01121	EB1845
R1823	301-0184-00			RES., FXD, CMPSN: 180K OHM, 5%, 0.50W	01121	EB1845
R1824	302-0685-00			RES., FXD, CMPSN: 6.8M OHM, 10%, 0.50W	01121	EB6851
R1825	315-0471-00			RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715
R1828	303-0224-00			RES., FXD, CMPSN: 220K OHM, 5%, 1W	01121	GB2245
R1829	315-0433-00			RES., FXD, CMPSN: 43K OHM, 5%, 0.25W	01121	CB4335
R1831	307-0113-00			RES., FXD, CMPSN: 5.1 OHM, 5%, 0.25W	01121	CB51G5
R1834	301-0220-00			RES., FXD, CMPSN: 22 OHM, 5%, 0.50W	01121	EB2205
R1836	302-0105-00			RES., FXD, CMPSN: 1M OHM, 10%, 0.50W	01121	EB1051
R1841	301-0220-00			RES., FXD, CMPSN: 22 OHM, 5%, 0.50W	01121	EB2205
R1846	316-0471-00			RES., FXD, CMPSN: 470 OHM, 10%, 0.25W	01121	CB4711
R1847	316-0471-00			RES., FXD, CMPSN: 470 OHM, 10%, 0.25W	01121	CB4711

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R1848	316-0274-00			RES., FXD, CMPSN: 270K OHM, 10%, 0.25W	01121	CB2741
R1901	315-0392-00			RES., FXD, CMPSN: 3.9K OHM, 5%, 0.25W	01121	CB3925
R1902	315-0753-00			RES., FXD, CMPSN: 75K OHM, 5%, 0.25W	01121	CB7535
R1903	315-0273-00	XB143850	B149999	RES., FXD, CMPSN: 27K OHM, 5%, 0.25W	01121	CB2735
R1903	315-0104-00	B150000		RES., FXD, CMPSN: 100K OHM, 5%, 0.25W	01121	CB1045
R1904	315-0562-00			RES., FXD, CMPSN: 5.6K OHM, 5%, 0.25W	01121	CB5625
R1905	315-0223-00			RES., FXD, CMPSN: 22K OHM, 5%, 0.25W	01121	CB2235
R1916	315-0123-00			RES., FXD, CMPSN: 12K OHM, 5%, 0.25W	01121	CB1235
R1917	315-0224-00			RES., FXD, CMPSN: 220K OHM, 5%, 0.25W	01121	CB2245
R1918	315-0154-00			RES., FXD, CMPSN: 150K OHM, 5%, 0.25W	01121	CB1545
R1919	321-0366-00			RES., FXD, FILM: 63.4K OHM, 1%, 0.125W	91637	MFF1816G63401F
R1921	315-0471-00			RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715
R1922	321-0313-00			RES., FXD, FILM: 17.8K OHM, 1%, 0.125W	91637	MFF1816G17801F
R1924	315-0560-00			RES., FXD, CMPSN: 56 OHM, 5%, 0.25W	01121	CB5605
R1925	315-0202-00			RES., FXD, CMPSN: 2K OHM, 5%, 0.25W	01121	CB2025
R1926	321-0035-00	B010100	B010289	RES., FXD, FILM: 22.6 OHM, 1%, 0.125W	91637	CMF1/10216G22R60
R1926	321-0038-00	B010290		RES., FXD, FILM: 24.3 OHM, 1%, 0.125W	91637	MFF1816G24R30F
R1940	311-1266-00			RES., VAR, NONWIR: 2.5K OHM, 10%, 0.50W	32997	3329P-L58-252
R1941	321-0393-00			RES., FXD, FILM: 121K OHM, 1%, 0.125W	91637	MFF1816G12102F
R1942	321-0283-00			RES., FXD, FILM: 8.66K OHM, 1%, 0.125W	91637	MFF1816G86600F
R1943	315-0201-00			RES., FXD, CMPSN: 200 OHM, 5%, 0.25W	01121	CB2015
R1944	321-0282-00			RES., FXD, FILM: 8.45K OHM, 1%, 0.125W	91637	MFF1816G84500F
R1945	315-0821-00			RES., FXD, CMPSN: 820 OHM, 5%, 0.25W	01121	CB8215
R1951	321-0421-00			RES., FXD, FILM: 237K OHM, 1%, 0.125W	91637	MFF1816G23702F
R1952	321-0692-00			RES., FXD, FILM: 49.9K OHM, 0.5%, 0.125W	91637	MFF1816G49901D
R1953	321-0306-00			RES., FXD, FILM: 15K OHM, 1%, 0.125W	91637	MFF1816G15001F
R1954	321-0314-00			RES., FXD, FILM: 18.2K OHM, 1%, 0.125W	91637	MFF1816G18201F
R1955	321-0314-00			RES., FXD, FILM: 18.2K OHM, 1%, 0.125W	91637	MFF1816G18201F
R1956	321-0289-00			RES., FXD, FILM: 10K OHM, 1%, 0.125W	91637	MFF1816G10001F
R1957	321-0289-00			RES., FXD, FILM: 10K OHM, 1%, 0.125W	91637	MFF1816G10001F
R1958	315-0471-00			RES., FXD, CMPSN: 470 OHM, 5%, 0.25W	01121	CB4715
R1959	315-0103-00			RES., FXD, CMPSN: 10K OHM, 5%, 0.25W	01121	CB1035
R2006	315-0513-00			RES., FXD, CMPSN: 51K OHM, 5%, 0.25W	01121	CB5135
R2007	315-0513-00			RES., FXD, CMPSN: 51K OHM, 5%, 0.25W	01121	CB5135
R2013	301-0130-00			RES., FXD, CMPSN: 13 OHM, 5%, 0.50W	01121	EB1305
R2021	315-0100-00			RES., FXD, CMPSN: 10 OHM, 5%, 0.25W	01121	CB1005
R2023	315-0150-00			RES., FXD, CMPSN: 15 OHM, 5%, 0.25W	01121	CB1505
R2025	315-0150-00			RES., FXD, CMPSN: 15 OHM, 5%, 0.25W	01121	CB1505
R2041	321-0184-00			RES., FXD, FILM: 806 OHM, 1%, 0.125W	91637	MFF1816G806ROF
R2042	316-0682-00			RES., FXD, CMPSN: 6.8K OHM, 10%, 0.25W	01121	CB6821
R2043	315-0101-00			RES., FXD, CMPSN: 100 OHM, 5%, 0.25W	01121	CB1015
R2044	315-0182-00			RES., FXD, CMPSN: 1.8K OHM, 5%, 0.25W	01121	CB1825
R2045	315-0182-00			RES., FXD, CMPSN: 1.8K OHM, 5%, 0.25W	01121	CB1825
R2046	301-0181-00			RES., FXD, CMPSN: 180 OHM, 5%, 0.50W	01121	EB1815
R2047	321-0690-00			RES., FXD, FILM: 34K OHM, 1%, 0.125W	91637	MFF1816G34001D
R2048	311-1264-00			RES., VAR, NONWIR: 1.5K OHM, 10%, 0.50W	32997	3329P-L58-152
R2049	321-0779-03			RES., FXD, FILM: 7.020K OHM, 0.25%, 0.125W	91637	MFF1816D70200C
R2051	321-1331-02			RES., FXD, FILM: 27.2K OHM, 0.5%, 0.125W	91637	MFF1816D27701D
R2052	321-0669-00			RES., FXD, FILM: 6.08K OHM, 0.5%, 0.125W	91637	MFF1816D60800D
R2056	308-0446-00			RES., FXD, WW: 15 OHM, 5%, 5W	91637	RS2A-K15R00J
R2061	321-0775-03			RES., FXD, FILM: 45K OHM, 0.25%, 0.125W	91637	MFF1816D45001C
R2062	321-0260-01			RES., FXD, FILM: 4.99K OHM, 0.5%, 0.125W	91637	MFF1816G49900D
R2071	315-0472-00			RES., FXD, CMPSN: 4.7K OHM, 5%, 0.25W	01121	CB4725
R2072	315-0331-00			RES., FXD, CMPSN: 330 OHM, 5%, 0.25W	01121	CB3315
R2073	315-0102-00			RES., FXD, CMPSN: 1K OHM, 5%, 0.25W	01121	CB1025
R2074	321-0692-00			RES., FXD, FILM: 49.9K OHM, 0.5%, 0.125W	91637	MFF1816G49901D

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
R2075	321-0260-01			RES., FXD, FILM: 4.99K OHM, 0.5%, 0.125W	91637	MFF1816G49900D
R2083	315-0181-00			RES., FXD, CMPSN: 180 OHM, 5%, 0.25W	01121	CB1815
R2084	321-0769-03			RES., FXD, FILM: 50.33K OHM, 0.25%, 0.125W	91637	MFF1816D50331C
R2085	321-0285-01			RES., FXD, FILM: 9.09K OHM, 0.5%, 0.125W	91637	MFF1816G90900D
R2086	316-0682-00			RES., FXD, CMPSN: 6.8K OHM, 10%, 0.25W	01121	CB6821
R2087	304-0390-00	B010100	B143849	RES., FXD, CMPSN: 39 OHM, 10%, 1W	01121	GB3901
R2087	303-0200-00	B143850		RES., FXD, CMPSN: 20 OHM, 5%, 1W	01121	CB2005
R2089	315-0395-00	B010100	B069999X	RES., FXD, CMPSN: 3.9M OHM, 5%, 0.25W	01121	CB3955
R2093	315-0390-00			RES., FXD, CMPSN: 39 OHM, 5%, 0.25W	01121	CB3905
R2094	307-0109-00			RES., FXD, CMPSN: 8.2 OHM, 5%, 0.25W	01121	CB82G5
R2096	323-0038-00			RES., FXD, FILM: 24.3 OHM, 1%, 0.50W	91637	MFF1226G24R30F
R2100	311-1223-00			RES., VAR, NONWIR: 250 OHM, 10%, 0.50W	32997	3386F-T04-251
R2101	315-0220-00			RES., FXD, CMPSN: 20 OHM, 5%, 0.25W	01121	CB2205
R2102	321-0021-00			RES., FXD, FILM: 16.2 OHM, 1%, 0.125W	24546	NA55D16R2F
R2105	311-1223-00			RES., VAR, NONWIR: 250 OHM, 10%, 0.50W	32997	3386F-T04-251
R2106	315-0201-00			RES., FXD, CMPSN: 200 OHM, 5%, 0.25W	01121	CB2015
R2107	321-0698-00			RES., FXD, FILM: 1.89K OHM, 0.25%, 0.125W	91637	MFF1816C18900C
R2108	321-0249-09			RES., FXD, FILM: 3.83K OHM, 1%, 0.125W	91637	MFF1816C38300F
R2109	321-0321-07			RES., FXD, FILM: 21.5K OHM, 0.1%, 0.125W	91637	MFF1816C21501B
R2111	315-0221-00			RES., FXD, CMPSN: 220 OHM, 5%, 0.25W	01121	CB2215
R2112	321-0321-07			RES., FXD, FILM: 21.5K OHM, 0.1%, 0.125W	91637	MFF1816C21501B
R2113	316-0152-00			RES., FXD, CMPSN: 1.5K OHM, 10%, 0.25W	01121	CB1521
R2116	321-0102-00			RES., FXD, FILM: 113 OHM, 1%, 0.125W	91637	MFF1816G113ROF
R2117	315-0150-00			RES., FXD, CMPSN: 15 OHM, 5%, 0.25W	01121	CB1505
R2120	317-0181-00			RES., FXD, CMPSN: 180 OHM, 5%, 0.125W	01121	BB1815
R2122	317-0271-00			RES., FXD, CMPSN: 270 OHM, 5%, 0.125W	01121	BB2715
R2124	317-0430-00			RES., FXD, CMPSN: 43 OHM, 5%, 0.125W	01121	BB4305
R2130	311-1223-00			RES., VAR, NONWIR: 250 OHM, 10%, 0.50W	32997	3386F-T04-251
R2131	323-0225-09			RES., FXD, FILM: 2.15 OHM, 1%, 0.50W	91637	MFF1226C21500F
R2132	323-0225-09			RES., FXD, FILM: 2.15 OHM, 1%, 0.50W	91637	MFF1226C21500F
R2133	321-0255-00			RES., FXD, FILM: 4.42K OHM, 1%, 0.125W	91637	MFF1816G44200F
R2134	321-0961-07			RES., FXD, FILM: 500.5 OHM, 0.1%, 0.125W	24546	NE55E500R5B
R2139	315-0100-00			RES., FXD, CMPSN: 10 OHM, 5%, 0.25W	01121	CB1005
RT551	307-0127-00			RES., THERMAL: 1K OHM, 10%	50157	2D1596
RT644	307-0126-00			RES., THERMAL: 100 OHM, 10%	14193	2D21-101K
RT1487	307-0124-00			RES., THERMAL: 5K OHM, 10%	50157	1D1618
RT1821	307-0353-00			RES., FXD, FILM: 5 OHM, 10%, DISC	15454	5DA5RO-K-270SS
RT1822	307-0353-00			RES., FXD, FILM: 5 OHM, 10%, DISC	15454	5DA5RO-K-270SS
S15	-----			SWITCH, CAM: COUPLING (S15, SEE MPL FOR REPLACEMENT PARTS)		
S90	-----			SWITCH, CAM: CAL IN (S90, SEE MPL FOR REPLACEMENT PARTS)		
S95	-----			SWITCH, CAM: VOLTS/DIV (S95, SEE MPL FOR REPLACEMENT PARTS)		
S125A, B	260-1314-00			SWITCH, PUSH: 1 BUTTON, 50 OHM/1M OHM (S125A, B, 485, 485-1 ONLY)	80009	260-1314-00
S125A, B	260-1492-00			SWITCH, PUSH: RESET (S125A, B, 485-2 ONLY)	80009	260-1492-00
S310	260-0816-01			SWITCH, SLIDE: DPDT, 0.5A, 125V	80009	260-0816-01
S600	260-1315-00			SWITCH, PUSH: BEAM FINDER/BW LIMIT	71590	2KBM020000-529
S630						
S700	260-1395-00			SWITCH, ROTARY: A SOURCE	82104	260-1395-00
S705	260-1312-00			SWITCH, LEVER: 1 SECT, 4 POSN, 22.5 DEG	80009	260-1312-00
S710	260-0735-00			SWITCH, PUSH: SPST (S710, 485 ONLY)	81073	39-1

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
S720	-----			(S720, FURNISHED AS A UNIT WITH R720)		
S780	260-1313-00			SWITCH, LEVER: 1 SECT, 4 POSN 22.5 DEG	80009	260-1313-00
S898	-----			(FURNISHED AS A UNIT WITH R898)		
S1000A, B	260-1311-00			SWITCH, LEVER: 1 SECT, 4 POSN, 22.5 DEG	80009	260-1311-00
S1005	260-1312-00			SWITCH, LEVER: 1 SECT, 4 POSN, 22.5 DEG	80009	260-1312-00
S1020	-----			(FURNISHED AS A UNIT WITH R1020)		
S1400	-----			(S1400, SEE MPL FOR REPLACEMENT PARTS)		
S1420	105-0281-00	B010100	B049999	ACTR ASSY, CAM S: A TIME/DIV AND DELAY TIME	80009	105-0281-00
S1420	105-0470-00	B050000		ACTR ASSY, CAM S: A B TIME/DIV AND A DELAY TIME	80009	105-0470-00
S1460	105-0335-00	B010100	B049999	ACTR ASSY, CAM S: B TIME/DIV	80009	105-0335-00
S1460	105-0470-00	B050000		ACTR ASSY, CAM S: A B TIME/DIV AND A DELAY TIME	80009	105-0470-00
S1500	260-1318-00			SWITCH, PUSH: 4 BUTTON, 2 POLE, INTERLOCK	80009	260-1318-00
S1580	260-1319-00			SWITCH, PUSH: 6 BUTTON, INTERLOCK	80009	260-1319-00
S1590	260-1317-00			SWITCH, PUSH: 3 BUTTON, 2 POLE, INTERLOCK	80009	260-1317-00
S1801	260-1368-01			SWITCH, SENS: SPST, 15A, 250VAC	77342	A1-M1-361-6-33
S1802	260-0638-00			SW, THERMOSTATIC: 10A, 240V, OPEN 75 DEG C	93410	110-364
S1803	260-1300-00			SWITCH, SLIDE:	82389	46206LFE
S2105	260-1208-00			SWITCH, PUSH: DPDT	80009	260-1208-00
T205	276-0614-00			CORE, FERRITE:	80009	276-0614-00
T305	276-0614-00			CORE, FERRITE:	80009	276-0614-00
T719	120-0797-00			XFMR, TOROID:	80009	120-0797-00
T1015	120-0797-00			XFMR, TOROID:	80009	120-0797-00
T1801	120-0716-00			XFMR, PWR, STPDN: LINE TRIGGER	80009	120-0716-00
T1825	120-0640-00			XFMR, TOROID: 18 TURNS, BIFILAR	80009	120-0640-00
T1831	120-0788-00			XFMR, TOROID: 4 WINDINGS	80009	120-0788-00
T1848	120-0747-00			XFMR, TOROID: 55 TURNS, SINGLE	80009	120-0747-00
T1960	120-0787-00			XFMR, PWR, SDN:	80009	120-0787-00
U48	156-0105-00			MICROCIRCUIT, LI: OPERATIONAL AMPLIFIER (U48, 485, 485-1 ONLY)	80009	156-0105-00
U80	155-0076-00			MICROCIRCUIT, LI: ML, INPUT PROTECTION	80009	155-0076-00
U210	155-0078-00	B010100	B143429	MICROCIRCUIT, LI: ML, VERT AMPL	80009	155-0078-00
U210	155-0078-10	B143430		MICROCIRCUIT, LI: ML, VERTICAL AMPLIFIER	80009	155-0078-10
U250	155-0078-03	B010100	B144129	MICROCIRCUIT, LI: ML, VERTICAL AMPL, SEL	80009	155-0078-03
U250	155-0078-13	B144130	B155949	MICROCIRCUIT, LI: ML, VERTICAL AMPL, SEL	80009	155-0078-13
U250	155-0078-10	B155950		MICROCIRCUIT, LI: ML, VERTICAL AMPLIFIER	80009	155-0078-10
U310	155-0078-00	B010100	B143429	MICROCIRCUIT, LI: ML, VERT AMPL	80009	155-0078-00
U310	155-0078-10	B143430		MICROCIRCUIT, LI: ML, VERTICAL AMPLIFIER	80009	155-0078-10
U332	156-0067-00			MICROCIRCUIT, LI: OPERATIONAL AMPLIFIER	80009	156-0067-00
U350	155-0078-03	B010100	B144129	MICROCIRCUIT, LI: ML, VERTICAL AMPL, SEL	80009	155-0078-03
U350	155-0078-13	B144130	B155949	MICROCIRCUIT, LI: ML, VERTICAL AMPL, SEL	80009	155-0078-13
U350	155-0078-10	B155950		MICROCIRCUIT, LI: ML, VERTICAL AMPLIFIER	80009	155-0078-10
U410	155-0078-01	B010100	B143429	MICROCIRCUIT, LI: ML, VERT AMPL, SEL	80009	155-0078-01
U410	155-0078-11	B143430	B155949	MICROCIRCUIT, LI: ML, VERTICAL AMPLIFIER, SEL	80009	155-0078-11
U410	155-0078-10	B155950		MICROCIRCUIT, LI: ML, VERTICAL AMPLIFIER	80009	155-0078-10
U430	155-0078-01	B010100	B143429	MICROCIRCUIT, LI: ML, VERT AMPL, SEL	80009	155-0078-01
U430	155-0078-11	B143430	B155949	MICROCIRCUIT, LI: ML, VERTICAL AMPLIFIER, SEL	80009	155-0078-11
U430	155-0078-10	B155950		MICROCIRCUIT, LI: ML, VERTICAL AMPLIFIER	80009	155-0078-10
U510	155-0078-01	B010100	B143429	MICROCIRCUIT, LI: ML, VERT AMPL, SEL	80009	155-0078-01
U510	155-0078-11	B143430	B155949	MICROCIRCUIT, LI: ML, VERTICAL AMPLIFIER, SEL	80009	155-0078-11
U510	155-0078-10	B155950		MICROCIRCUIT, LI: ML, VERTICAL AMPLIFIER	80009	155-0078-10
U530	155-0078-01	B010100	B143429	MICROCIRCUIT, LI: ML, VERT AMPL, SEL	80009	155-0078-01
U530	155-0078-11	B143430	B155949	MICROCIRCUIT, LI: ML, VERTICAL AMPLIFIER, SEL	80009	155-0078-11
U530	155-0078-10	B155950		MICROCIRCUIT, LI: ML, VERTICAL AMPLIFIER	80009	155-0078-10
U620	155-0078-01	B010100	B143429	MICROCIRCUIT, LI: ML, VERT AMPL, SEL	80009	155-0078-01
U620	155-0078-11	B143430	B155949	MICROCIRCUIT, LI: ML, VERTICAL AMPLIFIER, SEL	80009	155-0078-11
U620	155-0078-10	B155950		MICROCIRCUIT, LI: ML, VERTICAL AMPLIFIER	80009	155-0078-10

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
U650	155-0078-02	B010100	B143429	MICROCIRCUIT, LI:ML,VERT AMPL,SELECTED	80009	155-0078-02
U650	155-0078-03	B143430	B144129	MICROCIRCUIT, LI:ML,VERTICAL AMPL, SEL	80009	155-0078-03
U650	155-0078-12	B144130	B155949	MICROCIRCUIT, LI:ML,VERTICAL AMPLIFIER, SEL	80009	155-0078-12
U650	155-0078-10	B155950		MICROCIRCUIT, LI:ML,VERTICAL AMPLIFIER	80009	155-0078-10
U660	155-0064-00			MICROCIRCUIT, LI:OUTPUT AMPLIFIER	80009	155-0064-00
U730	155-0078-02	B010100	B143429	MICROCIRCUIT, LI:ML,VERT AMPL,SELECTED	80009	155-0078-02
U730	155-0078-03	B143430	B155949	MICROCIRCUIT, LI:ML,VERTICAL AMPL, SEL	80009	155-0078-03
U730	155-0078-10	B155950		MICROCIRCUIT, LI:ML,VERTICAL AMPLIFIER	80009	155-0078-10
U738	155-0078-02	B010100	B143429	MICROCIRCUIT, LI:ML,VERT AMPL,SELECTED	80009	155-0078-02
U738	155-0078-03	B143430	B155949	MICROCIRCUIT, LI:ML,VERTICAL AMPL, SEL	80009	155-0078-03
U738	155-0078-10	B155950		MICROCIRCUIT, LI:ML,VERTICAL AMPLIFIER	80009	155-0078-10
U740	155-0078-02	B010100	B143429	MICROCIRCUIT, LI:ML,VERT AMPL,SELECTED	80009	155-0078-02
U740	155-0078-03	B143430	B155949	MICROCIRCUIT, LI:ML,VERTICAL AMPL, SEL	80009	155-0078-03
U740	155-0078-10	B155950		MICROCIRCUIT, LI:ML,VERTICAL AMPLIFIER	80009	155-0078-10
U780	155-0049-00	B010100	B049999	MICROCIRCUIT, DI:SWEEP CONTROL	80009	155-0049-00
U780	155-0049-01	B050000	B144849	MICROCIRCUIT, DI:MONOLITHIC,SWEEP CONTROL	80009	155-0049-01
U780	155-0049-02	B144850		MICROCIRCUIT, DI:SWEEP CONTROL,W/LOCKOUT	80009	155-0049-02
U830	155-0078-02	B010100	B143429	MICROCIRCUIT, LI:ML,VERT AMPL,SELECTED (485 ONLY)	80009	155-0078-02
U830	155-0078-03	B143430	B155949	MICROCIRCUIT, LI:ML,VERTICAL AMPL, SEL (485 ONLY)	80009	155-0078-03
U830	155-0078-10	B155950		MICROCIRCUIT, LI:ML,VERTICAL AMPLIFIER (485 ONLY)	80009	155-0078-10
U910	156-0067-02	B010100	B149999	MICROCIRCUIT, LI:OPNL AMPLIFIER,SELECTED	80009	156-0067-02
U910	156-0067-00	B150000		MICROCIRCUIT, LI:OPERATIONAL AMPLIFIER	80009	156-0067-00
U960	156-0067-00			MICROCIRCUIT, LI:OPERATIONAL AMPLIFIER	80009	156-0067-00
U1030	155-0078-02	B010100	B143429	MICROCIRCUIT, LI:ML,VERT AMPL,SELECTED	80009	155-0078-02
U1030	155-0078-03	B143430	B155949	MICROCIRCUIT, LI:ML,VERTICAL AMPL, SEL	80009	155-0078-03
U1030	155-0078-10	B155950		MICROCIRCUIT, LI:ML,VERTICAL AMPLIFIER	80009	155-0078-10
U1038	155-0078-02	B010100	B143429	MICROCIRCUIT, LI:ML,VERT AMPL,SELECTED	80009	155-0078-02
U1038	155-0078-03	B143430	B155949	MICROCIRCUIT, LI:ML,VERTICAL AMPL, SEL	80009	155-0078-03
U1038	155-0078-10	B155950		MICROCIRCUIT, LI:ML,VERTICAL AMPLIFIER	80009	155-0078-10
U1040	155-0078-02	B010100	B143429	MICROCIRCUIT, LI:ML,VERT AMPL,SELECTED	80009	155-0078-02
U1040	155-0078-03	B143430	B155949	MICROCIRCUIT, LI:ML,VERTICAL AMPL, SEL	80009	155-0078-03
U1040	155-0078-10	B155950		MICROCIRCUIT, LI:ML,VERTICAL AMPLIFIER	80009	155-0078-10
U1480	156-0281-00			MICROCIRCUIT, LI:4 TRANSISTOR ARRAY	80009	156-0281-00
U1530	156-0047-00			MICROCIRCUIT, DI:TPL 3-INPUT POS NAND GATE	80009	156-0047-00
U1535	156-0041-00			MICROCIRCUIT, DI:DUAL D-TYPE FLIP-FLOP	27014	DM7474N
U1560	155-0012-00			MICROCIRCUIT, LI:ML,Z-AXIS AND AMPLIFIER	80009	155-0012-00
U1580	156-0030-00			MICROCIRCUIT, DI:QUAD 2-INPUT POS NAND GATE	01295	SN7400N
U1585	155-0011-00			MICROCIRCUIT, DI:ML,CLOCK AND CHOP BLANKING	80009	155-0011-00
U1600	152-0509-00			SEMICONV DEVICE:V MULTR,3KV IN,18KV OUT	80009	152-0509-00
U1624	156-0067-00			MICROCIRCUIT, LI:OPERATIONAL AMPLIFIER	80009	156-0067-00
U1710	155-0012-00			MICROCIRCUIT, LI:ML,Z-AXIS AND AMPLIFIER	80009	155-0012-00
U1910	155-0067-02			MICROCIRCUIT, DI:ML,POWER SUPPLY REGULATOR	80009	155-0067-02
U2042	156-0067-00			MICROCIRCUIT, LI:OPERATIONAL AMPLIFIER	80009	156-0067-00
U2052	156-0067-00			MICROCIRCUIT, LI:OPERATIONAL AMPLIFIER	80009	156-0067-00
U2062	156-0067-00			MICROCIRCUIT, LI:OPERATIONAL AMPLIFIER	80009	156-0067-00
U2072	156-0067-00			MICROCIRCUIT, LI:OPERATIONAL AMPLIFIER	80009	156-0067-00
U2086	156-0067-00			MICROCIRCUIT, LI:OPERATIONAL AMPLIFIER	80009	156-0067-00
V1700	154-0652-00	B010100	B091499	ELECTRON TUBE:CRT	80009	154-0652-00
V1700	154-0652-05	B091500		ELECTRON,TUBE:CRT	80009	154-0652-05
VR71	152-0395-00			SEMICONV DEVICE:ZENER,0.4W,4.3V,5% (VR71, 485,485-1 ONLY)	04713	1N749A
VR838	152-0127-00			SEMICONV DEVICE:ZENER,0.4W,7.5V,5% (VR838, 485 ONLY)	80009	152-0127-00

Replaceable Electrical Parts—485

Ckt No.	Tektronix Part No.	Serial/Model No. Eff	Dscont	Name & Description	Mfr Code	Mfr Part Number
VR839	152-0127-00			SEMICONV DEVICE:ZENER,0.4W,7.5V,5% (VR839, 485 ONLY)	80009	152-0127-00
VR844	152-0175-00			SEMICONV DEVICE:ZENER,0.4W,5.6V,5%	80009	152-0175-00
VR1131	152-0175-00			SEMICONV DEVICE:ZENER,0.4W,5.6V,5%	80009	152-0175-00
VR1549	152-0243-00			SEMICONV DEVICE:ZENER,0.4W,15V,5%	80009	152-0243-00
VR1740	152-0280-00			SEMICONV DEVICE:ZENER,0.4W,6.2V,5%	80009	152-0280-00
VR1831	152-0401-00			SEMICONV DEVICE:SILICON,3-LAYER,TRIGGER	04713	1N5761
VR1846	152-0287-00	B010100	B143554	SEMICONV DEVICE:ZENER,0.4W,110V,5%	04713	1N986B
VR1846	152-0657-00	B143555		SEMICONV DEVICE:ZENER,0.4W,108V,2%	04713	S2G20107
VR1912	152-0288-00			SEMICONV DEVICE:ZENER,0.4W,140V,5%	80009	152-0288-00
VR1928	152-0243-00	B010100	B029999	SEMICONV DEVICE:ZENER,0.4W,15V,5%	80009	152-0243-00
VR1928	152-0304-00	B030000		SEMICONV DEVICE:ZENER,0.4W,20V,5%	80009	152-0304-00
VR1945	152-0212-00			SEMICONV DEVICE:ZENER,0.5W,9V,5%	80009	152-0212-00
VR2042	152-0411-00			SEMICONV DEVICE:ZENER,0.25W,9V,5%	04713	1N937
VR2043	152-0283-00			SEMICONV DEVICE:ZENER,0.4W,43V,5%	80009	152-0283-00